

## 7. Electric Parts List

### 7-I. CT6846W (29 inch Only)

Loc No	New Code No	Old Code No	Description	Specification	Remark
<b>7-I -1. CT6846W/ASPCX (BUYER ; S.E.P.A Only)</b>					
			ASSY-PCB,MAIN		
	*AA97-10034X		ASSY-PCB,MAIN(COM)	CT6846W/ASPCX,KCT52A,SEPA	
01L0T1	AA41-10526A	36029-0590-000	PCB-MAIN	KCT52A,1L,FR-1,330X245X1.1	BARE PCB
C101	2401-000962	31607-402-260	C-AL	22UF,20%,50V,GP,5X11,5,TP	
C102	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C103	2401-001530	31607-401-670	C-AL	47UF,20%,25V,GP,5X11MM,5M	
C104	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7.	
C105	2401-001333	31607-402-200	C-AL	470UF,20%,50V,GP,5X11,5,T	
C106	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7.	
C107	2401-001333	31607-402-200	C-AL	470UF,20%,50V,GP,5X11,5,T	
C108	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C109	2401-001530	31607-401-670	C-AL	47UF,20%,25V,GP,5X11MM,5M	
C110	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C111	2201-000611	31407-105-280	C-CERAMIC,DISC	56PF,5%,50V,NPO,6.3X3,5,T	
C112	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C201	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7.	
C202	2301-000247	31507-127-009	C-FILM,PEF	33NF,5%,50V,8.1X4.5X13MM,	
C203	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C204	2401-000660	31607-402-220	C-AL	2.2UF,20%,50V,GP,5X11,5,T	
C205	2301-000223	31507-137-016	C-FILM,PEF	22NF,5%,100V,7.2X4.5X9.0M	
C206	2301-000192	31507-127-000	C-FILM,PEF	1NF,5%,50V,5.3X10MM,5MM,T	
C209	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C210	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C211	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C212	2301-000285	31507-127-010	C-FILM,PEF	47NF,5%,50V,7.5X4.0X6.5,5	
C213	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C214	2301-000380	31507-127-006	C-FILM,PEF	10NF,5%,50V,6.5X3MM,5MM,T	
C216	2201-000986	31407-105-110	C-CERAMIC,DISC	12PF,5%,50V,NPO,5X3.2,5MM	
C217	2201-000976	31407-105-180	C-CERAMIC,DISC	22PF,5%,50V,NPO,5.0X3.0,5	
C218	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C219	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C220	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C221	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C222	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C223	2201-000144	31407-105-660	C-CERAMIC,DISC	100PF,5%,50V,NPO,8.0X4.0,	
C224	2301-000264	31507-127-016	C-FILM,PEF	4.7NF,5%,50V,6.5X5.5X3.0X	
C225	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C226	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C227	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C228	2401-000660	31607-402-220	C-AL	2.2UF,20%,50V,GP,5X11,5,T	
C229	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C230	2202-000162	A1100-0824	C-CERAMIC,MLC-AXIAL	15PF,5%,50V,SL,3.5X19,-,T	
C231	2301-000201	31507-127-002	C-FILM,PEF	2.2NF,5%,50V,7.4X3.9X13MM	
C232	2301-000264	31507-127-016	C-FILM,PEF	4.7NF,5%,50V,6.5X5.5X3.0X	
C233	2401-000603	31607-402-210	C-AL	1UF,20%,50V,GP,5X11MM,5MM	

Loc No	New Code No	Old Code No	Description	Specification	Remark
C237	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C238	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C239	2401-000660	31607-402-220	C-AL	2.2UF,20%,50V,GP,5X11.5,T	
C240	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C241	2201-000483	31407-057-330	C-CERAMIC,DISC	33PF,5%,50V,NP0.5X3.5,5,T	
C242	2401-000480	31607-402-250	C - A L	10UF,20%,50V,GP,5X11MM,5M	
c244	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C249	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C251	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
c252	2401-000405	31607-803-120	C-AL	10UF,20%,16V,BP,6X11MM,5M	
C253	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C301	2202-000121	AI100-0798	C-CERAMIC,MLC-AXIAL	100PF,10%,50V,Y5P,1.9X3.5	
C302	2305-000708	A1102-0303	C-FILM,MPEF	150NF,5%,100V,16.5X10.3X5	
C303	2305-000149	A1102-0302	C-FILM,MPEF	100NF,5%,100V,7.5X4.0X5.0	
c304	2305-000149	A1102-0302	C-FILM,MPEF	100NF,5%,100V,7.5X4.0X5.0	
c305	2202-000173	AI100-0338	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,1.9X3.5,-	
C306	2401-001397	A1104-0012	C-AL	470UF,20%,25V,GP,10X16MM,	
C307	2401-001569	A1104-0512	C-AL	47UF,20%,50V,BP,10X12.5MM	
C308	2201-000108	31417-901-680	C-CERAMIC,DISC	1.5NF,10%,1KV,Y5P,-,5,TP	
C401*	2301-000148	31507-137-013	C-FILM,PEF	10NF,5%,100V,7X3.2X7MM,5M	
C402*	2306-000322	A1102-0212	C-FILM,MPPF	12NF,5%,1.6KV,28.5X20.5X1	
C404*	2306-000235	A1102-0409	C-FILM,MPPF	560NF,5%,400V,26X22.5X14,	
C405*	2305-000704	31517-390-502	C-FILM,MPEF	100NF,5%,250V,16.5X5.7X10	
C406	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C407	2401-001397	A1104-0012	C-AL	470UF,20%,25V,GP,10X16MM,	
C408	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C409	2401-001662	31607-403-070	C-AL	68UF,20%,100V,GP,10X16MM,	
C411	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C412	2401-000927	31607-403-500	C-AL	22UF,20%,250V,GP,13X20MM,	
C413	2401-000302	31607-401-680	C-AL	100UF,20%,25V,GP,6X11MM,5	
C414	2201-000984	31417-901-410	C-CERAMIC,DISC	680PF,10%,2KV,Y5P,-,7.5MM	
C415	2303-000331	A1102-0372	C-FILM,PPF	4.7NF,5%,630V,19.5X12X7.5	
C417	2201-000599	31417-468-561	C-CERAMIC,DISC	560PF,10%,500V,Y5P,6X4.5,	
C418	2401-001570	31607-402-470	C-AL	47UF,20%,50V,WT,10X20MM,5	
C419*	2306-000327	A1102-0348	C-FILM,MPPF	6.3NF,3%,1.6KV,31X17X10MM	
C601*	2202-000295	AI100-0797	C-CERAMIC,MLC-AXIAL	68PF,5%,50V,SL,3.5X19,-,T	
C603	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C604	2301-000198	31507-137-005	C-FILM,PEF	2.2NF,5%,100V,10.5X12.5X6	
C605	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C606	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C607	2301-000192	31507-127-000	C-FILM,PEF	1NF,5%,50V,5.3X10MM,5MM,T	
C608	2301-000301	31507-127-017	C-FILM,PEF	6.8NF,5%,50V,6.5X5.5X3.0X	
C609	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C610	2301-000301	31507-127-017	C-FILM,PEF	6.8NF,5%,50V,6.5X5.5X3.0X	
C611	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7.5X4.0X5.0M	
C612	2401-000587	31607-803-280	C-AL	1UF,20%,50V,BP,6X11MM,5MM	
C613	2401-000587	31607-803-280	C-AL	1UF,20%,50V,BP,6X11MM,5MM	
C614	2401-001397	A1104-0012	C-AL	470UF,20%,25V,GP,10X16MM,	
C615	2301-000320	31507-127-021	C-FILM,PEF	82NF,5%,50V,8.0X4.5X8.5MM	
C616	2201-000863	31417-104-270	C-CERAMIC,DISC	680PF,10%,50V,Y5P,5X5MM,5	
C617	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C618	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C619	2401-000947	31607-402-070	C-AL	22UF,20%,35V,GP,5X11MM,-,	
C620	2401-000947	31607-402-070	C-AL	22UF,20%,35V,GP,5X11MM,-,	
C623	2401-001026	31607-402-230	C-AL	3.3UF,20%,50V,GP,5X11MM,5	
C624	2401-001026	31607-402-230	C-AL	3.3UF,20%,50V,GP,5X11MM,5	
C625*	2201-000673	31417-104-170	C-CERAMIC,DISC	820PF,10%,50V,Y5P,4X3.5,5	
C626*	2201-000673	31417-104-170	C-CERAMIC,DISC	820PF,10%,50V,Y5P,4X3.5,5	
C627	2401-000706	31607-401-770	C-AL	2200UF,20%,25V,GP,16X25MM	
C632	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C633	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	

Loc No	New Code No	Old Code No	Description	Specification	Remark
C634	2401-001333	31607-402-200	C-AL	470UF,20%,50V,GP,5X11,5,T	
C637	2301-000192	31507-127-000	C-FILM,PEF	1NF,5%,50V,5,3X10MM,5MM,T	
C638	2401-000611	A1104-0524	C-AL	1UF,20%,50V,WT,5X11MM,5MM	
C640	2202-000819	A1100-0825	C-CERAMI C. MLC-AXI AL	47NF,+80-20%,50V,Y5V,3,5X	
C641	2202-000819	A1100-0825	C-CERAMI C. MLC-AXI AL	47NF,+80-20%,50V,Y5V,3,5X	
C701	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C702	2401-000460	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C703	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C704	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
c707	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C708	2401-000460	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C709	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C710	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C711	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7,5X4,0X5,0M	
C712	2401-002463	31607-401-500	C-AL	470UF,20%,16V,GP,10X12,5,	
△ C801	2401-001426	A1104-0538	C-AL	470UF,20%,400V,GP,35X45MM	
C802	2201-000332	31467-102-010	C-CERAMIC,DISC	2,2NF,20%,250V,Y5U,-,7,5M	
C803	2201-000332	31467-102-010	C-CERAMIC,DISC	2,2NF,20%,250V,Y5U,-,7,5M	
△ C804	2201-000446	31466-105-010	C-CERAMIC,DISC	3,3NF,20%,400V,Y5U,-,10MM	
C805	2201-000991	31417-901-400	C-CERAMIC,DISC	560PF,10%,2KV,Y5P,8X5,5,T	
△ C806	2401-001105	A1104-0526	C-AL	330UF,20%,200V,GP,22X35MM	
C807	2201-000599	31417-468-561	C-CERAMIC,DISC	560PF,10%,500V,Y5P,6X4,5,	
△ C808	2401-002288	A1104-0740	C-AL	470UF,20%,25V,GP,10X16MM,	
C809	2401-000287	A1104-0368	C-AL	100UF,20%,16V,WT,6X11MM,5	
△ C810	2401-000611	A1104-0524	C-AL	1UF,20%,50V,WT,5X11MM,5MM	
C811	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C812	2401-000287	A1104-0368	C-AL	100UF,20%,16V,WT,6X11MM,5	
△ C813	2401-001513	A1104-0461	C-AL	47UF,20%,16V,WT,5X11MM,5M	
△ C814	2305-000283	31569-201-230	C-FILM,MPEF	220NF,20%,250V,32X12,0X18	
C815	2401-000293	31607-403-990	C-AL	100UF,20%,200V,GP,16X26,7	
△ C816	2401-000166	A1104-0534	C-AL	1000UF,20%,25V,WT,13X20MM	
△ C817	2306-000324	A1102-0200	C-FILM,MPPF	3,3NF,5%,1,6KV,28,5X13,8X	
△ C818	2401-000493	A1104-0577	C-AL	10UF,20%,50V,WT,5X11MM,5M	
C819	2201-000599	31417-468-561	C-CERAMIC,DISC	560PF,10%,500V,Y5P,6X4,5,	
△ C820	2401-000166	A1104-0534	C-AL	1000UF,20%,25V,WT,13X20MM	
C821	2301-000192	31507-127-000	C-FILM,PEF	1NF,5%,50V,5,3X10MM,5MM,T	
C850	2401-000808	31607-401-480	C-AL	220UF,20%,16V,GP,8X11MM,5	
△ C851	2401-002289	A1104-0770	C-AL	470UF,20%,35V,GP,10X20MM,	
C852	2401-002461	31607-402-110	C-AL	220UF,20%,35V,GP,10X12,5,	
C853	2401-000395	31607-403-210	C-AL	10UF,20%,160V,GP,10X12,5M	
△ C854	2305-000407	A1102-0324	C-FILM,MPEF	470NF,5%,100V,-,5MM,TP	
C855	2201-000599	31417-468-561	C-CERAMIC,DISC	560PF,10%,500V,Y5P,6X4,5,	
C856	2401-000901	31607-403-220	C-AL	22UF,20%,160V,GP,10X20MM,	
△ C861	2401-000240	31607-401-840	C-AL	100UF,20%,10V,GP,6X11MM,5	
C862	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C901	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C902	2202-000173	A1100-0338	C-CERAMI C. MLC-AXI AL	1NF,10%,50V,Y5P,1,9X3,5,-	
C903	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C904	2202-000173	A1100-0338	C-CERAMI C. MLC-AXI AL	1NF,10%,50V,Y5P,1,9X3,5,-	
C905	2401-001333	31607-402-200	C-AL	470UF,20%,50V,GP,5X11,5,T	
C906	2201-000600	31417-104-560	C-CERAMIC,DISC	560PF,10%,50V,Y5P,4X3,5,5	
c907	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C908	2201-000573	31407-105-260	C-CERAMIC,DISC	47PF,5%,50V,NPO,6,5X3,0,5	
C909	2201-000193	31407-105-090	C-CERAMIC,DISC	10PF,0,3PF,50V,NPO,-,5,TP	
C910	2305-000665	A1102-0298	C-FILM,MPEF	100NF,5%,63V,7,5X4,0X5,0M	
C911	2401-000808	31607-401-480	C-AL	220UF,20%,16V,GP,8X11MM,5	
C912	2301-000380	31507-127-006	C-FILM,PEF	10NF,5%,50V,6,5X3MM,5MM,T	
C913	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7,	
C914	2202-000279	A1100-0796	C-CERAMI C. MLC-AXI AL	47PF,5%,50V,SL,3,5X19,-,T	
C819	2306-000222	A1102-0320	C-FILM,MPPF	47NF,5%,400V,-,15MM,BK	
C820	2303-000191	31509-335-170	C-FILM,PPF	270NF,5%,200V,30,5X19,5X1	

Loc No	New Code	Old Code	Description	Specification	Remark
CE014	2301-000380	31507-127-006	C-FILM,PEF	10NF,5%,50V,6.5X3MM,5MM,T	
CE024	2305-000407	A1102-0324	C-FILM,MPEF	470NF,5%,100V,-,5MM,TP	
CE034	2305-000407	A1102-0324	C-FILM,MPEF	470NF,5%,100V,-,5MM,TP	
CFN01*	AA29-10001B	37169-0002-000	FILTER-COMB	-,CFM102,NTSC,-	
CLAMP/F	AA65-30002A	33333-0005-010	CLAMP-FBT	-,NYLON-66,V0,BLK,-,-	
CLAMP/F	AA65-30009A	36633-101-911	CLAMP-FBT	-,ABS,V0,BLK,-,-	
CLAMP/W	AA65-30003A	33333-0011-000	CLAMP-WIRE	-,NYLON-66,V0,NTR,V-MODEL	
CLAMP/W	AA65-30010A	36634-111-010	CLAMP-WIRE	-,NYLON-66,V0,NTR,-,-	
CLAMP/W	AA65-30010B	36634-111-020	CLAMP-WIRE	-,NYLON-66,V0,NTR,-,-	
CLAMP/W	AA65-30018A	36635-112-010	CLAMP-WIRE	-,NYLON6.6,-,-,DATL-600.D	
CN502*	3711-002641	33347-110-410	CONNECTOR-HEADER	BOX,10P,1R,2.5MM,STRAIGHT	
CN601	3711-002643	33347-114-810	CONNECTOR-HEADER	BOX,4P,1R,2.5MM,STRAIGHT	
CN602*	3711-002644	33347-108-180	CONNECTOR-HEADER	BOX,5P,1R,2.5MM,STRAIGHT	
CN701*	3711-002648	33347-110-110	CONNECTOR-HEADER	BOX,9P,1R,2.5MM,STRAIGHT	
CN905*	3711-002644	33347-108-180	CONNECTOR-HEADER	BOX,5P,1R,2.5MM,STRAIGHT	
△ CNO1*	AA59-40001U	A1294-0057	MODULE-MTS	-,MZ-200,ZENITH,USA,54X44	
CNV02*	3711-002645	33347-108-140	CONNECTOR-HEADER	BOX,6P,1R,2.5MM,STRAIGHT	
CP01	2202-000109	A1100-0340	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5P,1.9	
CP02	2202-000109	A1100-0340	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5P,1.9	
CP03	2202-000109	A1100-0340	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5P,1.9	
CU024	2202-000109	A1100-0340	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5P,1.9	
cuo4	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CU05	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CU06	2401-000440	31607-401-430	C-AL	10UF,20%,25V,GP,5X11MM,5M	
CX014	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
△ D-COIL	AA27-20002B	A1149-0014	COIL-DEGAUSSING	-,29",13.30HM,70T,L3100,E	
D201	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D202	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
D203	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D204	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D205	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D206	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D207	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D208	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D401	0402-000493	32167-207-120	DIODE-RECTIFIER	1R5GU41,400V,1.5A,DO-15L	
D402	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
D403	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
△ D404	0402-000540	84102-0068	DIODE-RECTIFIER	RU20A,600V,1.5A,-	
D405	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D601	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D701	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D702	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
△ D8014	0402-000116	84104-0112	DIODE-BRIDGE	RBV606,600V,6A,-	
D802	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D804	0402-000213	32167-208-580	DIODE-RECTIFIER	ERB12-06,600V,1.0A,DO-41	
D805	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D806	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D8074	0402-000493	32167-207-120	DIODE-RECTIFIER	1R5GU41,400V,1.5A,DO-15L	
D808	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D813	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D814	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D815	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D903	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D908	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D910	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D951	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
D962	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D8024	0402-000533	B4114-0014	DIODE-RECTIFIER	FMP-3FU,600/1500V,5A,TO-2	
DU014	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
DU024	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
DU034	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	

Loc No	New Code No	Old Code No	Description	Specification	Remark
DU04*	0401-000005	32167-406-480	DI ODE-SWI TCH NG	1N4148, 100V, 200MA, 500MW, 4	
DX01*	0402-000546	32167-201-170	DI ODE- RECTI FI ER	TVR10G, 400V, 1.0A, D0-41	
△ DZ101	0403-000700	A4106-0227	DIODE-ZENER	TZP33A, 33V, 31-35V, 1W, D0-41	
△ DZ301	0403-000690	32167-406-140	DI ODE-ZENER	MTZ10C, 10V, 9.7-10.2V, 500M	
△ DZ302	0403-000690	32167-406-140	DI ODE-ZENER	MTZ10C, 10V, 9.7-10.2V, 500M	
△ DZ303	0403-000660	32167-406-200	DI ODE-ZENER	MTZ22A, 22V, 20.15-21.2V, 50	
△ DZ305*	0403-000700	A4106-0227	DI ODE-ZENER	TZP33A, 33V, 31-35V, 1W, D0-41	
△ DZ401	0403-000705	A4106-0205	DI ODE-ZENER	TZP8.2B, 8.2V, 8.2-9.3V, 1W, J	
02402	0403-000295	32167-406-080	DI ODE-ZENER	MTZ5.1B, 5.1V, 4.94-5.20V, 5	
△ DZ801	1405-000188	32167-401-041	VARI STOR	430V, 1250A, 14X7.5MM, TP	
△ DZ802	1405-000188	32167-401-041	VARI STOR	430V, 1250A, 14X7.5MM, TP	
△ DZ803	0403-000697	A4106-0237	DI ODE-ZENER	TZP10A, 10V, 9.4-10.6V, 1W, D	
DZ804	0403-000295	32167-406-080	DI ODE-ZENER	MTZ5.1B, 5.1V, 4.94-5.20V, 5	
△ DZ805	0403-000563	32167-406-130	DI ODE-ZENER	MTZ9.1B, 9.1V, 8.57-9.01V, 5	
△ DZ806	0403-000656	32167-403-780	DI ODE-ZENER	MTZ15C, 15V, 14.35-15.09V, 5	
DZ807	0403-000296	32167-401-800	DI ODE-ZENER	MTZ5.6B, 5.6V, 5.45-5.73V, 5	
DZ808	0403-000296	32167-401-800	DI ODE-ZENER	MTZ5.6B, 5.6V, 5.45-5.73V, 5	
DZ901	0403-000295	32167-406-080	DI ODE-ZENER	MTZ5.1B, 5.1V, 4.94-5.20V, 5	
DZ902	0403-000296	32167-401-800	DI ODE-ZENER	MTZ5.6B, 5.6V, 5.45-5.73V, 5	
DZ903	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
DZ904	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
DZ905	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
DZ906	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
DZ907	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
DZ908	0403-000297	32167-408-080	DI ODE-ZENER	MTZ6.2B, 6.2V, 5.96-6.27V, 5	
△ DZE01*	0403-000700	A4106-0227	DI ODE-ZENER	TZP33A, 33V, 31-35V, 1W, D0-41	
△ DX01*	0403-000667	A4106-0128	DI ODE-ZENER	MTZ6.8A, 6.8V, 6.29-6.63V, 5	
EYELET	AA60-40011A	33104-107-210	EYELET	ID2.0, 0D2.8, -, -, BST, -	EY401-EY857
EYELET	AA60-40011B	33104-107-220	EYELET	ID2.2, 0D3.2, -, -, BSP, -	EL301-EL859
△ F801	3601-001012		FUSE-FERRULE	250V, 4A, SLOW-BLOW, GLASS, 5	
F801A	3602-000114	33167-001-001	FUSE-HOLDER	-, -, 30MOHM	
F801B	3602-000114	33167-001-001	FUSE-HOLDER	-, -, 30MOHM	
GT102	AA39-20010B	33054-834-014	LEAD-CONNECTOR. ASSY	-, YFH800-01, S, 1P, 500, 1617	
△ HC101*	AA13-20004A		I C-HYBRID	-, PAP102, SIP, 6P, PRE-AMP	
△ HC801	AA13-20003B	A4010-0094	I C-HYBRID	-, FLO01T, SIP, 5P, SMPSI CONT	
△ HC802*	AA13-20003A	A4010-0093	I C-HYBRID	-, PCL001T, SIP, 5P, SMPSI CON	
IC101	1203-000298	A4008-0520	IC-POSITIVE FIXED REG.	7809, TO-220, 3P, -, PLASTIC J	
△ IC201	1204-000427	B4012-0609	IC-HOR./VER.PROCESSOR	TDA8377A, DIP, 56P, -, PLASTIC J	
△ IC202	1204-000506	B4012-0360	IC-IF DETECTOR	LA7510, SIP, 9P, -, PLASTIC, J	
△ IC602	0904-000004	B4012-0286	IC-PERIPHERAL	1853, -, DIP, 30P, -, -, ST, -, P	
IC701	1001-000215	32119-101-730	IC-ANALOG SWITCH	M51321P, CMOS, DIP, 18P, -, S	
△ IC851	0604-000117	32309-024-040	PHOTO-COUPLER	TR, 130-260%, 200MW, DIP-4, S	
△ IC852	1203-000580	32119-110-098	IC-POWER PRESCALER	130, TO-220, 3P, -, PLASTIC, J	
△ IC901	AA13-30010K		IC-MCU	-, Z8933212PSC-R2502, 16BIT	
IC902	1103-000189	B4000-0049	IC-EEPROM	24C02, 256X8BIT, DIP, 8P, 30Q	
J153*	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 24Q	
J233	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 24Q	
JA701	3722-000499	A3040-0198	JACK-RCA	9P(S), -, -, SN	
L-WRNG	AA68-50063X	38114-691-210	LABEL-WARNING	A/P120(S), TO.2, -, -, WHT, NT	
L102	2701-000197	32427-904-922	INDUCTOR-AXIAL	5.6UH, 10%, 2.5X3.4MM	
L103	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L104	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L130	2901-000296	A1247-0058	FILTER-EMI ON BOARD	-, -, -, 7	
L201	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L203	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L204	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L205	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L206	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L301	2701-000116	32427-805-882	INDUCTOR-AXIAL	10UH, 10%, 4.2X9.8MM	
△ L304*	AA27-10001B	32427-226-080	COIL-CHOKE	-, 1.0UH, K, 25, 2100A, T, SP04	
△ L305*	AA27-10001B	32427-226-080	COIL-CHOKE	-, 1.0UH, K, 25, 2100A, T, SP04	

Loc No	New Code No	Old Code No	Description	Specification	Remark
L401	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
△ L401*	AA27-30001N	A1150-0006I	COIL-LINEARITY	-,30UH,DR1415,P10,12X20,1	
L602	2701-000116	32427-805-882	INDUCTOR-AXIAL	10UH,10%,4.2X9.8MM	
LB02	AA29-30001N	32429-633-121	FILTER-LINE	-,6MH,1.54A,-,-	
△ LB04	2901-000296	A1247-0058I	FILTER-EMI ON BOARD	-, -, -, -	
L807	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
△ L808	2901-000296	A1247-0058I	FILTER-EMI ON BOARD	-, -, -, -	
△ L809	AA27-10002Y	B1133-0009	COIL-CHOKE	-,100UH,K,10,700MA,T,100U	
△ L810	AA27-10002Y	B1133-0009	COIL-CHOKE	-,100UH,K,10,700MA,T,100U	
△ L811	2901-000299	B1247-0057	FILTER-EMI ON BOARD	-,6A,UL/CSA,-	
△ L812	2901-000296	A1247-0058I	FILTER-EMI ON BOARD	-, -, -, -	
LB62	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
LB63	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
LB64	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
LB65	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240	
L901	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH,10%,2.5X3.4MM	
LQ02	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH,10%,2.5X3.4MM	
LB02*	AA27-40001E	32449-412-601	COIL-HORIZ.WIDTH	-,1.5MH,SB-5S820,2UEW0.6J	
LE01	AA27-40001E	32449-412-602	COIL-HORIZ.WIDTH	-,1MH,DR1520,P10,4,-	
LK803*	AA29-30001E	32429-627-010	FILTER-LINE	-,800UH,1.3A,-,HL38I	
NT0406	AA68-50067A	34503-0100-000	LABEL-RATING	T/P 90(G),T0.2,-,-,-,-,AL	
△ NT801	1404-000181	32189-609-381	THERMISTOR-NTC	4.7OHM,20%,2900K,-,BK	
△ PB01*	1404-000178	A1332-0017I	THERMISTOR-PTC	70HM,20%,-,290V,25A,-,BK	
PD801	AA39-10002C	33053-817D06C	POWER-CORD	DP,KKP-419C,VCTFK,1.8M,H0	
PD801	AA61-20050A	33323-0015-010	HOLDER-CORD	-,PP,V0,BLK,DO,-	
PIN-GT	AA60-40014A	33124-111-100	PIN-GT,ASSY	1P,-,-,-,AUTO	PIN-GT,ALL
Q201	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
Q203	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
Q204	0501-000283	32137-401-530	TR-SMALL SIGNAL	KSA539,PNP,-60V,-45V,-200	
Q251	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
△ Q402*	0502-001007		TR-POWER	KSC2073-H2,NPN,150V,150VJ	
Q601	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
Q701	0504-000123	A4060-0033	TR-DIGITAL	KSR1010,NPN,300MW,10K,T0-	
Q702	0504-000123	A4060-0033	TR-DIGITAL	KSR1010,NPN,300MW,10K,T0-	
△ Q801	0503-000153	A4058-0009	TR-DARLINGTON	TIP102,NPN,100V,100V,8A,2	
△ Q802*	0502-000244	A4052-0055I	TR-POWER	-,PNP,1.5W,T0-220,-,40-14	
Q901	0504-000123	A4060-0033	TR-DIGITAL	KSR1010,NPN,300MW,10K,T0-	
Q902	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
Q951	0501-000369	32137-301-560	TR-SMALL SIGNAL	KSC2331-Y,NPN,80V,60V,700	
QU03*	0504-000123	A4060-0033	TR-DIGITAL	KSR1010,NPN,300MW,10K,T0-	
QU05	0501-000283	32137-401-530	TR-SMALL SIGNAL	KSA539,PNP,-60V,-45V,-200	
QX01*	0501-000283	32137-401-530	TR-SMALL SIGNAL	KSA539,PNP,-60V,-45V,-200	
R102	2001-000221	31018-177-122	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8	
R103	2001-000563	31018-177-273	R-CARBON	27KOHM,5%,1/8W,AA,TP,1.8X	
R104	2001-000411	31018-177-183	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X	
△ R106	2003-000713	A1004-0428I	R-METAL OXIDE(S)	470HM,5%,2W,AD,TP,4X12MM	
R107	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R108	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R202	2001-000221	31018-177-122	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8	
R203	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
R204	2001-000793	31018-177-470	R-CARBON	470HM,5%,1/8W,AA,TP,1.8X3	
R205	2001-000490	31018-177-201	R-CARBON	2000HM,5%,1/8W,AA,TP,1.8X	
R206	2001-000869	31018-177-560	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3	
R208	2001-000674	31018-177-361	R-CARBON	3600HM,5%,1/8W,AA,TP,1.8X	
R209	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R210	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R211	2001-000397	31018-177-184	R-CARBON	180KOHM,5%,1/8W,AA,TP,1.8	
R212	2001-000832	31018-177-511	R-CARBON	5100HM,5%,1/8W,AA,TP,1.8X	
R213	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R214	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R215	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	

Loc No	New Code No	Old Code No	Description	Specification	Remark
R216	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R217	2001-000508	31018-177-224	R-CARBON	220KOHM, 5%, 1/8W, AA, TP, 1.8	
R219	2001-001113	31018-377-274	R-CARBON(S)	270KOHM, 5%, 1/2W, AA, TP, 2.4	
R222	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R223	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R224	2001-000780	31018-177-471	R-CARBON	4700HM, 5%, 1/8W, AA, TP, 1.8X	
R225	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R226	2001-000273	31018-177-104	R-CARBON	100KOHM, 5%, 1/8W, AA, TP, 1.8	
R227	2001-000745	31018-177-479	R-CARBON	4.7OHM, 5%, 1/8W, AA, TP, 1.8X	
R228	2004-001089	31018-177-564	R-METAL	560KOHM, 5%, 1/8W, AA, TP, 1.8	
R229	2004-001205	31018-177-680	R-METAL	680HM, 5%, 1/8W, AA, TP, 1.8X3	
R230	2001-000591	31018-177-332	R-CARBON	3.3KOHM, 5%, 1/8W, AA, TP, 1.8	
R231	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R232	2001-000440	31018-177-109	R-CARBON	10HM, 5%, 1/8W, AA, TP, 1.8X3	
R233	2001-000539	31018-177-243	R-CARBON	24KOHM, 5%, 1/8W, AA, TP, 1.8X	
R234	2001-000008	31018-177-153	R-CARBON	15KOHM, 5%, 1/8W, AA, TP, 1.8X	
R235	2001-000522	31018-177-223	R-CARBON	22KOHM, 5%, 1/8W, AA, TP, 1.8X	
R236	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R237	2001-001139	31018-377-393	R-CARBON(S)	39KOHM, 5%, 1/2W, AA, TP, 2.4X	
R239	2004-001104	31018-177-563	R-METAL	56KOHM, 5%, 1/8W, AA, TP, 1.8X	
R240	2004-001104	31018-177-563	R-METAL	56KOHM, 5%, 1/8W, AA, TP, 1.8X	
R241	2001-000454	31018-177-225	R-CARBON	2.2MOHM, 5%, 1/8W, AA, TP, 1.8	
R251	2004-001240	31018-177-750	R-METAL	750HM, 5%, 1/8W, AA, TP, 1.8X3	
R252	2004-001240	31018-177-750	R-METAL	750HM, 5%, 1/8W, AA, TP, 1.8X3	
R301	2001-000258	31018-177-182	R-CARBON	1.8KOHM, 5%, 1/8W, AA, TP, 1.8	
R304	2001-001184	31018-377-754	R-CARBON(S)	750KOHM, 5%, 1/2W, AA, TP, 2.4	
R305	2001-001184	31018-377-754	R-CARBON(S)	750KOHM, 5%, 1/2W, AA, TP, 2.4	
⚠ R306	2003-000998	A1004-0488	R-METAL OXIDE	3000HM, 5%, 2W, AF, TP, 3.9X10	
R307	2001-000016	31018-377-109	R-CARBON(S)	10HM, 5%, 1/2W, AA, TP, 2.4X6	
R308	2001-000016	31018-377-109	R-CARBON(S)	10HM, 5%, 1/2W, AA, TP, 2.4X6	
⚠ R309	2003-000998	A1004-0488	R-METAL OXIDE	3000HM, 5%, 2W, AF, TP, 3.9X10	
R403	2001-001114	31018-377-271	R-CARBON(S)	2700HM, 5%, 1/2W, AA, TP, 2.4X	
R404	2001-000117	31018-377-680	R-CARBON(S)	680HM, 5%, 1/2W, AA, TP, 2.4X6	
⚠ R405	2003-000540	A1004-0404	R-METAL OXIDE(S)	1KOHM, 5%, 2W, AD, TP, 4X12MM	
R407	2001-001153	31018-377-470	R-CARBON(S)	470HM, 5%, 1/2W, AA, TP, 2.4X6	
⚠ R408	2004-001390	31048-361-001	R-METAL(S)	1KOHM, 2%, 1/2W, AA, TP, 2.4X6	
⚠ R409	2008-000254	A1010-0085	R-FUSIBLE(S)	0.680HM, 5%, 2W, AF, TP, 3.9X1	
⚠ R410	2008-000206	AI010-0035	R-FUSIBLE(S)	10HM, 5%, 1/2W, AF, TP, 2.5X6	
⚠ R411	2004-001899	31047-356-193	R-METAL(S)	61.9KOHM, 1%, 1/2W, AA, TP, 2.	
⚠ R412	2001-001194	31018-377-823	R-CARBON(S)	82KOHM, 5%, 1/2W, AA, TP, 2.4X	
⚠ R413	2001-001037	A1000-0660	R-CARBON(S)	0.390HM, 5%, 1/2W, AA, TP, 2.4	
⚠ R415	2003-000993	A1004-0481	R-METAL OXIDE(S)	3.9KOHM, 5%, 1W, AF, TP, 2.5X6	
R416	2001-000613	31018-177-392	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
⚠ R417	2008-001003		R-FUSIBLE(S)	5.60HM, 5%, 1W, AF, TP, 3.9X10	
⚠ R450	2008-000266	A1010-0061	R-FUSIBLE(S)	10HM, 5%, 2W, AF, TP, 3.9X10MM	
R602	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R603	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R604	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R606	2004-001284	31018-177-824	R-METAL	820KOHM, 5%, 1/8W, AA, TP, 1.8	
R607	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R608	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R609	2001-000613	31018-177-392	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R610	2001-000734	31018-177-472	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
R611	2001-000281	31018-177-101	R-CARBON	4.7KOHM, 5%, 1/8W, AA, TP, 1.8	
R612	2001-000281	31018-177-101	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R613	2001-000313	31018-177-113	R-CARBON	1000HM, 5%, 1/8W, AA, TP, 1.8X	
R614	2001-000313	31018-177-113	R-CARBON	11KOHM, 5%, 1/8W, AA, TP, 1.8X	
R615	2001-000429	31018-177-102	R-CARBON	11KOHM, 5%, 1/8W, AA, TP, 1.8X	
R616	2001-000273	31018-177-104	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R618	2001-001146	31018-377-479	R-CARBON(S)	100KOHM, 5%, 1/8W, AA, TP, 1.8	
R619	2001-000522	31018-177-223	R-CARBON	4.70HM, 5%, 1/2W, AA, TP, 2.4X	
				22KOHM, 5%, 1/8W, AA, TP, 1.8X	



Loc No	New Code No	Old Code No	Description	Specification	Remark
R620	2001-000009	31018-177-203	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X	
R663	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
R667*	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R701	2001-001146	31018-377-479	R-CARBON(S)	4.7OHM,5%,1/2W,AA,TP,2.4X	
R705*	2001-001187	31018-377-750	R-CARBON(S)	750HM,5%,1/2W,AA,TP,2.4X6	
R708	2001-001187	31018-377-750	R-CARBON(S)	750HM,5%,1/2W,AA,TP,2.4X6	
R709	2001-001187	31018-377-750	R-CARBON(S)	750HM,5%,1/2W,AA,TP,2.4X6	
R712	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R713	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R714	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R715	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R716	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R717	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R718	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R719	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R720*	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R721*	2001-000085	31018-377-104	R-CARBON(S)	100KOHM,5%,1/2W,AA,TP,2.4	
R722	2001-000252	31018-177-162	R-CARBON	1.6KOHM,5%,1/8W,AA,TP,1.8	
R723	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R724	2001-000028	31018-377-101	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X	
R725	2001-000028	31018-377-101	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X	
⚠ R801*	2006-000334	A1008-0016	0.18OHM,10%,5W,CJ,TP,5.5X	110HM,5%,5W,CB,BK,9.5X13.	
⚠ R802	2001-001117	A1000-0586	R-CARBON(S)	2KOHM,5%,1/2W,AA,TP,2.4X6	
⚠ R803	2001-001117	A1000-0586	R-CARBON(S)	2KOHM,5%,1/2W,AA,TP,2.4X6	
R804	2001-001150	31018-377-474	R-CARBON(S)	470KOHM,5%,1/2W,AA,TP,2.4	
⚠ R805*	2002-000334	31028-328-825	R-COMPOSITION	8.2MOHM,10%,1/2W,AA,TP,3.	
R806	2001-001071	31018-377-123	R-CARBON(S)	12KOHM,5%,1/2W,AA,TP,2.4X	
R807	2001-001071	31018-377-123	R-CARBON(S)	12KOHM,5%,1/2W,AA,TP,2.4X	
R808	2001-001150	31018-377-474	R-CARBON(S)	470KOHM,5%,1/2W,AA,TP,2.4	
⚠ R809*	2003-000713	A1004-0428	R-METAL OXIDE(S)	470HM,5%,2W,AD,TP,4X12MM	
⚠ R810	2003-001023	A1004-0478	R-METAL OXIDE(S)	1200HM,5%,2W,AF,TP,3.9X10	
⚠ R811*	2003-000746	A1004-0427	R-METAL OXIDE(S)	560HM,5%,2W,AD,TP,4X12MM	
⚠ R812	2008-000251	A1010-0066	R-FUSIBLE(S)	0.27OHM,10%,2W,AF,TP,3.9X	
R813	2001-001078	31018-377-153	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X	
⚠ R814	2001-001117	A1000-0586	R-CARBON(S)	2KOHM,5%,1/2W,AA,TP,2.4X6	
⚠ R815*	2006-000294	A1014-0075	R-CEMENT	110HM,5%,5W,CB,BK,9.5X13.	
⚠ R816	2003-001093	A1004-0454	R-METAL OXIDE(S)	12KOHM,5%,2W,AF,TP,3.9X10	
⚠ R817	2003-000996	A1004-0491	R-METAL OXIDE(S)	8.2KOHM,5%,2W,AF,TP,3.9X1	
⚠ R818	2003-001090	A1004-0431	R-METAL OXIDE(S)	10KOHM,5%,2W,AF,TP,4X12MM	
⚠ R819	2003-001035	A1004-0437	R-METAL OXIDE(S)	270HM,5%,2W,AF,TP,2.4X6.4	
R820*	2001-001187	31018-377-750	R-CARBON(S)	750HM,5%,1/2W,AA,TP,2.4X6	
R821*	2001-001143	31018-377-432	R-CARBON(S)	4.3KOHM,5%,1/2W,AA,TP,2.4	
R822	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
R851*	2001-001143	31018-377-432	R-CARBON(S)	4.3KOHM,5%,1/2W,AA,TP,2.4	
R852*	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
⚠ R853*	2003-000592	A1004-0409	R-METAL OXIDE(S)	220HM,5%,2W,AD,TP,4X12MM	
R901	200 1-000793	31018-177-470	R-CARBON	470HM,5%,1/8W,AA,TP,1.8X3	
R902	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R903	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R904	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R905	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R906	2001-000472	31018-177-272	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8	
R907	2004-001291	31018-177-821	R-METAL	8200HM,5%,1/8W,AA,TP,1.8X	
R908	2001-000232	31018-177-132	R-CARBON	1.3KOHM,5%,1/8W,AA,TP,1.8	
R909	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R910	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R911	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R912	2001-000832	31018-177-511	R-CARBON	5100HM,5%,1/8W,AA,TP,1.8X	
R914	2001-000515	31018-177-221	R-CARBON	2200HM,5%,1/8W,AA,TP,1.8X	
R915	2001-000472	31018-177-272	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8	
R916	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	



Loc No	New Code No	Old Code No	Description	Specification	Remark
R917	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R919	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R920	2001-000734	31018-177-472	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8	
R921	2001-001062	31018-377-106	R-CARBON(S)	10MOHM,5%,1/2W,AA,TP,2.4X	
R922	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R923	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R924	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R925	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R926	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R927	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R928	2004-001104	31018-177-563	R-METAL	56KOHM,5%,1/8W,AA,TP,1.8X	
R930*	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
R931	2004-001201	31018-177-683	R-METAL	68KOHM,5%,1/8W,AA,TP,1.8X	
R932	2001-001062	31018-377-106	R-CARBON(S)	10MOHM,5%,1/2W,AA,TP,2.4X	
R933	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R934	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R935	2001-000832	31018-177-511	R-CARBON	510OHM,5%,1/8W,AA,TP,1.8X	
R951	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R952	2001-000472	31018-177-272	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8	
R953	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R954	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R955	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R956	2001-000734	31018-177-472	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8	
R957	2001-000117	31018-377-680	R-CARBON(S)	68OHM,5%,1/2W,AA,TP,2.4X6	
△ R958	2004-000152	31047-176-152	R-METAL	1.5KOHM,2%,1/8W,AA,TP,1.8	
R959	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R960	2001-000281	31018-177-101	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X	
R961	2001-000679	31018-177-363	R-CARBON	36KOHM,5%,1/8W,AA,TP,1.8X	
R962	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R963	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R964	2001-001088	31018-377-102	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6	
R965	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
△ RA01*	2003-001040	A1004-0466	R-METAL OXIDE(S)	47KOHM,5%,2W,AF,TP,3.9X10	
△ RA02*	2003-001040	A1004-0466	R-METAL OXIDE(S)	47KOHM,5%,2W,AF,TP,3.9X10	
△ RA03*	2003-001040	A1004-0466	R-METAL OXIDE(S)	47KOHM,5%,2W,AF,TP,3.9X10	
RA207*	2001-000674	31018-177-361	R-CARBON	3600HM,5%,1/8W,AA,TP,1.8X	
RB207	2001-000258	31018-177-182	R-CARBON	1.8KOHM,5%,1/8W,AA,TP,1.8	
RE01*	2001-001155	31016-377-5628	R-CARBON(S)	5.6KOHM,5%,1/2W,AA,TP,2.4	
RE02*	2001-001194	31018-377-823	R-CARBON(S)	82KOHM,5%,1/2W,AA,TP,2.4X	
RE03*	2001-000028	31018-377-101	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X	
△ RE04	2003-000762	A1004-0416	R-METAL OXIDE(S)	6.8OHM,5%,2W,AD,TP,4X12MM	
△ RE05*	2003-000762	A1004-0416	R-METAL OXIDE(S)	6.8OHM,5%,2W,AD,TP,4X12MM	
△ RE07*	2003-000762	A1004-0416	R-METAL OXIDE(S)	6.8OHM,5%,2W,AD,TP,4X12MM	
△ RL801	3501-000285	34729-004-0 10	RELAY-POWER	12V,-,10A,-,15MS.5MS	
△ RM901*	AA59-60003B		MODULE-REMOCON	-,SR-12V,38KHZ,940NM,MESH	
RN01*	2004-001291	31018-177-821	R-METAL	8200HM,5%,1/8W,AA,TP,1.8X	
RN10*	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
RN11*	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
△ RU01*	2002-000326	31028-328-185	R-COMPOSITION	1.8MOHM,10%,1/2W,AA,TP,3.	
RU02*	2001-000780	31018-177-471	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X	
RU03*	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
RU04	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
RU05	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
RU06	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
RU07	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
RU08*	2001-000005	31018-177-391	R-CARBON	3900HM,5%,1/8W,AA,TP,1.8X	
RU09*	2001-000005	31018-177-391	R-CARBON	3900HM,5%,1/8W,AA,TP,1.8X	
RU10*	2001-000005	31018-177-391	R-CARBON	3900HM,5%,1/8W,AA,TP,1.8X	
RU12	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
RU13	2001-000613	31018-177-392	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8	
RU14*	2004-001989	31018-177-621	R-METAL	6200HM,5%,1/8W,AA,TP,1.8X	

Loc No	New Code No	Old Code No	Description	Specification	Remark
RU15#	2004-001989	31018-177-621	R-METAL	6200HM,5%,1/8W,AA,TP,1.8X	
RU16#	2004-001989	31018-177-621	R-METAL	6200HM,5%,1/8W,AA,TP,1.8X	
RU17#	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
RU18	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
RU19	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
RX01#	2001-000397	31018-177-184	R-CARBON	180KOHM,5%,1/8W,AA,TP,1.8X	
RX02#	2004-001990	31018-177-623	R-METAL	62KOHM,5%,1/8W,AA,TP,1.8X	
RX03#	2001-000522	31018-177-223	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X	
RX04#	2001-000766	31018-177-433	R-CARBON	43KOHM,5%,1/8W,AA,TP,1.8X	
RX05#	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
△ RX06#	2008-000206	AI 010-0035	R-FUSIBLE(S)	10HM,5%,1/2W,AF,TP,2.5X6J	
SFI 01 *	2904-000287	B1245-0052	FILTER-SAW AV	45.75MHZ,SIP5P,ST	
SFI02	2904-000289	81245-0045	FILTER-SAW AV	45.75MHZ,SIP5P,STI	
△ SPK	3001-000190	34209-200-007	SPEAKER	5W,80HM,89DB,150HZI	
SPK	AA39-20505B		LEAD CONNECTOR- ASSY	- ,YSH025-04,REC,4P,600,80	
SW901#	3404-000244	B3018-0034	SWITCH-TACT	15V,20MA,90-170GF,7.5X7MM	
SW902#	3404-000244	B3018-0034	SWITCH-TACT	15V,20MA,90-170GF,7.5X7MM	
SW903*	3404-000244	B3018-0034	SWITCH-TACT	15V,20MA,90-170GF,7.5X7MM	
SW904#	3404-000244	B3018-0034	SWITCH-TACT	15V,20MA,90-170GF,7.5X7MM	
SW905*	3404-000244	83018-0034	SWITCH-TACT	15V,20MA,90-170GF,7.5X7MM	
SWN01#	3404-000291	A3018-0072	SWITCH-TACT	12V,50MA,160GF,8.4X22.7.S	
T201#	AA26-10005E	A1195-0028	TRANS-IF	- ,7MM,1F,0.136UH,7MM,27PF	
△ T401#	AA26-50001M	A1202-0008	HORIZ.DRIVE	- ,60MH,520UH,4UH,EI19,-	
△ T444#	AA26-30002K	A1201-0048	TRANS-FRYBACK	- ,FTH-29A001,29",130V	
△ T801#	AA26-20004E	A1206-0097	TRANS-SWITCHING	- ,80-260V,- ,ER534521,460U	
△ TU01#	AA40-10005B		TUNER-F/S	- ,TECC1080PK25A,NTSC/USAJ	
X202#	2801-000229	B1280-0116	CRYSTAL-UNIT	3.579545MHZ,30PPM,28-AAMJ	
X901	B1280-0219	3Y84-70052-010	CRYSTAL	32.768KHZ P3 20PPM	
Z201	34527-460-001		FILTER-CERAMIC	TPS4,5MCTF21	
Z601#	2903-000135	81243-0071	FILTER-CERAMIC	BP,4.5MHZ	
			ASSY-LED,GUIDE		
△ LD901#	*AA96-30001B	*3H77-00001-070	ASSY-LED,GUIDE	- ,AA61-50055A,DL-G5RGA,-	
			ASSY-H&SOUND		
△ IC601#	*AA96-60270A 1201-000484	*3Y81-00010-010 B4012-0418	ASSY-H/S,SOUND IC-POWER AMP	SOUND,AA62-30004P,TDA7266 7266,ZIP,15P,- ,DUAL,- ,PLA	
			ASSY-H/S,VERTI		
△ Q401#	*AA96-60271A 0502-000450	*3Y82-20080-010 32159-210-032	ASSY-H/S,VERTI TR-POWER	VERT,AA62-30002A,2SD1887Y 2SD1887YD,NPN,1500V,800V,	
			ASSY-H/S,VERTI		
△ IC301*	*AA96-60272A 1204-000426	*3Y82-20081-010 B4012-0607	ASSY-H/S,VERT IC-VERTICAL PROCESSO	VERT,AA62-300080,TDA8350Q TDA8350Q/N4,SIP,13P,- ,PLA	
			ASSY-H/S,POWER		
△ IC801#	*AA96-60273A AA13-20002K	*3Y83-20036-010 B4010-0042	ASSY-H/S,POWER IC-HYBRID	POWER,AA62-30004E,S6709,- -,STR-S6709,LF953,SIP,9PJ	
			ASSY-H/S,POWER		
△ D803	*AA96-60274A 0402-000233	● 3Y83-20037-010 32169-101-090	ASSY-H/S,POWER DIODE-RECTIFIER	POWER,AA62-30029A,FML-G12 FML-G12S,200V,5A,-	

Loc No	New Code No	Old Code No	Description	Specification	Remark
ASSY-H&POWER					
△ IC802	*AA96-60275A 1203-000575	● 3Y83-20038-010 64008-1162	ASSY-H/S,POWER IC-POS1,ADJUST,REG	POWER,AA62-30031A,TDA8133 8133,SIP,9P,-,PLASTIC,5/5	
ASSY-H/S,TR					
△ QE01*	*AA96-60278A 0502-000242	*3Y84-70049-010 A4052-0057	ASSY-H/S,TR TR-POWER	TR,AA62-30006C,KSA614-Y,- -,PNP,25W,T0-220,TP,40-24	
ASSY-H/S,TR					
△ IC853	*AA96-60279A 1203-000165	*3Y84-70050-010 A4008-1140	ASSY-H/S,TR IC-POS1,ADJUST,REG	TR,AA62-30013A,KA78R12,- 78R12,T0-220,3P,-,-,12V,-	
ASSY-H/S,TR					
△ D812*	● AA96-60280A 0402-000231	*3Y84-70051-010 84102-0074	ASSY-H/S,TR DIODE-RECTIFIER	TR,AA62-30013A,FMG-G26S,- FMG-G26S,600V,4A,T0-220F	
ASSY-H/S,TR					
△ D810	*AA96-60281A 0402-000564	*3Y84-70052-010 84102-0087	ASSY-H/S,TR DIODE-RECTIFIER	TR,AA62-30013D,FML-G22S,- FML-G22S,200V,10A,T0-220	
ASSY-ACCESSORY					
PLUG 8ATT MACH/TI RCA/CA USER/M USER/M BOOK/M	3721-000136 4301-000115 AA26-90001F AA39-40001F AA68-10752A AA68-10755A AA68-30004A	33324-101-120 34719-035-510 32759-115-050 33394-100-163  34729-0052-000	PLUG-CONVERSION BATTERY-MN TRANS-MATCHING CABLE-RCA MANUAL-USERS MANUAL-USERS MANUAL-800K	2P,4.0MM,N,N1 1.5V,-,AAA,44.5X10.5,HOLD -,3000HM/750HM,NTSC,40-89 -,RCA,150MM,0.12/10,WHT/R WP100,-,-,ENG KCT51A SEA. WP100,-,-,SPA KCT52A,CT-6 -,W/P120(G),-,SEPA,-,-	
ASSY-CRT					
△ CRT △ D/Y △ C/Y SP-DY	AA03-10007V AA27-50002V AA27-60001M AA63-60032B	B1320-0207 B1148-0029 A1155D0003 36814-101-921	CRT-COLOR DEFLECTION-YOKE MAGNET-CONVERGENCE SPACER-DY	-,A68KSA30X,+380MG,29",11 -,KY4UL465B/YG29VQAT,29"/ DP,NY-291,29.1MM -,NEOPRENE,-,BLK,VOL SL-10	
ASSY-PCB,CRT					
	*AA97-70001U	*3Y32-00046-010	ASSY-PCB,CRT	-,KCT52A,29",-,CT-6846	
03LOT	AA41-10459A	36029-0539-000	PCB-CRT	KP2,1,FR-1,330X245X1.6T	
△ C502	2305000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
C503	2401-000832	31607-401-690	C-AL	220UF,20%,25V,GP,8X11MM,5	
△ C504	2202-002005		C-CERAMIC,MLC-AXIAL	5.6PF,10%,50V,CH,1.9X3.5M	
△ C505	2202-002005		C-CERAMIC,MLC-AXIAL	5.6PF,10%,50V,CH,1.9X3.5M	
△ C506	2202-002005		C-CERAMIC,MLC-AXIAL	5.6PF,10%,50V,CH,1.9X3.5M	
C507	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C508	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C509	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5,	
C510	2401-001232	31607-403-480	C-AL	4.7UF,20%,250V,GP,10X12.5	
△ C511	2305-000410	31517-002-530	C-FILM,MPEF	470NF,5%,250V,21.5X7.9X13	
△ C512	2305-000410	31517-002-530	C-FILM,MPEF	470NF,5%,250V,21.5X7.9X13	

Loc No	New Code No	Old Code No	Description	Specification	Remark
C514	2201-000379	31417-109-220	C-CERAMIC,DISC	22NF,+80-20%,50V,Y5V,8.0X	
C515	2401-000430	31607-403-490	C-AL	10UF,20%,250V,GP,10X16,5J	
△ C516	2305-000410	31517-002-530	C-FILM,MPEFI	470NF,5%,250V,21.5X7.9X13	
C517	2201-000969	A1100-0831	C-CERAMIC,DISC	10NF,+80-20%,3KV,Y5V,-,10	
C519	2401-000832	31607-401-690	C-AL	220UF,20%,25V,GP,8X11MM,5	
△ C520	2305-000665	A1102-0298	C-FILM,MPEFI	100NF,5%,63V,7.5X4.0X5.0M	
CN501	3711-002641	33347-110-410	CONNECTOR-HEADER	BOX,10P,1R,2.5MM,STRAIGHT	
CN501	AA39-20025E	33058-015-016	LEAD-CONNECTOR,ASSY	-,67096-010,S,10P,400,100	
CNV02	3711-002645	33347-108-140	CONNECTOR-HEADER	BOX,6P,1R,2.5MM,STRAIGHT J	
CNV02	AA39-20027C	33058-017-020	LEAD-CONNECTOR,ASSY	-,67096-006,S,6P,500,1007	
D501	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
△ 0503	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,D0-41	
D504	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
0505	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
D506	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
0507	0401-000005	32167-406-480	DIODE-SWITCHING	1N4148,100V,200MA,500MW,4	
DZ501	0403-000655	32167-406-150	DIODE-ZENER	MTZ13A,13V,12.11-12.75V,5	
DZ502	0403-000662	32167-441-002	DIODE-ZENER	MTZ3.0B,3.0V,3.01-3.22V,5	
DZ503	0403-000655	32167-406-150	DIODE-ZENER	MTZ13A,13V,12.11-12.75V,5	
DZ504	0403-000655	32167-406-150	DIODE-ZENER	MTZ13A,13V,12.11-12.75V,5	
GT501	AA60-40014A	33124-111-100	PIN-GT,ASSY	1P,-,-,AUTO	
GT502	AA60-40014A	33124-111-100	PIN-GT,ASSY	1P,-,-,AUTO	
Q501	0501-000389	32137-301-720	TR-SMALL SIGNAL	KSC815-Y,NPN,60V,45V,200M	
R501	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
△ R502	2004-001397	A1006-0741	R-METAL(S)	4.7KOHM,1%,1/2W,AA,TP,2.4	
△ R503	2004-001402	A1006-0672	R-METAL(S)	6.8KOHM,1%,1/2W,AA,TP,2.4	
R505	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R506	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
R507	2001-000449	31018-177-222	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8	
△ R508	2004-001970	A1006-1005	R-METAL(S)	1.8KOHM,1%,1/2W,AA,TP,6.5	
△ R509	2004-001970	A1006-1005	R-METAL(S)	1.8KOHM,1%,1/2W,AA,TP,6.5	
△ R510	2004-001970	A1006-1005	R-METAL(S)	1.8KOHM,1%,1/2W,AA,TP,6.5	
△ R511	2004-002011	31049-375-114	R-METAL(S)	110KOHM,1%,1/2W,AA,TP,2.4	
△ R512	2004-002011	31049-375-114	R-METAL(S)	110KOHM,1%,1/2W,AA,TP,2.4	
△ R513	2004-002011	31049-375-114	R-METAL(S)	110KOHM,1%,1/2W,AA,TP,2.4	
R514	2001-000490	31018-177-201	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X	
R515	2001-000490	31018-177-201	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X	
R516	2001-000490	31018-177-201	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X	
△ R517	2002-000327	31028-328-272	R-COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
△ R518	2002-000327	31028-328-272	R-COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
△ R519	2002-000327	31028-328-272	R-COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
R520	2001-000096	31018-377-105	R-CARBON(S)	1MOHM,5%,1/2W,AA,TP,2.4X6	
R522	2001-000037	31018-377-331	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X	
△ R523	2008-000299	A1010-0094	R-FUSIBLE	470HM,5%,2W,AF,TP,3.9X10M	
△ R524	2002-000330	31028-328-472	R-COMPOSITION	4.7KOHM,10%,1/2W,AA,TP,3J	
△ R525	2008-000266	A1010-0061	R-FUSIBLE(S)	1OHM,5%,2W,AF,TP,3.9X10MM	
R526	2001-000281	31018-177-101	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X	
△ VQ00	3704-000111		SOCKET-CRT	10P,29.1PI,35.5PI,AU	
			ASSY-H/S,TR		
△ IC501	● AAQ6-60277A 1201-000506	*3Y84-70048-010 32119-110-111	ASSY-H/S,TR IC-VIDEO AMP	TR,AA61-10060A,TDA6101Q,- 6101,ZIP,9P,-,SINGLE,-,PL	
			ASSY-H/S,TR		
△ IC502	● AAQ6-60277A 1201-000506	*3Y84-70048-010 32119-110-111	ASSY-H/S,TR IC-VIDEO AMP	TR,AA61-10060A,TDA6101Q,- 6101,ZIP,9P,-,SINGLE,-,PL	

Loc No	New Code No	Old Code No	Description	Specification	Remark
ASSY-H/S,TR					
△ IC503	*AA96-60277A 1201-000506	*3Y84-70048-010 32119-110-111	ASSY-H/S,TR IC-VIDEO AMP	TR,AA61-10060A,TDA6101Q,- 6101,ZIP,9P,-,SINGLE,-,PL	
ASSY-PCB A/M					
	● 1/16 5/16 3/8 1/2 5/8 3/4 1		ASSY-PCB A/M	-, -, KCT52A, -, -, 21-29", SMX	
PC8	AA41-10329A	36029-0369-000	PCB-F/AM	KV2,1,FR-1,245X245X1.6T	BARE PCB
BAND-W	AA63-10002A	36634-111-110	BAND-TIE	-, NYLON66 V2, -, -, L100, NTR	
CE60	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
CE61	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
CN602B	AA39-20069D	36434-0009-040	LEAD-CONNECTOR, ASSY	-, YBNH025-05, 67096-005, 5P	
CN701B	AA39-20112D	36434-0089-030	LEAD-CONNECTOR, ASSY	-, YBNH025-09, 67096-009, 9P	
JB01	3722-001031		JACK- RCA	3P, 3.6MM, #18, AU	
JE60	3722-000143	33339-521-070	JACK- PHONE	1P, 3.4MM, MBAG, BLACK, -	
RE60	2001-001077	31018-377-151	R- CARBON(S)	1500HM, 5%, 1/2W, AA, TP, 2.4X	
RE61	2001-001077	31018-377-151	R- CARBON(S)	1500HM, 5%, 1/2W, AA, TP, 2.4X	
REMOCON					
	*AA59-10032F		REMOCON	-, TM48, RM292EV, 37, WHT, SS	
ASSY-CABINET					
CB+CF	6002-000514	37148-540-153	SCREW- TAPPING	RH, +, 2, M4, L15, ZPC(BLK), SW	
CB+RCAL	6002-000514	37148-540-153	SCREW- TAPPING	RH, +, 2, M4, L15, ZPC(BLK), SW	
KC+CF	6002-000514	37148-540-153	SCREW- TAPPING	RH, +, 2, M4, L15, ZPC(BLK), SW	
RMC+CF	6002-000514	37148-540-153	SCREW- TAPPING	RH, +, 2, M4, L15, ZPC(BLK), SW	
SPK+CF	6002-000514	37148-540-153	SCREW- TAPPING	RH, +, 2, M4, L15, ZPC(BLK), SW	
PA+CF	AA60-10002A	37144-001-210	SCREW- TAPPING	RH, +, M4, L12, ZPC(YEL), -, 0D	
CRT+CF	AA60-10050D		SCREW- ASSY	WC, HH, +, M5, L35, SWRCH18, -	
SUPPORT	AA61-40042A	33073-0016-000	SUPPORT- CRT	-, HIPS, VO, BLK, -, -, 6846	
STOPPER	AA61-40053A	33383-0004-000	STOPPER- PCB	-, HIPS, HB, -, WHT, ALL MODEL	
SPRG- CS	AA61-60003E	36674-137-820	SPRING- CS	-, -, SUS304, 0.5, 0D8, H9, N5J	
GRI /WOOF	AA63-50290A		' GRILLE- WOOFER. R	DP, -, -, -, AA63-50189A, 68	
GRI /WOOF	AA63-50290B		GRILLE- WOOFER, L	DP, -, -, -, AA63-50189B, 68	
SP- FELT	AA63-60001Q	36844-112-360	SPACER- FELT	-, FELT, TO.35, -, 150X8, -	
WIN/RE	AA64-40241A	34073-0109-000	WINDOW-REMOCON	-, PC, -, -, -, 6845, 46, -	
IND/LED	AA64-40247A	34163-0062-000	INDICATOR- LED	-, ACRYL, HB, -, -, 6845, 46, -	
IN- BACK	AA64-60052B	34012-0207-020	INLAY- BACK	-, PS, TO.5, -, BLK, KP2 USA, -	
IN- AV	AA64-60278B		INLAY- AV	-, PS, TO.3, -, BLK, GOLD NTSC	
BAOGE	AA64-70010C	34533-0074-020	BADGE- BRAND	-, AL, -, L50, GOLD, FLAT SS 2	
CLAMP/C	AA65-30008A	36633-101-610	CLAMP- CORD	-, PE, HB, BLK, -, -	
CLAMP/W	AA65-30010A	36634-111-010	CLAMP- WI RE	-, NYLON-66, VO, NTR, -, -	
CLAMP, D	AA65-30017A	36635-002-010	CLAMP-D, COIL	-, NYLON-66, VO, NTR, DADH300	

Loc No	New Code No	Old Code No	Description	Specification	Remark
--------	-------------	-------------	-------------	---------------	--------

## 7-I -2. CT6846W/ASEMCM (BUYER ; S.E.M Only)

			ASSY-PCB,MAIN	
			ASSY-PCB,MAIN(COM)	CT6846W/ASEMCM,KCT52A,SEM
	● AA97-10035c			
△ P801*	1404-000177		THERMISTOR-PTC	50HM,20%,100V,125V,24A,-J
R663*	2001-000273		R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8
△ R805*	2202-000331		R-COMPOSITION	4.7MOHM,10%,1/2W,AA,TP,3J
C804*	2201-000954		C-CERAMIC,DISC	4.7NF,20%,400V,Y5U,7X16,1
C801*	2401-001386		C-AL	470UF,20%,250V,GP,25X40MM
△ D-COIL	AA27-20001N		COIL-DEGAUSSING	-.29",90HM,50T,L3200,E
L801*	AA29-30001K		FILTER-LINE	-.3,0MH,1.75A,-,-
PD801	AA39-10002D		POWER-CORD	DP,DW-006,SPC2,2.1M,HOUSJ
NT0405	AA68-50067A		LABEL-RATING	T/P 90(G),TO.2,-,-,-,-,AL
			ASSY-ACCESSORY	
USER/M	AA68-10893A		MANUAL- USERS	KCT52A,WP100,-,SPA,SEM,-J
CARD/W	AA68-40025A		CARD- WARRANTY	-,W/P 100(G),-,WHT,SEM,-J

## 7-I-3. CT6846W/AGECM (BUYER ; G/SUPPLY Only)

			ASSY-PCB,MAIN	
			ASSY-PCB,MAIN(COM)	CT6846W/AGECM,KCT52A,G/SU
	*AA97-10034Y			
△ C814	2306-000159		C-FILM,MPPF	220NF,20%,250V,-,22.5MM,B
△ R801*	31035-578-168		R-METAL,PLATE	MPC,71,0.18,K,(5W:0.18)
NT0409	AA68-50067A		LABEL-RATING	T/P 90(G),TO.2,-,-,-,-,AL



## 7-2.CT6346W (25 Inch) ; CT6846W and CT6346W Sisimilar Parts

Lot No	New Code No	Description	Specification	Remark
<b>7-2-I. CT6346W/ASPCX (BUYER ; S.E.P.A Only)</b>				
<b>ASSY-PCB,MAIN</b>				
	<b>*AA97-10034Z</b>	<b>ASSY-PCB,MAIN(COM)</b>	<b>CT6346W/ASPCX,KCT52A,SEPA</b>	
△ C402*	2306-000355	C-FILM,MPPF	7.4NF,5%,1.6KV,28.5X18.5X	
△ C404*	2306-000231	C-FILM,MPPF	510NF,5%,.250V,26X19X11.5J	
△ C419*	2306-000326	C-FILM,MPPF	4.7NF,5%,1.6KV,28.5X16X9M	
△ D-C01L	<b>AA27-20002C</b>	COIL-OEGAUSSING	-.25",14.30HM,70T,L2770,EL	
J15G	3301-000287	CORE-FERRITE 8EA0	AA,3.5X1.0X6.0MM,1500.24Q	
J233	3301-000287	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500.24Q	
NT0401	<b>AA68-50067A</b>	LABEL-RATING	T/P 90(G),T0.2,-,-,-,AL	
R211	2001-000004	R-CARBON	200KOHM,5%,1/8W,AA,TP,1.8	
R219*	2001-001150	R-CARBON(S)	470KOHM,5%,1/2W,AA,TP,2.4	
△ R411*	2004-001408	R-METAL(S)	91KOHM,1%,1/2W,AA,TP,2.4X	
△ R801*	31035-578-188	R-METAL,PLATE	MPC,71,0.18,K,(5W:0.18)	
<b>ASSY-H/S,MAIN</b>				
△ Q401*	<b>*AA96-60350A</b> 0502-000209	<b>ASSY-H/S,MAIN</b> TR-POWER	<b>MAIN,AA62-30002A,2SD1880,</b> 2SD1880,NPN,1500V,800V,8A	
<b>ASSY-CRT</b>				
ADHES	0201-000281	ADHESIVE-RBFI	D-5250,YEL,6000CPS+-500	
△ D/Y	<b>AA27-50002U</b>	DEFLECTION-YOKE	-.DAJ5012M,26"/A63LAV11XJ	
△ CRT	81320-0210	CRT-COLOR	A63AFW32X 261NCH 100DEG 3	
<b>ASSY-PCB,CRT</b>				
	<b>*AA97-70004A</b>	<b>ASSY-PCB,CRT</b>	<b>-.KCT52A,25",-.CT-6346</b>	
R511	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4	
R512	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4	
R513	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4	
△ R525	2008-000290	R-FUSIBLE	2.40HM,5%,2W,AF,TP,3.9X10	
<b>ASSY-CABINET</b>				
HOLD/CI	<b>AA61-20044A</b>	HOLDER-CLAMPER	-.NYLON-66,V0,NTR,-,-,I	
GRILL/WOOD	<b>AA63-50191A</b>	GRILLE-WOOFER,R	DP,-,-,-,I,AA63-50190A,63	
GRILL/WOOD	<b>AA63-50291B</b>	GRILLE-WOOFER,L	OP,-,-,-,I,AA63-50190B,63	
SPA,GUM	<b>AA63-60004L</b>	SPACER-GUM,CRT	-.NTR RUBBER,T3.0,BLK,NEW	
WIN/REI	<b>AA64-40242A</b>	WINDOW-REMOCON	-.PC,-,-,-,6345.46,-I	
IND/LED	<b>AA64-40248A</b>	INDICATOR-LEO	-.ACRYL.HB,-,-,6345.46,-I	

Loc	No	New Code No	Description	Specification	Remark
-----	----	-------------	-------------	---------------	--------

## 7-2-2. CT6346W/ASEMCX (BUYER : S.E.M Only)

### ASSY-PCB,MAIN(COM)

	● AA97-100358	ASSY-PCB,MAIN(COM)	CT6346W/ASEMCX,KCT52A,SEM
⚠ C402*	2306-000355	C-FILM,MPPF	7.4NF,5%,1.6KV,28.5X18.5X
⚠ C404*	2306-000231	C-FILM,MPPF	510NF,5%,250V,26X19X11.5J
⚠ C419*	2306-000326	C-FILM,MPPF	4.7NF,5%,1.6KV,28.5X16X9M
⚠ C801*	2401-001386	C-AL	470UF,20%,250V,GP,25X40MM
⚠ C804*	2201-000954	C-CERAMIC,DISC	4.7NF,20%,400V,Y5U,7X16,1
⚠ D-COIL	AA27-20001W	COIL-DEGAUSSING	- ,25" ,7.5OHM,33T,L2800,EL
J153	3301-000287	CORE-FERRITE 8EAD	AA,3.5X1.0X6.0MM,1500,240
J233	3301-000287	CORE-FERRITE 8EAD	AA,3.5X1.0X6.0MM,1500,240
L801*	AA29-30001K	FILTER-LINE	- ,3.0MH,1.75A,- ,1
NT0400	AA68-50067A	LABEL-RATING	T/P 90(G),TO,2,- ,-, -,AL
P801*	1404-000177	THERMISTOR-PTC	50HM,20%,100V,125V,24A,-J
PD801	AA39-10002D	POWER-CORD	DP,DW-006,SPC2,2.1M,HOUSJ
R211	2001-000004	R-CARBON	200KOHM,5%,1/8W,AA,TP,1.8
R219*	2001-001150	R-CARBON(S)	470KOHM,5%,1/2W,AA,TP,2.4
⚠ R411*	2004-001408	R-METAL(S)	91KOHM,1%,1/2W,AA,TP,2.4X
R667	2001-000290	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X
⚠ R801*	31035-578-188	R-METAL,PLATE	MPC,71.0.18,K,(5W:0.18)
⚠ R805*	2002-000331	R-COMPOSITION	4.7MOHM,10%,1/2W,AA,TP,3J
⚠ TU01	AA40-10005B	TUNER-F/S	- ,TECC1080PK25A,NTSC/USAJ

### ASSY-H/S,MAIN

⚠ Q401*	● AA96-60350A 0502-000209	ASSY-H/S,MAIN TR-POWER	MAIN,AA62-30002A,2SD1880J 2SD1880,NPN,1500V,800V,8A
---------	------------------------------	---------------------------	--

### ASSY-ACCESSORY

USER/M CARD/W	AA68-10893A AA68-40025A	MANUAL-USERS CARD-WARRANTY	KCT52A,WP100,- ,SPA,SEM,- -,W/P 100(G),-,WHT,SEM,-
------------------	----------------------------	-------------------------------	---

### ASSY-CRT

⚠ CRT	81320-0210	CRT-COLOR	A63AFW32X 261NCH 100DEG 3
⚠ ADHE	0201-000281	ADHESIVE-RBPI	D-5250,YEL,6000CPS+500
⚠ D/Y	AA27-50002U	DEFLECTION-YOKE	- ,DAJ5012M,26"/A63LAV11XJ

### ASSY-PCB,CRT

	● AA97-70004A	ASSY-PCB,CRT	- ,KCT52A,25" ,-,CT-6346
R511	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
R512	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
R513	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
⚠ R525	2008-000290	R-FUSIBLE	2.4OHM,5%,2W,AF,TP,3.9X10

### ASSY-CABINET(COM)

HOLD/C	AA61-20044A	HOLDER-CLAMPER	- ,NYLON-66,V0,NTR,- ,1
GR1/WOOD	AA63-50291A	GRILLE-WOOFER,P	DP,- ,-, -,AA63-50190A,63
GR /WOOD	AA63-50291B	GRILLE-WOOFER,L	DP,- ,-, -,AA63-50190B,63
SPA,GUM	AA63-60004L	SPACER-GUM,CRT	- ,NTR RUBBER,T3.0,BLK,NEW
WIN/RE	AA64-40242A	WINDOW-REMOCON	- ,PC,- ,-, -,6345,46,-1
IND/LED	AA64-40248A	INDICATOR-LED	- ,ACRYL,HB,- ,-,6345,46,-1

Loc No	New Code No	Description	Specification	Remark
--------	-------------	-------------	---------------	--------

### 7-2-3. CT6346W/AGECX (BUYER ; G/SUPPLY Only)

#### ASSY-PCB,MAIN

	*AA97-10035A	ASSY-PCB,MAIN(COM)	CT6346W/AGECX,KCT52A,SAMT
△ C402*	2306-000355	C-FILM,MPPF	7.4NF,5%,1.6KV,28.5X18.5X
△ C404*	2306-000231	C-FILM,MPPF	510NF,5%,250V,26X19X11.5,
△ C419*	2306-000326	C-FILM,MPPF	4.7NF,5%,1.6KV,28.5X16X9MM
△ C814	2306-000159	C-FILM,MPPF	220NF,20%,250V,-,22.5MM,8
△ D-COIL	AA27-200020	COIL-DEGAUSSING	-,25",14.30HM,70T,L2770,E
NT0407	AA68-50067A	LABEL-RATING	T/P 90(G),TO.2,-,-,-,AL
R211	2001-000004	R-CARBON	200KOHM,5%,1/8W,AA,TP,1.8
R219*	2001-001150	R-CARBON(S)	470KOHM,5%,1/2W,AA,TP,2.4
△ R411*	2004-001408	R-METAL(S)	91KOHM,1%,1/2W,AA,TP,2.4X
△ R450*	2008-000290	R-FUSIBLE	2.4OHM,5%,2W,AF,TP,3.9X10

#### ASSY-H/S,MAIN

△ Q401*	*AA96-60350A	ASSY-H/S,MAIN	MAIN,AA62-30002A,2SD1880,
	0502-000209	TR-POWER	2SD1880,NPN,1500V,800V,8A

#### ASSY-CRT

△ CRT	81320-0210	CRT-COLOR	A63AFW32X 261NCH 100DEG 3
ADSH	0201-000281	ADHESIVE-RBR	D-5250,YEL.6000CPS+-500
△ D/Y	AA27-50002U	DEFLECTION-YOKE	-,DAJ5012W,26"/A63LAV11X1

#### ASSY-PCB,CRT

	*AA97-70004A	ASSY-PCB,CRT	-,KCT52A,25",-,CT-6346
R511	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
R512	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
R513	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
△ R525	2008-000290	R-FUSIBLE	2.4OHM,5%,2W,AF,TP,3.9X10

#### ASSY-CABINET

HOLD/CL	AA61-20044A	HOLDER-CLAMPER	-,NYLON-66,V0,NTR,-,-
GRILL/WOOD	AA63-50291A	GRILLE-WOOFER,R	DP,-,-,-,-AA63-50190A,63
GRILL/WOOD	AA63-50291B	GRILLE-WOOFER,L	DP,-,-,-,-AA63-50190B,63
SPA,GUM	AA63-60004L	SPACER-GUM,CRT	-,NTR RUBBER,T3.0,BLK,NEW
WIN/RE	AA64-40242A	WINDOW-REMOCON	-,PC,-,-,-,6345,46,-
IND/LED	AA64-40248A	INDICATOR-LED	-,ACRYL,HB,-,-,6345,46,-

## 7-3.CT5346WB(21 Inch) ; CT6846W and CT5346W Sisimilar Parts

Loc No	New Code No	Description	Specification	Remark
--------	-------------	-------------	---------------	--------

### 7-3-I. CT5346WB/ASMCX (BUYER ; S.E.M Only)

#### ASSY-PCB,MAIN

	●AA97-10036P	ASSY-PCB,MAIN(COM)	CT5346WB/ASMCX,K1,SEJ	
	C-AL	2401-000611	C-AL	1UF,20%,50V,WT,5X11MM,5MM
	C-AL	2401-002463	C-AL	470UF,20%,16V,GP,10X12,5J
△	C303	2305-000178	C-FILM,MPEF	10NF,5%,100V,-,5MM,TP
△	C402*	2306-000237	C-FILM,MPPF	6.3NF,5%,1.6KV,28.5X18X11
△	C403*	2201-000467	C-CERAMIC,DISC	330PF,10%,2KV,Y5P,-,7.5,T
△	C404	2306-000195	C-FILM,MPPF	360NF,5%,400V,26.0X11.0X11
	C410*	2401-002268	C-AL	2.2UF,20%,250V,LR,8X11MM,
	C605H	2301-000224	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,
	C606*	2301-000224	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,
	C801H	2401-001386	C-AL	470UF,20%,250V,GP,25X40MM
	C804*	2201-000954	C-CERAMIC,DISC	4.7NF,20%,400V,Y5U,7X16,1
	C814	2306-000159	C-FILM,MPPF	220NF,20%,250V,-,22.5MM,B
	C907H	2401-001495	C-AL	47UF,20%,16V,GP,5X11MM,5M
	C801H	2305-000283	C-FILM,MPEF	220NF,20%,250V,32X12.0X18
	CN502H	AA39-20054A	LEAD-CONNECTOR,ASSY	-,YBNH025-06,S,6P,400,100
	CNV02	AA39-20053A	LEAD-CONNECTOR,ASSY	-,YBNH025-05,S,5P,400,100
	D-COIL	AA27-20001D	COIL-DEGAUSSING	-,21",5.70HM,55T,L1410,D
	D803	0402-000233	DIODE-RECTIFIER	FML-G12S,200V,5A,-
	D811H	040-000540	DIODE-RECTIFIER	RU20A,600V,1.5A,-
	EL301	AA60-40011A	EYELET	ID2.0,0D2.8,-,-,BST,-
	EY858	AA60-40011A	EYELET	ID2.0,0D2.8,-,-,BST,-
△	IC852*	AA13-20002U	IC-HYBRID	-,SE125N,SIP,3P,ERROR AMP
	J	3301-000287	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240
	J153	3301-000287	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240
	J233	3301-000287	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240
	L302*	AA27-10001E	COIL-CHOKE	-,1.0UH,K,25,2100A,T,SP04
△	L303*	AA27-10001E	COIL-CHOKE	-,1.0UH,K,25,2100A,T,SP04
△	L401*	AA27-30001B	COIL-LINEARITY	-,195UH,Q1C1010,PI0.4,4.5
△	L403*	AA27-10002E	COIL-CHOKE	-,6.8MH,K,50,150MA,-,6.8M
△	L801*	AA29-30001F	FILTER-LINE	-,6MH,0.8A,-,SQ1913
△	L865	3301-000287	CORE-FERRITE BEAD	AA,3.5X1.0X6.0MM,1500,240
△	LA01*	AA27-10002X	COIL-CHOKE	-,43UH,K,10,1A,T,43UH-K(S
	NT0408	AA68-50067A	LABEL-RATING	T/P 90(G),T0.2,-,-,-,AL
△	P801*	1404-000208	THERMISTOR-PTC	70HM,20%,120V,140V,40A,-J
	PD801	AA39-10002D	POWER-CORD	DP,DW-006,SPC2.2,1M,HOUSJ
△	Q402H	0501-000369	TR-SMALL SIGNAL	KSC2331-Y,NPN,80V,60V,700
	R201	2001-000780	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X
	R211	2004-001104	R-METAL	56KOHM,5%,1/8W,AA,TP,1.8X
	R217H	2004-001234	R-METAL	75KOHM,5%,1/8W,AA,TP,1.8X
	R219H	2001-001161	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4
	R301H	2004-000152	R-METAL	1.5KOHM,2%,1/8W,AA,TP,1.8
	R303H	2001-001040	R-CARBON(S)	0.680HM,5%,1/2W,AA,TP,2.4
△	R306	2003-000998	R-METAL OXIDE	3000HM,5%,2W,AF,TP,3.9X10
△	R406*	2008-000262	R-FUSIBLE(S)	1500HM,5%,2W,AF,TP,3.9X10
	R411H	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
	R412H	2004-001373	R-METAL(S)	100KOHM,1%,1/2W,AA,TP,2.4
	R613	2001-000009	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X
	R614	2001-000009	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X

EL301-EL814

Loc No	New Code No	Description	Specification	Remark
R667	2001-000290	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R801*	2006-000336	R- CEMENT	0.270HM,10%,5W,CJ,TP,5.5X	
△ R805*	2002-000331	R- COMPOSITI ON	4.7MOHM,10%,1/2W,AA,TP,3J	
△ R815*	2006-000308	R- CEMENT	220HM,5%,5W,CB,BK,9.5X13J	
R851*	2001-001099	R-CARBON(S)	2.7KOHM,5%,1/2W,AA,TP,2.4	
R852*	2001-001050	R- CARBON(S)	1.5KOHM,5%,1/2W,AA,TP,2.4	
△ R853	2003-000592	R- METAL OXIDE(S)	220HM,5%,2W,AD,TP,4X12MM	
△ RA01*	2003-000458	R- METAL OXIDE(S)	1000HM,5%,2W,AD,TP,4X12MM	
△ RA02*	2003-000458	R- METAL OXIDE(S)	1000HM,5%,2W,AD,TP,4X12MM	
△ RA03*	2003-000458	R- METAL OXIDE(S)	1000HM,5%,2W,AD,TP,4X12MM	
△ SPK	3001-000191	SPEAKER	3W,80HM,90DB,180HZ	
SPK	AA39-20503A	LEAD CONNECTOR- ASSY	-,YSH025-04,REC,4P,600,10	
△ T401*	AA26-50001B	HORIZ.DRIVE	-,7.1MH,102UH,10-20UH,YLO	
△ T444*	AA26-30002H	TRANS- FLYBACK	-,FSV-20B001,20",125V	
△ T801*	AA26-20004D	TRANS- SWITCHI NG	-,80-260V,-,ER424215,630U	
ASSY-H/S,VERT				
△ Q401*	*AA96-60351A 0502-000295	ASSY-H/S,VERT TR-POWER	VERT,AA62-30002A,KSD5072Y KSD5072YD,NPN,1500V,800VJ	
ASSY-H/S,POWER				
△ IC801*	*AA96-60352A AA13-20002H	ASSY-H/S,POWER IC-HYBRID	POWER,AA62-30004D,STRS670 -,STRS6707,SIP,9P,SMPS CO	
ASSY-H/S,VERT				
△ IC301*	*AA96-60353A 1204-000441	ASSY-H/S,VERT IC-IF CIRCUIT	VERT,AA62-30008B,TDA8356J TDA8356,SIP,9P,-,PLASTICJ	
ASSY-ACCESSORY				
USER/M CARD/W	AA68-10893A AA68-40025A	MANUAL- USERS CARD- WARRANTY	KCT52A,WP100,-,SPA,SEM,- -,W/P 100(G),-,WHT,SEM,-	
ASSY-CRT				
△ CRT	AA03-10004K	CRT- COLOR	-,A51KRE83X(BU),+380MG,21	
△ D/Y	AA27-50001F	DEFLECTI ON- YOKE	-,DSE-2192GL,21"/A51KRE83	
△ C/Y	AA27-60001K	MAGNET- CONVERGENCE	-,NY-291,29.1MM	
SP- DY	AA63-60028A	S P A C E R - D Y	-,NEOPRENE,-,BLK,VO W12,-	
ASSY-PCB,CRT				
	*AA97-70004B	ASSY-PCB, CRT	-,CT5346,KCT52A,21",SEA/S	
C224	2301-000264	C-FILM,PEF	4.7NF,5%,50V,6.5X5.5X3.0X	
C501	2305-000412	C-FILM,MPEF	470NF,5%,63V,-,5MM,TP	
C504	2202-000162	C-CERAMIC,MLC-AXIAL	15PF,5%,50V,SL,3.5X19,-,T	
C505	2202-000162	C-CERAMIC,MLC-AXIAL	15PF,5%,50V,SL,3.5X19,-,T	
C506	2202-000162	C-CERAMIC,MLC-AXIAL	15PF,5%,50V,SL,3.5X19,-,T	
O502	0401-000005	DIODE- SWITCHI NG	1N4148,100V,200MA,500MW,4	
EY501	AA60-40011A	EYELET	ID2.0,OD2.8,-,-,BST,-	
IC501	1201-000506	IC- VIDEO AMP	6101,ZIP,9P,-,SINGLE,-,PL	
IC502	1201-000506	IC- VIDEO AMP	6101,ZIP,9P,-,SINGLE,-,PL	
IC503	1201-000506	IC- VIDEO AMP	6101,ZIP,9P,-,SINGLE,-,PL	
△ R503	2004-000187	R- METAL	10.5KOHM,1%,1/4W,AA,TP,2J	
R504	2001-000522	R- CARBON	22KOHM,5%,1/8W,AA,TP,1.8X	
R508	2001-001357	R- CARBON(S)	1.8KOHM,2%,1/2W,AA,TP,2.4	

Loc No	New Code No	Description	Specification	Remark
R509	2001-001357	R- CARBON(S)	1.8KOHM,2%,1/2W,AA,TP,2.4J	
R510	2001-001357	R- CARBON(S)	1.8KOHM,2%,1/2W,AA,TP,2.4J	
R511	2004-001899	R- METAL(S)	61.9KOHM,1%,1/2W,AA,TP,2J	
R512	2004-001899	R- METAL(S)	61.9KOHM,1%,1/2W,AA,TP,2J	
R513	2004-001899	R- METAL(S)	61.9KOHM,1%,1/2W,AA,TP,2J	
△ R517	2002-000327	R- COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
△ R518	2002-000327	R- COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
△ R519	2002-000327	R- COMPOSITION	2.7KOHM,10%,1/2W,AA,TP,3J	
△ R522	2001-001107	R- CARBON(S)	220OHM,5%,1/2W,AA,TP,2.4X	
△ V999	3704-000109	SOCKET- CRT	14P,29.1PI,22.5PI,SN	

## ASSY-CABINET

WR+CF	6002-000514	SCREW- TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW
HOLD/CL	AA61-20044A	HOLDER- CLAMPER	-,NYLON-66,VO,NTR,-,-
HOLD/CA	AA61-20158A	HOLDER- CABINET	-,HIPS,VO,BLK,-,-
SPRG- CS	AA61-60003T	SPRING- CS	-, -, SUS304,0.5,007,H13.5J
GR I /woo	AA63-50292A	GRILLE-WOOFER,R	DP,-,-,-,AA63-50197A,53
GR I /WOOD	AA63-50292B	GRILLE-WOOFER,L	DP,-,-,-,AA63-50197B,53
WIN/RE	AA64-40254A	WINDOW- REMOCON	-,PC,-,-,-,5345,6,-
IND/LED	AA64-40255A	INDICATOR- LED	-,ACRYL,HB,-,-,5345,6,-
BADGE	AA64-70015B	BADGE- BRAND	-,AL,-,L45,GOLD,R2000 SS