

2-1. Electrical Parts List

ABBREVIATIONS : cc C-CERAMIC
CE C-ELECTROLYTIC
CFS C-M, POLYESTER
CK C-CERAMIC, HK
CQ C-POLYPROPYLENE, POLYESTER
CS C-TANTALIUM, SOLID

RC R-COMPOSITION
RD R-CARBON
RF R-FUSIBLE
RM R-METAL, FILM
RP R-CEMENT WIRE
RS R-METAL, OXIDE

NOTE : The items with "*" are usually out of stock since they are seldom required for the routine service. There may be some anticipated delay when you order these items.

S.N.A. = Service Not Available , L/C = Local Purchase

The components identified by mark "*" are critical for safety. Replace only with Supplier part number specified.

When indicating parts' location number, Please include the PWB names
(PWB = Printed Writing Board)

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
CT3362V/1CORMX BUYER : CORRIPIO ('94.11.07) ASSY-PWB MAIN *3T30-02481-020 CT3362V/1CORMX, CKC50HM M-PCB 36029-0146-000 T1.6 W330 L245 (S.N.A) RESISTORS					
J048	31018-177-102	RD 1/8T 1K-J	R202	31018-177-202	RD 1/8T 2K-J
J049	31018-177-102	RD 1/8T 1K-J	R203	31018-177-221	RD 1/8T 220-J
J055	31018-177-563	RD 1/8T 56K-J	R206	31018-177-821	RD 1/8T 820-J
5131	31018-177-221	RD 1/8T 220-J	R208	31018-177-562	RD 1/8T 5.6K-J
J132	31018-177-221	RD 1/8T 220-J	R209	31018-177-913	RD 1/8T 91K-J
5133	31018-177-221	RD 1/8T 220-J	R214	31018-177-391	RD 1/8T 390-J
R101	31018-177-101	RD 1/8T 100-J	R215	31018-177-471	RD 1/2T 470-J
R102	31018-177-562	RD 1/8T 5.6K-J	**R224	31046-567-101	RS 2T 100-J (UTO)
R103	31018-177-122	RD 1/8T 1.2K-J	**R225	31046-567-220	RS 2T 22-J (AUTO)
R104	31018-177-330	RD 1/8T 33-J	R301	31018-177-331	RD 1/8T 33 6-J
R105	31018-177-681	RD 1/8T 680-J	R302	31018-377-224	R D 1/2T 220K-J
R106	31018-177-101	RD 1/8T 100-J	R303	31018-177-472	R D 1/8T 4.7K-J
R107	31018-177-472	RD 1/8T 4.7K-J	R304	31018-177-393	RD 1/8T 39K-J
R108	31018-177-470	RD 1/8T 47-J	R305	31018-377-684	R D 1/2T 680K-J
R109	31018-177-104	RD 1/8T 100K-J	R307	31018-177-331	RD 1/8T 330-J
R110	31018-177-104	RD 1/8T 100K-J	**R308	31057-002-010	RF 1/2T 1-J
R111	31018-177-221	RD 1/8T 220-J	R309	31018-177-823	RD 1/8T 82K-J
R112	31018-177-563	RD 1/8T 56K-J	**R310	31048-363-303	RM 1/2T 330K-G
R113	31018-177-154	RD 1/8T 150K-J	R311	31018-376-124	RD 1/2T 120K-G
R114	31018-177-223	RD 1/8T 22K-J	**R314	31047-176-152	RM 1/8T 1.53-G
R115	31018-177-333	RD 1/8T 33K-J	R315	31018-177-100	RD 1/8T 10-J
R116	31018-177-102	RD 1/8T 1K-J	R316	31018-177-752	RD 1/8T 7.5K-J
R117	31018-177-391	RD 1/8T 390-J	R317	31018-377-399	RD 1/2T 3.9-J
R118	31018-177-221	RD 1/8T 220-J	R320	31018-177-333	RD 1/8T 33K-J
R120	31018-177-102	RD 1/8T 1K-J	**R401	31046-567-562	RS 2T 5.6K-J (AUTO)
R121	31018-177-271	RD 1/8T 270-J	**R401A	31046-567-272	RS 2T 2.7K-J (AUTO)
R122	31018-177-223	RD 1/8T 22K-J	R402	31018-177-272	RD 1/8T 2.7K-J
R123	31018-177-822	RD 1/8T 8.2K-J	R403	31018-177-182	RD 1/8T 1.8K-J
R124	31018-177-562	RD 1/8T 5.6K-J	R404	31018-177-331	RD 1/8T 330-J
R201	31018-177-162	RD 1/8T 1.6K-J	R405	31018-177-681	RD 1/8T 680-J
			R406	31018-377-752	RD 1/2T 7.5K-J
			R406A	31018-377-822	RD 1/2T 8.2K-J
			**R407	31046-567-272	RS 2T 2.7K-J (AUTO)
			R408	31018-377-122	RD 1/2T 1.2K-J
			R408A	31018-377-272	RD 1/2T 2.7K-J
			**R414	31057-477-109	RF 1T 1.0-J/RF 1S 1.0-J
			**R415	31046-467-102	RS 1T 1K-J (AUTO)
			**R416	31049-311-600	RM 1/2T 133K-F

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**R417	31057-201-025	RF 1T 0.47-K	R902	31018-377-120	RD 1/2T 12-J
**R418	31048-361-001	RM 1/2T 1K-G	**R904	31046-567-123	RS 2T 12K-J(AUTO)
**R419	31046-567-272	RS 2T 2.7K-J(AUTO)	**R905	31046-567-123	RS 2T 12K-J(AUTO)
R421	31018-377-183	RD 1/2T 18K-J	R906	31018-177-752	RD 1/8T 7.5K-J
**R425	31046-567-750	RS 2T 75-J AUTO	R907	31018-177-103	RD 1/8T 10K-J
**R425A	31046-567-750	RS 2T 75-J AUTO	R908	31018-377-152	RD 1/2T 1.5K-J
R444	31018-377-330	RD 1/2T 33-J	R909	31018-377-752	RD 1/2T 7.5K-J
**R445	A1000-0660	RD 1/2 J(S) R39-K 0.39R	R910	31018-377-752	RD 1/2T 7.5K-J
R502	31018-177-101	RD 1/8T 100-J	R911	31018-177-103	RD 1/8T 10K-J
R508	31018-377-514	RD 1/2T 510K-J	R912	31018-177-682	RD 1/8T 6.8K-J
R510	31018-177-561	RD 1/8T 560-J	R913	31018-177-223	RD 1/8T 22K-J
R511	31018-177-561	RD 1/8T 560-J	R914	31018-177-560	RD 1/8T 56-J
R512	31018-177-561	RD 1/8T 560-J	R915	31018-177-823	RD 1/8T 82K-J
R513	31018-377-395	RD 1/2T 3.9M-J	R916	31018-177-823	RD 1/8T 82K-J
R516	31018-377-471	RD 1/2T 470-J	R917	31018-177-823	RD 1/8T 82K-J
R517	31018-177-222	RD 1/8T 2.2K-J	R918	31018-177-823	RD 1/8T 82K-J
R518	31018-177-272	RD 1/8T 2.7K-J	R919	31018-177-823	RD 1/8T 82K-J
R530	31018-177-101	RD 1/8T 100-J	R920	31018-177-823	RD 1/8T 82K-J
R531	31018-177-151	RD 1/8T 150-J	R921	31018-177-103	RD 1/8T 10K-J
R532	31018-177-151	RD 1/8T 150-J	R924	31018-177-823	RD 1/8T 82K-J
R533	31018-177-151	RD 1/8T 150-J	R925	31018-177-153	RD 1/8T 15K-J
R534	31018-177-102	RD 1/8T 1K-J	R926	31018-177-102	RD 1/8T 1K-J
R535	31018-177-102	RD 1/8T 1K-J	R931	31018-177-243	RD 1/8T 24K-J
R536	31018-177-102	RD 1/8T 1K-J	R933	31018-177-472	RD 1/8T 4.7K-J
**R537	31046-567-153	RS 2 15K-J(AUTO)	R934	31018-177-222	RD 1/8T 2.2K-J
**R538	31046-567-153	RS 2T 15K-J(AUTO)	R935	31018-177-153	RD 1/8T 15K-J
**R539	31046-567-153	RS 2T 15K-J(AUTO)	R937	31018-177-122	RD 1/8T 1.2K-J
**R540	31028-328-472	RC 1/2T 4.7K-K	**R939	31046-567-820	RS 2T 82-J(AUTO)
**R541	31028-328-472	RC 1/2T 4.7K-K	R940	31018-177-513	RD 1/8T 51K-J
**R542	31028-328-472	RC 1/2T 4.7K-K	R941	31018-177-102	RD 1/8T 1K-J
R543	31018-177-472	RD 1/8T 4.7K-J	R942	31018-177-123	RD 1/8T 12K-J
R544	31018-377-331	RD 1/2T 330-J	R944	31018-177-183	RD 1/8T 18K-J
**R545	31057-477-109	RF 1T 1.0-J/RF 1S 1.0-J	R946	31018-177-203	RD 1/8T 20K-J
R546	31018-177-472	RD 1/8T 4.7K-J	R947	31018-177-393	RD 1/8T 39K-J
R547	31018-377-331	RD 1/2T 330-J	R949	31018-177-433	RD 1/8T 43K-J
R548	31018-377-331	RD 1/2T 330-J	R952	31018-177-102	RD 1/8T 1K-J
R549	31018-177-472	RD 1/8T 4.7K-J	R953	31018-177-103	RD 1/8T 10K-J
**R599	31046-567-470	RS 2T 47-J (UTC)	R956	31018-177-202	RD 1/8T 2K-J
**R600	31057-577-561	RF 2T 560-J/RF 2S 560-J	R957	31018-177-102	RD 1/8T 1K-J
R601	31018-177-681	RD 1/8T 680-J	R958	31018-177-331	RD 1/8T 330-J
R602	31018-177-102	RD 1/8T 1K-J	R960	31018-177-472	RD 1/8T 4.7K-J
R603	31018-177-102	RD 1/8T 1K-J	R961	31018-377-681	RD 1/2T 680-J
R604	31018-177-512	RD 1/8T 5.1K-J	R962	31018-177-681	RD 1/8T 680-J
R605	31018-177-202	RD 1/8T 2K-J	R964	31018-177-682	RD 1/8T 6.8K-J
R605	31018-177-122	RD 1/8T 1.2K-J	R966	31018-177-223	RD 1/8T 22K-J
R606	31018-177-622	RD 1/8T 6.2K-J	R968	31018-177-153	RD 1/8T 15K-J
R607	31018-377-274	RD 1/2T 270K-J	R970	31018-177-821	RD 1/8T 820-J
**R608	31046-467-123	RS 1T 12K-J(AUTO)	R971	31018-177-821	RD 1/8T 820-J
**R699	31049-101-130	RS 1P 22-J	R972	31018-177-821	RD 1/8T 820-J
**R802	31036-787-339	RW 10H 3.3-J ST	R973	31018-177-332	RD 1/8T 3.3K-J
R803A	31018-377-224	RD 1/2T 220K-J	R974	31018-177-332	RD 1/8T 3.3K-J
R803B	31018-377-224	RD 1/2T 220K-J	R975	31018-177-332	RD 1/8T 3.3K-J
R804	31018-377-221	RD 1/2T 220-J	R976	31018-177-472	RD 1/8T 4.7K-J
R805	31018-377-229	RD 1/2T 2.2-J	R981	31018-177-333	RD 1/8T 33K-J
**R808	31057-002-010	RF 1/2T 1-J	R982	31018-177-152	RD 1/8T 1.5K-J
R888A	31018-377-514	RD 1/2T 510K-J	**R990	31046-567-123	RS 2T 12K-J(AUTO)
R901	31018-177-102	RD 1/8T 1K-J			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
R991	31018-177-102	RD 1/8T 1K-J	C103	31417-109-140	CK45 TAPG F 50V 103-Z
R992	31018-177-102	RD 1/8T 1K-J	C105	31417-109-140	CK45 TAPG F 50V 103-Z
R993	31018-177-102	RD 1/8T 1K-J	C106	31417-104-290	CK45 TAPG B 50V 472-K
R994	31018-177-102	RD 1/8T 1K-J			
R995	31018-177-102	RD 1/8T 1K-J	C107	31407-105-660	CC45 (T) CH 50V 101-J
R999	31018-177-103	RD 1/8T 10K-J	C108	31407-105-660	CC45 (T) CH 50V 101-J
RC15	31018-177-100	RD 1/8T 10-J	C110	31417-109-140	CK45 TAPG F 50V 103-Z
RC16	31018-177-100	RD 1/8T 10-J	C111	31507-127-007	ECQ B1 H 1535 F3
RC17	31018-177-100	RD 1/8T 10-J	C112	31407-105-110	CC45 TAPG CH 50V 120-J
RJ106	31018-177-223	RD 1/8T 22K-J	C114	31417-109-140	CK45 TAPG F 50V 103-Z
RV001	31018-377-680	RD 1/2T 68-J	C151	31607-402-240	CEO4W TAPG 50V 4.7M
**RV002	31057-002-040	RF 1/2T 68-J	C152	31607-402-240	CEO4W TAPG 50V 4.7M
RV003	31018-177-154	RD 1/8T 150K-J	C153	31607-402-200	CEO4W TAPG 50V 0.47M
RV004	31018-177-563	RD 1/8T 56K-J	C154	31607-401-510	CEO4W TAPG 16V 1000U-M
RV005	31018-177-153	RD 1/8T 15K-J	-C155	31607-402-260	CEO4W TAPG 50V 22M-M
RV006	31018-177-331	RD 1/8T 330-J	C156	31607-401-500	CEO4W TAPG 16V 470M-M
**RV007	31028-328-475	RC 1/2T 4.7M-K	C201	31407-105-660	CC45 (T) CH 50V 101-J
RV010	31018-177-750	RD 1/8T 75-J	C202	31407-105-090	CC45 (T) CH 50V 100-C
RV011	31018-177-752	RD 1/8T 7.5K-J	C251	31607-401-430	CEO4W TAPG 25V 10M
RV012	31018-177-222	RD 1/8T 2.2K-J	C252	31607-401-430	CEO4W TAPG 25V 10M
RV013	31018-177-470	RD 1/8T 47-J	C253	31507-127-006	ECQ B1 H 1035 F3
RV021	31018-177-681	RD 1/8T 680-J	C254	31607-402-720	CEO4W TAPG 50V 2.2M-M
RV022	31018-177-471	RD 1/8T 470-J	C255	31507-127-006	ECQ B1 H 103J F3
RV023	31018-177-102	RD 1/8T 1K-J	C301	31507-127-001	ECQ B1 H 1525 F3
RV024	31018-177-622	RD 1/8T 6.2K-J	C302	31507-127-023	ECQ B1 H 1225 F3
RV025	31018-177-103	RD 1/8T 10K-J	C303	31507-127-016	ECQ B1 H 472J F3
RV026	31018-177-121	RD 1/8T 120-J	C304	31507-127-010	ECQ B1 H 4735 F3
RV027	31018-177-132	RD 1/8T 1.3K-J	C305	31507-127-022	ECQ B1 H 5135 F3
RV028	31018-177-183	RD 1/8T 18K-J	C307	31507-127-010	ECQ B1 H 4735 F3
RV029	31018-177-333	RD 1/8T 33K-J	C309	31507-127-006	ECQ B1 H 1035 F3
RV030	31018-177-302	RD 1/8T 3K-J	C311	31417-468-681	CK45 TAPG B500V 681-K
RV031	31018-177-822	RD 1/8T 8.2K-J	C320	31507-127-011	ECQ B1 H 6835 F3
RV032	31018-177-393	RD 1/8T 39K-J	**C321	B1102-0318	CF 922 N 50V T 104-J -4
RV034	31018-177-102	RD 1/8T 1K-J	C351	31607-902-250	CEO4W TAPG 50V 0.22M
RV035	31018-177-221	RD 1/8T 220-J	C352	31607-402-100	CEO4W TAPG 35V 100M-M
RV036	31018-177-123	RD 1/8T 12K-J	C353	31607-403-970	CEO4W TAPG 25V 1000M-M
RV037	31018-177-183	RD 1/8T 18K-J	C354	31607-402-250	CEO4W TAPG 50V 10M
RV038	31018-177-302	RD 1/8T 3K-J	C355	31607-402-130	CEO4W TAPG 35V 470M-N
RV039	31018-377-561	RD 1/2T 560-J	C356	31607-402-570	CEO4W TAPG 50V 1M
RV040	31018-177-152	RD 1/8T 1.5K-J	C357	31607-402-570	CEO4W TAPG 50V 1M
RV041	31018-177-472	RD 1/8T 4.7K-J	C399	31417-468-331	CK45 TAPG B500V 331-K
VARIABLE RESISTORS			C401	31507-127-009	ECQ B1 H 3335 F3
VR101	31249-128-005	EVN DJA A03 B53	C402	31507-127-010	ECQ B1 H 4735 F3
VR203	31249-128-008	EVN DJA A03 B54	C403	31507-127-005	ECQ B1 H 8225 F3
VR301	31249-128-006	EVN DJA A03 B22	C404	31417-109-100	CK45 TAPG F 50V 102-Z
VR401	31249-128-006	EVN DJA A03 B22	C405	31417-106-170	CK45 TAPG B 500V 222-K
VR531	31249-128-006	EVN DJA A03 B22	C406	31417-106-090	CK45 TAPG B 500V 471-K
VR532	31249-128-006	EVN DJA A03 B22	**C407	A1102-0205	CF 922 P 1.6KV T 632-J
VR533	31249-128-005	EVN DJA A03 B53	C408	31417-901-400	CK45 (T) B2KV 561-K
VR534	31249-128-005	EVN DJA A03 B53	C409	31607-401-670	CEO4W TAPG 25V 47M
VR535	31249-128-005	EVN DJA A03 B53	C410	31607-401-670	CEO4W TAPG 25V 47M
VRV01	31249-128-004	EVN DJA A03 B13	**C412	31517-390-502	CFS922M TAPG 250V 104-J
CAPACITORS			**C413	31517-333-334	CFS 922M TAPG 200V 334-a
C101	31417-109-100	CK45 TAPG F 50V 102-Z	C414	31417-106-090	CK45 TAPG B 500V 471-K
C102	31417-109-100	CK45 TAPG F 50V 102-Z	C451	31607-401-460	CEO4W TAPG 16V 47M
			C452	31607-402-210	CEO4W TAPG 50V 1M
			C456	31607-401-710	CEO4W TAPG 25V 470M-M
			C458	31607-403-490	CEO4W TAPG 250V 10M-M

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
C497	31417-318-152	CK45 TAPG B 50V 152-K	C954	31607-401-140	CE04W TAPG 6.3V 1000M-1
C499	31417-468-561	CK45 TAPG B500V 561-K	C955	31607-401-460	CE04W TAPG 16V 47M
C501	31407-105-260	CC45 (T) CH 50V 470-J	C956	31607-402-200	CE04W TAPG 50V 0.47M
C502	31407-106-760	CC45 (T) RH 50V 151-J	C957	31607-401-430	CE04W TAPG 25V 10M
C504	31417-109-140	CK45 TAPG F 50V 103-Z	C958	31607-401-430	CE04W TAPG 25V 10M
C506	31407-105-180	CC45(T) CH 50V 220-J	C959	31607-401-430	CE04W TAPG 25V 10M
C507	31507-127-007	ECQ B1 H 1535 F3	C960	31607-402-250	CE04W TAPG 50V 10M
C508	31417-104-070	CK45 TAPG B 50V 271-K	C961	31607-402-240	CE04W TAPG 50V 4.7M
C509	31417-104-070	CK45 TAPG B 50V 271-K	C962	31607-401-430	CE04W TAPG 25V 10M
C510	31417-104-070	CK45 TAPG B 50V 271-K	C963	31607-401-430	CE04W TAPG 25V 10M
C531	31417-318-152	CK45 TAPG B 50V 152-K	C964	31607-401-430	CE04W TAPG 25V 10M
C532	31417-318-152	CK45 TAPG B 50V 152-K	C965	31607-402-210	CE04W TAPG 50V 1M
C533	31417-318-152	CK45 TAPG B 50V 152-K	C966	31417-104-070	CK45 TAPG B 50V 271-K
C534	31417-767-102	CK45(T) B2KV 102-K	C970	31607-401-430	CE04W TAPG 25V 10M
C535	31417-109-100	CK45 TAPG F 50V 102-Z	C971	31507-127-016	ECQ B1 H 472J F3
C536	31417-109-100	CK45 TAPG F 50V 102-Z	C972	31607-401-430	CE04W TAPG 25V 10M
C537	31417-109-100	CK45 TAPG F 50V 102-Z	**C973	B1102-0318	CF 922 N 50V T 104-J -40
C551	31607-402-170	CE04W TAPG 50V 0.1U-L, L	**CA101	31467-001-001	CK45P TAPG E400V 222-M
C553	31607-402-230	CE04W TAPG 50V 3.3M	**CA102	31467-001-001	CK45P TAPG E400V 222-M
C554	31607-402-220	CE04W TAPG 50V 2.2M	**CN901	31497-009-440	EXF-FP5 331MDV(6P 331)
C555	31607-401-670	CE04W TAPG 25V 47M	**CN902	31497-009-350	EXF-FP7 331MDV(8P 331)
C556	31607-402-210	CE04W TAPG 50V 1M	**CN903	31497-009-430	EXF-FP3 331MDV(4P 331)
C557	31607-402-210	CE04W TAPG 50V 1M	**CN904	31497-009-360	EXF-FP8 331MDV(9P 331)
C558	31417-109-140	CK45 TAPG F 50V 103-Z	CV002	31417-109-140	CK45 TAPG F 50V 103-Z
C560	31607-401-690	CE04W TAPG 25V 220M-M	CV003	31417-106-090	CK45 TAPG B 500V 471-K
C561	31607-401-430	CE04W TAPG 25V 10M	**CV005	31466-001-005	CK45P E400V 222-M T4KV
C601	31407-106-150	CC45 (T) RH 50V 150-J	CV051	31607-401-430	CE04W TAPG 25V 106
C602	31507-127-006	ECQ B1 H 1035 F3	CV052	31607-401-700	CE04W TAPG 25V 330M-M
C603	31417-109-140	CK45 TAPG F 50V 103-Z	CV053	31607-401-670	CE04W TAPG 25V 47M
C606	31417-106-010	CK45 TAPG B 500V 101-K	CV055	31607-401-460	CE04W TAPG 16V 47M
C607	31417-104-330	CK45 TAPG B 50V 331-K	**CV059	A1104-0521	CE 04 -40/85 50V T 330 M
C651	31607-401-430	CE04W TAPG 25V 10M	CV060	31607-401-430	CE04W TAPG 25V 10M
C655	31607-403-210	CE04W TAPG 160V 10M-M	CV061	31607-803-730	CE04W TAPG 50V 4.7M-NP
C656	31607-402-250	CE04W TAPG 50V 10M	I C		
C657	31607-403-210	CE04W TAPG 160V 10M-M	IC101	32119-102-131	CXA1110BSI
C701	31607-402-470	CE04W TAPG 50V 47M-M(FR	IC501	32119-102-020	LA7625
**C777	31467-001-001	CK45P TAPG E400V 222-M	**IC901	B4002-0302	Z8622704PSC-R1006/R112
**C801	31516-002-140	ECQ-E2A 224M N86(TAPG)	ICV01	32109-410-270	TC4066BP
C803	31407-052-709	CC45 (T) CH 50V 070-C	TRANSISTORS		
C812	31417-767-102	CK45 (T) B2KV 102-K	Q101	32137-301-050	KSC 1674(TAPG)
C850	31507-127-026	ECQ-V1H 474J Z3	Q201	32137-401-530	KSA 539-Y(TAPG)/YTAM
C851	31607-403-250	CE04W TAPG 160V 100M-M	Q203	32137-103-430	KSA 642-0(TAPG)
**C852	31606-403-840	CE04W 400V 220M-M 30X40	**Q401	32137-301-530	KSC 2330-0(TAPG)
C900	31607-401-690	CE04W TAPG 25V 226M-M	Q501	32137-301-560	KSC 2331-Y(TAPG)
C901	31417-468-681	CK45 TAPG B500V 681-K	Q531	32137-301-530	KSC 2330-0 (TAPG)
C902	31417-109-100	CK45 TAPG F 50V 102-Z	Q532	32137-301-530	KSC 2330-0 (TAPG)
C905	31407-105-180	CC45 (T) CH 50V 220-J	Q533	32137-301-530	KSC 2330-0 (TAPG)
C906	31407-105-180	CC45 (T) CH 50V 220-J	Q534	32137-301-530	KSC 2330-0 (TAPG)
C907	31407-105-270	CC45 (T) CH 50V 300-J	Q535	32137-301-530	KSC 2330-0 (TAPG)
C908	31417-109-100	CK45 TAPG F 50V 102-Z	Q536	32137-301-530	KSC 2330-0 (TAPG)
C909	31407-105-150	CC45(T) CH 50V 160-J	Q601	32137-301-540	KSC 2330-Y(TAPG)
C912	31407-105-660	CC45(T) CH 50V 101-J	**Q602	A4052-0055	KSA940 25W -1.5A 4MHZ
C919	31417-109-140	CK45 TAPG F 50V 103-Z	**Q603	A4052-0059	KSC2073 25W 1.5A 4MHZ
**C951	B1102-0318	CF 922 N 50V T 104-J -41	Q901	32137-301-560	KSC 2331-Y(TAPG)
C952	31607-401-430	CE04W TAPG 25V 10M	Q905	32137-301-720	KSC 815-Y(TAPG)/YTAM
C953	31607-401-290	CE04W TAPG 10V 220U			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
Q907	32137-301-720	KSC 815-Y(TAPG)/YTAM	D971	32167-101-130	1K34A (TAPG)
Q909	32137-301-720	KSC 815-Y(TAPG)/YTAM	DA00	32167-406-080	MTZ 5.1B
Q910	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV002	32167-201-170	TVR10G (TAPG)
9911	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV003	32167-406-480	1N4148 TAPG
Q912	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV004	32167-406-480	1N4148 TAPG
Q923	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD01	32167-408-080	EQA02-06D/MTZ6.2B (TAPG)
QV001	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD02	32167-408-080	EQA02-06D/MTZ6.2B (TAPG)
QV002	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD03	32167-408-080	EQA02-06D/MTZ6.2B (TAPG)
QV003	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD501	32167-406-150	MTZ 13A
QV004	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD901	32167-406-080	MTZ 5.1B
QV005	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD902	A4106-0128	MTZ6.8A-T72 6.29/6.63V
QV006	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD903	32167-406-080	MTZ 5.1B
QV007	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD904	32167-403-850	EOB 01-33(TAPG)
QV008	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD905	32167-406-130	MTZ 9.1B
QV009	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD906	32167-406-080	MTZ 5.1B
DIODES			ZD908	32167-406-150	MTZ 13A
D201	32167-406-480	1N4148 TAPG	POSISTOR		
D202	32167-406-480	1N4148 TAPG	**R801	32189-609-390	2C18R
D203	32167-406-480	1N4148 TAPG	MODULE REMOCON		
D204	32167-201-070	1N 4003/LTIN 4003	PRE-AM	32196-411-002	SR-5CP ST
D301	32167-201-170	TVR10G(TAPG)	LED-GUIDE, ASSY		
D302	32167-201-170	TVR10G(TAPG)	LED/G	32306-101-020	DL-G2RA
D303	32167-406-480	1N4148 TAPG	PHOTO-COUPLER		
D304	32167-406-480	1N4148 TAPG	**PC001	32309-024-040	LTV817B
D305	32167-406-480	1N4148 TAPG	**PC002	32309-025-000	HP6N136-020 8DIP 5KV
**D401	32167-201-170	TVR10G(TAPG)	COILS		
**D406	32167-201-170	TVR10G(TAPG)	L101	32427-904-918	AL02-1R0K
**D408	32167-406-480	1N4148 TAPG	L102	32427-904-944	AL02 R56-M
**D409	32167-406-480	1N4148 TAPG	L103	32427-904-945	AL02 R80M(0.8UH)
D502	32167-406-480	1N4148 TAPG	**L201	A1132-0040	18UH-K AX AL02 95OF1 3MHZ
D503	32167-406-480	1N4148 TAPG	L202	32427-100-101	ELF0607RA-101K(100MH)
D601	32167-406-480	1N4148 TAPG	L301	32427-803-130	10UH-K TAPG
D699	32167-406-480	1N4148 TAPG	**L401	32427-904-924	AL02-100K(10UH)
D701	32167-207-120	1R5GU41(TAPG)	**L402	32446-705-050	195UH ST
D800	32167-401-041 32167-208-580	ENC431D-10A(ERB 2-TAPG)	**L403	32427-904-924	AL02-100K(10UH)
**D801		ERB 12-06 TA	**L407	32426-226-190	82UH-K(ROBOT:0.8A)
**D802	32167-208-580	ERB 12-06 TAPG	L501	32427-904-924	AL02-100K 10UH)
**D803			L532	32427-805-858	AL03 331- \$
**D804	32167-208-580	ERB ERB 12-06 12-06 TAPG TAPG	L602	32427-805-878	AL02 220-J
**D805	32167-207-120	1R5GU41(TAPG)	**L801	32426-633-160	6MH-SQ1913 ST
**D806	32167-201-170	TVR10G(TAPG)	**L802	32479-029-380	14"/230HM/T100/L940MM
**D807	32167-201-170	TVR10G(TAPG)	L901	32427-805-550	47UH-K TAPG
**D808	32167-401-850	R-2KY(TAPG)	L902	32427-904-924	AL02-100K(10UH)
D900	32167-201-170	TVR10G(TAPG)	L903	32427-904-924	AL02-100K(10UH)
D901	32167-406-480	1N4148 TAPG	LA00	32427-805-840	AL03 100-K
D902	32167-406-480	1N4148 TAPG	LA01	32427-805-840	AL03 100-K
D904	32167-406-480	1N4148 TAPG	LV01	32427-904-924	AL02-100K(10UH)
D905	32167-406-480	1N4148 TAPG	DELAY-LINE		
D906	32167-406-480	1N4148 TAPG	X201	32466-200-013	SDL401TN
D907	32167-406-480	1N4148 TAPG	TRANS-PLY BACK		
D908	32167-406-480	1N4148 TAPG			
D909	32167-201-070	1N 4003/LTIN 4003			
D913	32167-406-480	1N4148 TAPG			
D914	32167-406-480	1N4148 TAPG			
D915	32167-406-480	1N4148 TAPG			
D916	32167-406-480	1N4148 TAPG			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**T444	32859-153-410	FCK-1415EL TRANS	SILD/C	34543-130-810	STPE TO.25
L105	32707-200-014	45.75MHZ/2(7M/M)	CLMP/W	36635-112-010	NYLON 6.6 DATL-600
L106	32707-200-013	45.75MHZ(7M/M)	L-WFNG	38114-691-210	ART PAPER120(S) P58SC
**T401	32846-070-006	130MH/105UH ST			ASSY-H/SINK VERT
T601	32786-550-080	200:40EM 24MM ST	*3H82-00530-000	31124-0014-000	KA2131
**T801	32896-001-090	P:90-260 S:95V ER354	**IC301	32119-102-300	KA 2131
**T802	32996-001-000	486UH:28.8UH ST	H/SINK	31124-0014-000	SPC-1 T1.O FT-2 (S.N.A)
**TV001	A1207-0004	EE1916 2MH 50HM ST	SCREW	37158-230-061	2S-3X8 FE FZY (S.N.A)
		CORE-FERRITES			ASSY-H/SINKVERT(HORI)
L404	34047-019-060	3.5X6X1.0	*3H82-00530-001	31124-0014-000	ISD1711Y
L803	34047-019-060	3.5X6X1.0	**Q402	32159-210-070	2SD1711YD
L804	34047-019-060	3.5X6X1.0	H/SINK	31124-0014-000	SPC-1 T1.O FT-2 (S.N.A)
		FILTERS	SCREW	37158-230-081	2S-3X8FE FZY (S.N.A)
**Z101	B1245-0050	TSF1230L NTSC/USA VIP	WASHER	37334-105-910	SPC-1 T1.O FZY-1 (S.N.A)
2102	34527-700-024	SAR41MC80Z-TF01			ASSY-H/SINK POWER
2201	34527-460-001	TPS4.5MCTF21	*3H83-00780-000	31122-0017-070	STR50103
**Z601	B1243-0071	BP 4.5M SFSH4.5MCB-TF21	**Q801	32119-910-003	STR50103A LF501
2602	34527-460-064	CDA4.5ME30 TF21	H/SINK	31122-0017-070	A6063, EXTR, WGT
		CRYSTALS	SCREW	37158-230-101	2S-3X10 FE FZY (S.N.A . .)
X501	34537-001-002	3.579545MHZ			ASSY-POWER CORD
X901	34537-001-003	4.0MHZ	*3H64-00051-200	H/C200MM	BLK-HOU EP2/NO
		RESONATOR	PC801	33053-817-080	DW-006/MSP-10/, SPC-2
X40 1	34539-300-000	CSB503F5	HOLD/C	33323-0015-000	PP VO BLACK
		FUSE			ASSY-ACCESSORY
**FUSE	34709-087-020	T/L 250V 4A 20M/M	MACH/Y	32759-115-050	R300-R75CSA
		TUNER	ROD/A	34509-223-023	4S N/IL DIPOLE 620MM BRN
**H901	A1292-0040	TECC1880PA09C(S) 181CH	SVC/N	38134-379-010	ART PAPER 100
		SOCKET-CRT	I/B	38134-454-310	W/P120(S) EXP STANDARD
**V999	A3047-0013	ISMS01S P114.3 HI-FOCUS	PE-BAG	38653-108-161	HDPETO.015 400X230 NO
		MISCELLANEOUS			ASSY-CRT
ANT/B	32079-0033-000	100PFX470PF 100MM 4KV	**CRT	32019-400-081	A34KQV42X
CN81A	33054-834-014	P1XP1/DIW/500	**D/Y	32439-210-090	DSE-1422FL
CNO1	33058-372-014	B10XB0/F/350	SP-DY	33309-0020-000	NEOPLENE VO BLK W 12MM
JA01	A3040-0134	P13.5UL-PJ 1P MONO-12.5	**C/Y	A1155-0004	NY-225 P122.5
JA02	A3040-0135	P13.5UL-PJ 1P MONO-12.5			ASSY-TRANSMITTER
EYE-P	33104-107-210	BST 2.8X2.0	*3F14-00034-900	TM34 RM238	33 E S/S BR
GT-PIN	33124-111-100	1PAUTO			ASSY-SPEAKER
F801	33167-001-001	PFC 5000-0202	*3H73-20030-011	5902BR3W*2, L300, W600	
FBT/C	33333-0005-000	NYLON 66 VO NTR			
PA11	33347-108-31	(67094-003(AUTO))	LEAD/C	33058-003-012	S302B 2/F8300
			**SPK	34209-169-140	59 2 R R 2W
SW201	33546-007-010	JRS-1301-1/KLR-1301A			
SW02	33596-001-001	JTR-1104 ST			
SW901	33606-101-011	KPT-1112 ST			
SW902	33606-101-025	KPT-2104-21 ST			
WT0046	34503-0100-000	TETRONE PAPER 90(G) ALL			

2-2 Electrical Parts List

ABBREVIATIONS : CC C-CERAMIC
 CE C-ELECTROLYTIC
 CFS C-M. POLYESTER
 CK C-CERAMIC, HK
 CQ C-POLYPROPYLENE, POLYESTER
 CS C-TANTALUM, SOLID

RC R-COMPOSITION
 RD R-CARBON
 RF R-FUSIBLE
 RM R-METAL, FILM
 RP R-CEMENT WIRE
 RS R-METAL, OXIDE

NOTE : The items with "*" are usually out of stock since they are seldom required for the routine service. There may be some anticipated delay when you order these items.

S.N.A. = Service Not Available , L/C = Local Purchase

The components identified by mark "*" are critical for safety. Replace only with Supplier part number specified.

When indicating parts by location number, Please include the PWB names
 (PWB = Printed Writing Board)

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
CT3362V/1ANMCX BUYER : ANTARES ('94.11.07) ASSY-PWB MAIN *3X30-02481Y080 CT3362V/1ANMCX (S.N.A) 02LOT 36029-0146-000 T116 W330 L245 CKC50Z RESISTORS JO48 31018-177-102 RD 1/8T 1K-J JO49 31018-177-102 RD 1/8T 1K-J JO55 31018-177-563 RD 1/8T 56K-J J106 31018-177-223 RD 1/8T 22K-J 5131 31018-177-221 RD 1/8T 220-J J132 31018-177-221 RD 1/8T 220-J 5133 31018-177-221 RD 1/8T 220-J R101 31018-177-101 RD 1/8T 100-J R102 31018-177-562 RD 1/8T 5.6K-J R103 31018-177-122 RD 1/8T 1.2K-J R104 31018-177-330 RD 1/8T 33-J R105 31018-177-681 RD 1/8T 680-J R106 31018-177-101 RD 1/8T 100-J R107 31018-177-472 RD 1/8T 4.7K-J R108 31018-177-470 RD 1/8T 47-J R109 31018-177-104 RD 1/8T 100K-J R110 31018-177-104 RD 1/8T 100K-J R111 31018-177-221 RD 1/8T 220-J R112 31018-177-563 RD 1/8T 56K-J R113 31018-177-154 RD 1/8T 150K-J R114 31018-177-223 RD 1/8T 22K-J R115 31018-177-333 RD 1/8T 33K-J R116 31018-177-102 RD 1/8T 1K-J R117 31018-177-391 RD 1/8T 390-J R118 31018-177-221 RD 1/8T 220-J R120 31018-177-102 RD 1/8T 1K-J R121 31018-177-271 RD 1/8T 270-J R122 31018-177-223 RD 1/8T 22K-J R123 31018-177-822 RD 1/8T 8.2K-J R124 31018-177-562 RD 1/8T 5.6K-J			R201 31018-177-162 RD 1/8T 1.6K-J R202 31018-177-202 RD 1/8T 2K-J R203 31018-177-221 RD 1/8T 220-J R206 31018-177-821 RD 1/8T 820-J R208 31018-177-562 RD 1/8T 5.6K-J R209 31018-177-913 RD 1/8T 91K-J R214 31018-177-391 RD 1/8T 390-J R215 31018-377-471 RD 1/2T 470-J **R224 31049-315-101 RS 2P 160-J **R225 31048-527-220 RS 2P 22-J R301 31018-177-331 RD 1/8T 330-J R302 31018-377-224 RD 1/2T 220K-J R303 31018-177-472 RD 1/8T 4.7K-J R304 31018-177-393 RD 1/8T 39K-J R305 31018-377-684 RD 1/2T 680K-J R307 31018-177-331 RD 1/8T 330-J **R308 31057-002-010 RF 1/2T 1-J R309 31018-177-823 RD 1/8T 82K-J **R310 31048-363-303 RM 1/2T 330K-G R311 31018-376-124 RD 1/2T 120K-G **R314 31047-176-152 RM 1/8T 1.5K-G R315 31018-177-100 RD 1/8T 10-J R316 31018-177-752 RD 1/8T 7.5K-J R317 31018-377-399 RD 1/2T 3.9-J R320 31018-177-333 RD 1/8T 33K-J **R401 31049-527-562 RS 2P 5.6K-J **R401A 31049-527-272 RS 2P 2.7K-J R402 31018-177-272 RD 1/8T 2.7K-J R403 31018-177-182 RD 1/8T 1.8K-J R404 31018-177-331 RD 1/8T 330-J R405 31018-177-681 RD 1/8T 680-J R406 31018-377-752 RD 1/2T 7.5K-J R406A 31018-377-822 RD 1P 2T 8.2K-J **R407 31049-527-272 RS 2 2.7K-J R408 31018-377-122 RD 1/2T 1.2K-J R408A 31018-377-272 RD 1P 2T 2.7K-J **R414 31059-003-100 RF 1 1K **R415 31049-101-350 RS 1P 1K-J		

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**R416	31049-311-600	RM 1/2P 133K-F	R901	31018-177-102	R D 1/8T 1K-J
**R417	31059-428-047	RF 1P 0.47-K	R902	31018-377-120	RD 1/2T 12-J
**R418	31048-361-001	RM 1/2T 1K-G	**R904	31049-103-820	RS 2P 12K-J
**R419	31049-527-272	RS 2P 2.7K-J	**R905	31049-103-820	RS 2P 12K-J
R421	31018-377-183	RD 1/2T 18K-J	R906	31018-177-752	RD 1/8T 7.5K-J
**R425	A1004-0336	RS 2 N S 750-J 75R	R907	31018-177-103	RD 1/8T 10K-J
**R425A	A1004-0336	RS 2 N S 750-J 75R	R908	31018-377-152	RD 1/2T 1.5K-J
R444	31018-377-330	RD 1/2T 33-J	R909	31018-377-752	RD 1/2T 7.5K-J
**R445	A1000-0660	RD 1/2T (S) R39-K 0.39R	R910	31018-377-752	RD 1/2T 7.5K-J
R502	31018-177-101	RD 1/8T 100-J	R911	31018-177-103	RD 1/8T 10K-J
R508	31018-377-514	RD 1/2T 510K-J	R912	31018-177-682	RD 1/8T 6.8K-J
R510	31018-177-561	RD 1/8T 560-J	R913	31018-177-223	RD 1/8T 22K-J
R511	31018-177-561	RD 1/8T 560-J	R914	31018-177-560	RD 1/8T 56-J
R512	31018-177-561	RD 1/8T 560-J	R915	31018-177-823	RD 1/8T 82K-J
R513	31018-377-395	RD 1/2T 3.9M-J	R916	31018-177-823	RD 1/8T 82K-J
R516	31018-377-471	RD 1/2T 470-J	R917	31018-177-823	RD 1/8T 82K-J
R517	31018-177-222	RD 1/8T 2.2K-J	R918	31018-177-823	RD 1/8T 82K-J
R518	31018-177-272	RD 1/8T 2.7K-J	R919	31018-177-823	RD 1/8T 82K-J
R530	31018-177-101	RD 1/8T 100-J	R920	31018-177-823	RD 1/8T 82K-J
R531	31018-177-151	RD 1/8T 150-J	R921	31018-177-103	RD 1/8T 10K-J
R532	31018-177-151	RD 1/8T 150-J	R924	31018-177-823	RD 1/8T 82K-J
R533	31018-177-151	RD 1/8T 150-J	R925	31018-177-153	RD 1/8T 15K-J
R534	31018-177-102	RD 1/8T 1K-J	R926	31018-177-102	RD 1/8T 1K-J
R535	31018-177-102	RD 1/8T 1K-J	R931	31018-177-243	RD 1/8T 24K-J
R536	31018-177-102	RD 1/8T 1K-J	R933	31018-177-472	RD 1/8T 4.7K-J
**R537	31049-101-409	RS 1 4 15K-J	R934	31018-177-222	RD 1/8T 2.2K-J
**R538	31049-101-409	RS 1P 15K-J	R935	31018-177-153	RD 1/8T 15K-J
**R539	31049-101-409	RS 1P 15K-J	R937	31018-177-122	RD 1/8T 1.2K-J
**R540	31028-328-472	RC 1/2T 4.7K-K	**R939	31049-527-820	RS 2P 82-J
**R541	31028-328-472	RC 1/2T 4.7K-K	R940	31018-177-513	RD 1/8T 51K-J
**R542	31028-328-472	RC 1/2T 4.7K-K	R941	31018-177-102	RD 1/8T 1K-J
R543	31018-177-472	RD 1/8T 4.7K-J	R942	31018-177-123	RD 1/8T 12K-J
R544	31018-377-331	RD 1 4 2T 330-J	R944	31018-177-183	RD 1/8T 18K-J
**R545	31059-003-100	RF 1 1-K	R946	31018-177-203	RD 1/8T 20K-J
R546	31018-177-472	RD 1/8T 4.7K-J	R947	31018-177-393	RD 1/8T 39K-J
R547	31018-377-331	RD 1/2T 330-J	R949	31018-177-433	RD 1/8T 43K-J
R548	31018-377-331	RD 1/2T 330-J	R952	31018-177-102	RD 1/8T 1K-J
R549	31018-177-472	RD 1 4 8T 4.7K-J	R953	31018-177-103	RD 1/8T 10K-J
**R599	31049-103-510	RS 2 47-J	R956	31018-177-202	RD 1/8T 2K-J
**R600	31057-577-561	RF 2T 560-J/RF 2S 560-J	R957	31018-177-102	RD 1/8T 1K-J
R601	31018-177-681	RD 1/8T 680-J	R958	31018-177-331	RD 1/8T 330-J
R602	31018-177-102	RD 1/8T 1K-J	R960	31018-177-472	RD 1/8T 4.7K-J
R603	31018-177-102	RD 1/8T 1K-J	R961	31018-177-681	RD 1/8T 680-J
R604	31018-177-512	RD 1/8T 5.1K-J	R962	31018-177-681	RD 1/8T 680-J
R605	31018-177-202	RD 1/8T 2K-J	R964	31018-177-682	RD 1/8T 6.8K-J
R606	31018-177-622	RD 1/8T 6.2K-J	R965	31018-177-122	RD 1/8T 1.2K-J
R607	31018-377-274	RD 1/2T 270K-J	R966	31018-177-223	RD 1/8T 22K-J
**R608	31049-101-360	RS 1P 12K-J	R967	31018-177-363	RD 1/8T 36K-J
**R699	31049-101-130	RS 1P 22-J	R968	31018-177-153	RD 1/8T 15K-J
**R802	31039-787-339	RW 10H 3.3-J	R970	31018-177-821	RD 1/8T 820-J
R803A	31018-377-224	RD 1/2T 220K-J	R971	31018-177-821	RD 1/8T 820-J
R803B	31018-377-224	RD 1/2T 220K-J	R972	31018-177-821	RD 1/8T 820-J
R804	31018-377-221	RD 1/2T 220-J	R973	31018-177-332	RD 1/8T 3.3K-J
R805	31018-377-229	RD 1/2T 2.2-J	R974	31018-177-332	RD 1/8T 3.3K-J
**R806	31039-567-331	RW 5H 330-J	R975	31018-177-332	RD 1/8T 3.3K-J
**R808	31057-002-O 10	RF 1/2T 1-J	R976	31018-177-472	RD 1/8T 4.7K-J
R888A	31018-377-514	RD 1/2T 510K-J			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
R981	31018-177-333	RD 1/8T 33K-J	C101	31417-109-100	CK45 TAPG F 50V 102-Z
R982	31018-177-152	RD 1/8T 1.5K-J	C102	31417-109-100	CK45 TAPG F 50V 102-Z
**R990	31049-103-820	RS 2P 12K-J	C103	31417-109-140	CK45 TAPG F 50V 103-Z
R991	31018-177-102	RD 1/8T 1K-J	C105	31417-109-140	CK45 TAPG F 50V 103-Z
R992	31018-177-102	RD 1/8T 1K-J	C106	31417-104-290	CK45 TAPG B 50V 472-K
R993	31018-177-102	RD 1/8T 1K-J	C107	31407-105-660	CC45 (T) CH 50V 101-J
R994	31018-177-102	RD 1/8T 1K-J	C108	31407-105-660	CC45 (T) CH 50V 101-J
R995	31018-177-102	RD 1/8T 1K-J	C110	31417-109-140	CK45 TAPG F 50V 103-Z
R999	31018-177-103	RD 1/8T 10K-J	C111	31507-127-007	ECQ B1 H 1535 F3
RC15	31018-177-100	RD 1/8T 10-J	C112	31407-105-110	CC45 TAPG CH 50V 120-J
RC16	31018-177-100	RD 1/8T 10-J	C114	31417-109-140	CK45 TAPG F 50V 103-Z
RC17	31018-177-100	RD 1/8T 10-J	C151	31607-402-240	CE04W TAPG 50V 4.7M
RJ106	31018-177-223	RD 1/8T 22K-J	C152	31607-402-240	CE04W TAPG 50V 4.7M
RV001	31018-377-680	RD 1/2T 68-J	**C153	A1102-0298	CF 922 N 63V T 104-J -4I
**RV002	31059-002-040	RF 1/2P 68-J	C154	31607-401-510	CE04W TAPG 16V 1000U-M
RV003	31018-177-154	RD 1/8T 150K-J	C155	31607-402-070	CE04W TAPG 35V 22M
RV004	31018-177-563	RD 1/8T 56K-J	C156	31607-401-500	CE04W TAPG 16V 470M-M
RV005	31018-177-153	RD 1/8T 15K-J	C201	31407-105-660	CC45 (T) CH 50V 101-J
RV006	31018-177-331	RD 1/8T 330-J	C202	31407-105-090	CC45 (T) CH 50V 100-C
**RV007	31028-328-475	RC 1/2T 4.7M-K	C251	31607-401-430	CE04W TAPG 25V 10M
RV010	31018-177-750	RD 1/8T 75-J	C252	31607-401-430	CE04W TAPG 25V 10M
RV011	31018-177-752	RD 1/8T 7.5K-J	C253	31507-127-006	ECQ B1 H 1035 F3
RVO 12	31018-177-222	RD 1/8T 2.2K-J	C254	31607-402-720	CE04W TAPG 50V 2.2M-M
RV013	31018-177-470	RD 1/8T 47-J	C255	31507-127-006	ECQ B1 H 1035 F3
RV021	31018-177-681	RD 1/8T 680-J	C301	31507-127-001	ECQ B1 H 1525 F3
RV022	31018-177-471	RD 1/8T 470-J	C302	31507-127-023	ECQ B1 H 1225 F3
RV023	31018-177-102	RD 1/8T 1K-J	C303	31507-127-016	ECQ B1 H 4725 F3
RV024	31018-177-622	RD 1/8T 6.2K-J	**C304	A1102-0294	CF 922 N 63V T 473-J -4I
RV025	31018-177-103	RD 1/8T 10K-J	**C305	A1102-0297	CF 922 N 63V T 513-J -4I
RV026	31018-177-121	RD 1/8T 120-J	**C307	A1102-0294	CF 922 N 63V T 473-J -4I
RV027	31018-177-132	RD 1/8T 1.3K-J	C309	31507-127-006	ECQ B1 H 1035 F3
RV028	31018-177-183	RD 1/8T 18K-J	C311	31417-468-681	CK45 TAPG B500V 681-K
RV029	31018-177-333	RD 1/8T 33K-J	**C320	A1102-0295	CF 922 N 63V T 683-J -4I
RV030	31018-177-302	RD 1/8T 3K-J	**C321	A1102-0298	CF 922 N 63V T 104-J -4I
RV031	31018-177-822	RD 1/8T 8.2K-J	C351	31607-902-250	CE04W TAPG 50V 0.22M
RV032	31018-177-393	RD 1/8T 39K-J	C352	31607-402-100	CE04W TAPG 35V 100M-M
RV034	31018-177-102	RD 1/8T 1K-J	C353	31607-403-970	CE04W TAPG 25V 1000M-M
RV035	31018-177-221	RD 1/8T 220-J	C354	31607-402-250	CE04W TAPG 50V 10M
RV036	31018-177-123	RD 1/8T 12K-J	C355	31607-402-130	CE04W TAPG 35V 470M-M
RV037	31018-177-183	RD 1/8T 18K-J	C356	31607-402-570	CE04W TAPG 50V 1M
RV038	31018-177-302	RD 1/8T 3K-J	C357	31607-402-570	CE04W TAPG 50V 1M
RV039	31018-177-561	RD 1/8T 560-J	C399	31417-468-331	CK45 TAPG B500V 331-K
RV040	31018-177-152	RD 1/8T 1.5K-J	C401	31507-127-009	ECQ B1 H 3335 F3
RV041	31018-177-472	RD 1/8T 4.7K-J	**C402	A1102-0294	CF 922 N 63V T 473-J -4C
VARIABLE RESISTORS			C403	31507-127-005	ECQ B1 H 8225 F3
VR101	31249-128-023	RH0638C100-472 4.7KB	C404	31417-109-100	CK45 TAPG F 50V 102-Z
VR203	31249-128-029	RH0638C100-473 47KB	C405	31417-106-170	CK45 TAPG B 500V 222-K
VR301	31249-128-015	RH0638C100-221 220B	C406	31417-106-090	CK45 TAPG B 500V 471-K
VR401	31249-128-015	RH0638C100-221 220B	**C407	31519-400-001	CFS 922M 1600V 0.0063-J
VR531	31249-128-015	RH0638C100-221 220B	C408	31417-901-400	CK45 (T) B2KV 561-K
VR532	31249-128-015	RH0638C100-221 220B	C409	31607-401-670	CE04W TAPG 25V 47M
VR533	31249-128-023	RH0638C100-472 4.7KB	C410	31607-401-670	CE04W TAPG 25V 47M
VR534	31249-128-023	RH0638C100-472 4.7KB	**C412	31517-390-502	CFS922M TAPG 250V 104-J
VR535	31249-128-023	RH0638C100-472 4.7KB	**C413	31518-333-334	CFS 922M 200V 0.33U-J
VRV01	31249-128-019	RH0638C100-102 1KB	C414	31417-106-090	CK45 TAPG B 500V 471-K
CAPACITORS			c451	31607-401-460	CE04W TAPG 16V 47M

Loc No	Supplier Parts No	Specification
C452	31607-402-210	CE04W TAPG 50V 1M
C456	31607-401-710	CE04W TAPG 25V 470M-M
C458	31607-403-490	CE04W TAPG 250V 10M-M
C497	31417-318-152	CK45 TAPG B 50V 152-K
C499	31417-468-561	CK45 TAPG B500V 561-K
C501	31407-105-260	CC45 (T) CH 50V 470-J
C502	31407-106-760	CC45 (T) RH 50V 151-J
C504	31417-109-140	CK45 TAPG F 50V 103-z
C506	31407-105-180	CC45(T) CH 50V 220-J
C507	31507-127-007	ECO B1 H 1535 F3
C508	31417-104-070	CK45 TAPG B 50V 271-K
C509	31417-104-070	CK45 TAPG B 50V 271-K
C510	31417-104-070	CK45 TAPG B 50V 271-K
C531	31417-318-152	CK45 TAPG B 50V 152-K
C532	31417-318-152	CK45 TAPG B 50V 152-K
C533	31417-318-152	CK45 TAPG B 50V 152-K
C534	31417-767-102	CK45(T) B2KV 102-K
C535	31417-109-100	CK45 TAPG F 50V 102-Z
C536	31417-109-100	CK45 TAPG F 50V 102-Z
C537	31417-109-100	CK45 TAPG F 50V 102-Z
C551	31607-402-170	CE04W TAPG 50V 0.1U-L, L
C553	31607-402-230	CE04W TAPG 50V 3.3M
C554	31607-402-220	CE04W TAPG 50V 2.2M
C555	31607-401-670	CE04W TAPG 25V 47M
C556	31607-402-210	CE0IW TAPG 50V 1M
C557	31607-402-210	CE04W TAPG 50V 1M
C558	31417-109-140	CK45 TAPG F 50V 103-Z
C560	31607-401-690	CE04W TAPG 25V 220M-M
C561	31607-401-430	CE04W TAPG 25V 10M
C601	31407-106-150	CC45 (T) RH 50V 150-J
C602	31507-127-006	ECO B1 H 1035 F3
C603	31417-109-140	CK45 TAPG F 50V 103-Z
C606	31417-106-010	CK45 TAPG B 500V 101-K
C607	31417-104-330	CK45 TAPG B 50V 331-K
C651	31607-401-430	CE04W TAPG 25V 10M
C655	31607-403-210	CE04W TAPG 160V 10M-M
C656	31607-402-250	CE04W TAPG 50V 10M
C657	31607-403-210	CE04W TAPG 160V 10M-M
C701	31607-402-470	CE0IW TAPG 50V 47M-M(FR)
**C777	31467-001-001	CK45P TAPG E400V 222-M
**C801	31516-002-140	ECQ-E2A 224M N86 (TAPG
C803	31407-052-709	CC45 (T) CH 50V 070-C
C812	31417-767-102	CK45 (T) B2KV 102-K
**C850	A1102-0293	CF 922 IN 63V T 474-J -4b
C851	31607-403-250	CE04W TAPG 160V 100M-M
**C852	31609-403-840	CE04W 400V 220M 30X40
C900	31607-401-690	CE0IW TAPG 25V 620M-M
C901	31417-468-681	CK45 TAPG B500V 681-K
C902	31417-109-100	CK45 TAPG F 50V 102-Z
C905	31407-105-180	CC45 (T) CH 50V 220-J
C906	31407-105-180	CC45 (T) CH 50V 220-J
C907	31407-105-270	CC45 (T) CH 50V 300-J
C908	31417-109-100	CK45 TAPG F 50V 102-Z
C909	31407-105-150	CC45(T) CH 50V 160-J
C912	31407-105-660	CC45(T) CH 50V 101-J
C919	31417-109-140	CK45 TAPG F 50V 103-Z
**C951	A1102-0298	CF 922 N 63V T 104-J -4b

Loc No	Supplier Part No	Specification
C952	31607-401-430	CE04W TAPG 25V 10M
C953	31607-401-290	CE04W TAPG 10V 220U
C954	31607-401-140	CE04W TAPG 6.3V 1000M-M
C955	31607-401-460	CE04W TAPG 16V 47M
C956	31607-402-200	CE04W TAPG 50V 0.47M
C957	31607-401-430	CE04W TAPG 25V 10M
C958	31607-401-430	CE04W TAPG 25V 10M
C959	31607-401-430	CE04W TAPG 25V 10M
C960	31607-402-250	CE01W TAPG 50V 10M
C961	31607-402-240	CE04W TAPG 50V 4.7M
C962	31607-401-430	CE04W TAPG 25V 10M
C963	31607-401-430	CE04W TAPG 25V 10M
C964	31607-401-430	CE04W TAPG 25V 10M
C965	31607-402-210	CE04W TAPG 50V 1M
C966	31417-104-070	CK45 TAPG B 50V 271-K
C970	31607-401-430	CE04W TAPG 25V 10M
C971	31507-127-016	ECQ B1 H 4725 F3
C972	31607-401-430	CE04W TAPG 25V 10M
**C973	A1102-0298	CF 922 N 63V T 104-J -40
**CA101	31467-001-001	CK45P TAPG E400V 222-M
**CA102	31467-001-001	CK45P TAPG E400V 222-M
**CN901	31497-009-440	EXF-FP5331MDV(6P 331)
**CN902	31497-009-350	EXF-FP7 331MDV 8P 331 }
**CN903	31497-009-430	EXF-FP3 331MDV 4P 331 }
**CN904	31497-009-360	EXF-FP8 331MDV 9P 331 }
CV002	31417-109-140	CK45 TAPG F 50V 103-Z
CV003	31417-106-090	CK45 TAPG B 500V 471-K
**CV005	31467-001-001	CK45P TAPG E400V 222-M
CV051	31607-401-430	CE04W TAPG 25V 10M
CV052	31607-401-700	CE04W TAPG 25V 330M-M
CV053	31607-401-670	CE04W TAPG 25V 47M
CV055	31607-401-460	CE01W TAPG 16V 47M
**CV059	A1104-0521	CE 04 -40/85 50V T 330-N
CV060	31607-401-430	CE04W TAPG 25V 10M
CV061	31607-803-730	CE04W TAPG 50V 4.7M-NP
IC301	31417-104-330	CK45 TAPG B 50V 331-K
I C		
IC101	32119-102-131	CXA1110BS
IC501	32119-102-020	LA7625
**IC901	B4002-0302	Z8622704PSC-R1006/R1127
ICV01	32109-410-270	TC4066BP
TRANSISTORS		
Q101	32137-301-050	KSC 1674 TAPG)
Q201	32137-401-530	KSA 539-6 TAPG)/YTAM
Q203	32137-103-430	KSA 642-O TAPG)
**Q401	32137-301-530	KSC 2330-O TAPG)
Q501	32137-301-560	KSC 2331-Y TAPG)
Q531	32137-301-530	KSC 2330-O TAPG)
Q532	32137-301-530	KSC 2330-O TAPG)
Q533	32137-301-530	KSC 2330-O TAPG)
Q534	32137-301-530	KSC 2330-O TAPG)
Q535	32137-301-530	KSC 2330-O TAPG)
Q536	32137-301-530	KSC 2330-O TAPG)
Q601	32137-301-540	KSC 2330-Y TAPG)
**Q602	A4052-0053	KTA1657 20 6 1.5A 4MHZ

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**Q603	A4052-0059	KSC2073 25W 1.5A 4MHZ	D908	32167-406-480	1N4148 TAPG
Q901	32137-301-560	KSC 2331-Y(TAPG)	D909	32167-201-070	1N 4003 LTIN 4003
Q905	32137-301-720	KSC 815-Y(TAPG)/YTAM	D913	32167-406-480	1N4148 TAPG
Q907	32137-301-720	KSC 815-Y(TAPG)/YTAM	D914	32167-406-480	1N4148 TAPG
Q909	32137-301-720	KSC 815-Y(TAPG)/YTAM	D915	32167-406-480	1N4148 TAPG
9910	32137-301-720	KSC 815-Y(TAPG)/YTAM	D916	32167-406-480	1N4148 TAPG
Q911	32137-301-720	KSC 815-Y(TAPG)/YTAM	D971	32167-406-480	1N4148 TAPG
Q912	32137-301-720	KSC 815-Y(TAPG)/YTAM	DA00	32167-406-080	MTZ 5.1B
Q923	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV002	32167-201-170	TVR10G(TAPG)
QV001	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV003	32167-406-480	1N4148 TAPG
QV002	32137-301-720	KSC 815-Y(TAPG)/YTAM	DV004	32167-406-480	1N4148 TAPG
QV003	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD501	32167-406-150	MTZ 13A
QV004	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD901	32167-406-080	MTZ 5.1B
QV005	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD902	A4106-0128	MTZ6.8A-T72 6.29/6.63V
QV006	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD903	32167-406-080	MTZ 5.1B
QV007	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD904	32167-403-850	EOB 01-33(TAPG)
QV008	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD905	32167-406-130	MTZ 9.1B
QV009	32137-301-720	KSC 815-Y(TAPG)/YTAM	ZD906	32167-406-080	MTZ 5.1B
DIODES			ZD908	32167-406-150	MTZ 13A
D1	32167-408-080	EQAO2-06D/MTZ6.2B(TAPG)	PQSISTOR		
D2	32167-408-080	EQAO2-06D/MTZ6.2B(TAPG)	**R801	32189-609-390	2C18R
D201	32167-406-480	1N4148 TAPG	MODULE REMOCON		
D202	32167-406-480	1N4148 TAPG	PRE-AM	32199-411-002	SR-5CP
D203	32167-406-480	1N4148 TAPG	LED-GUIDE, ASSY		
D3	32167-201-070	1N 4003 6 LTIN 4003	LED/G	32306-101-020	DL-G2RA
D301	32167-408-080 32167-201-170	EQAO2-06D/MTZ6.2B(TAPG)	PHOTO-COUPLER		
D302	32167-201-170	TVR10G TAPG	**PC001	32309-024-040	LTV817B
D303	32167-406-480	1N4148 TAPG	**PC002	32309-025-000	HP6N136-020 8DIP 5KV
D304	32167-406-480	184148 TAPG	COILS		
D305	32167-406-480	1N4148 TAPG	**CN89	32479-029-380	14"/230HM/T100/L940(L/C)
**D401	32167-201-170	TVR10G(TAPG)	L101	32427-904-918	AL02-1R0K
**D406	32167-201-170	TVR10G(TAPG)	L102	32427-904-944	AL02 R56-M
**D408	32167-406-480	1N4148 TAPG	L103	32427-904-945	AL02 R80M(0.8UH)
**D409	32167-406-480	1N4148 TAPG	L111	32427-805-840	AL03 100-K
D502	32167-406-480	114148 TAPG	L201	32427-904-926	AL02-15(K(15UH)
D503	32167-406-480	1N4148 TAPG	L202	32429-903-810	100UH-K(50)
D601	32167-406-480	1N4148 TAPG	L301	32427-803-130	10UH-K APK(I
D699	32167-406-480	1N4148 TAPG	**L401	32427-904-924 32449-712-010	AL02-100K(10UH)
**D800	32167-401-041 32167-208-580	ENC431D-10A(12-12TAPG)	**L402		
**D801	32167-208-580	ERB 12-06 TA	**L403	32427-904-924	AL02-100K(10UH)
**D802	32167-208-580	ERB 12-06 TAPG	**L407	32426-226-190	82UH-K6ROBOT:0.8A)
**D803	32167-208-580	ERB 12-06 TAPG	L501	32427-904-924	AL02-1 OK(10UH)
**D804	32167-208-580	ERB 12-06 TAPG	L532	32427-805-858	AL03 331-K
**D805	32167-207-120 32167-201-170	TVR10G(TAPG)	L602	32427-805-878	AL02 220-J
**D807	32167-201-170	TVR10G(TAPG)	**L801	32429-633D160	6MH-SQ1913
**D808	32167-401-850	R-2KY(TAPG)	L901	32427-805-550	47UH-K TAPG
D900	32167-201-170	TVR10G(TAPG)	L902	32427-904-924	AL02-100K(10UH)
D901	32167-406-480	1N4148 TAPG	L903	32427-904-924	AL02-100K(10UH)
D902	32167-406-480	1N4148 TAPG	LA00	32427-805-840	AL03 100-K
D904	32167-406-480	1N4148 TAPG	LA01	32427-805-840	AL03 100-K
D905	32167-406-480	1N4148 TAPG	LVO1	32427-904-924	AL02-100K(10UH)
D906	32167-406-480	1N4148 TAPG			
D907	32167-406-480	1N4148 TAPG			

Loc No	Supplier Parts No	Specification
	DELAY-LINES	
X201	32466-200-013	SDL401TN
	TRANS-FLY BACK	
*T444	32859-153-410	FCK-1415EL (L/C)
	TRANS	
L105	32707-200-014	45.75MHZ/2(7M/M)
L106	32707-200-013	45.75MHZ(7M/M)
*T401	32846-070-006	130MH/105UH ST
T601	32786-550-080	200:40EM 24MM ST
*T801	32899-001-090	P:90-260,S:95V ER3541
*T802	32999-001-000	(486UH:28.8UH
*TV001	A1207-0004	EE1916 2MH 50HM ST
	CORE-FERRITES	
L404	34047-019-060	'3.5X6X1.0
L803	34047-019-060	3.5X6X1.0
L804	34047-019-060	3.5X6X1.0
	FILTERS	
*Z101	34529-700-019	F52LM
Z102	34527-700-025	SAF41MC80Z-TFO1
Z201	34527-460-001	TPS4.5MCTF21
*Z601	B1243-00711	BP 4.5M SFSH4.5MCB-TF21
Z602	34527-460-064	CDA4.5ME30 TF21
	CRYSTALS	
X901	34537-001-003	4.0MHZ
X501	34539-013-010	HC-18/U(3.579545MHZ)
	RESONATOR	
x401	34539-300-006	CSB503F5
	FUSE	
*F801	34709-087-020	T/L 250V 4A 20M/M
	TUNER	
*H901	A1292-0040	TECC1880PA09C(S) (L/C:
	SOCKET-CRT	
*V999	A3047-0013	ISMS01S P114.3 HI-FOCUS
	MISCELLANEOUS	
ANT/B	32079-0033-000	100PFX470PF100MM (L/C:
PC801	33053-817-08	DW-006/MSP-10/SPC-2
CN81A	33054-834-018	P1XP1 DIW 1617#22 400
CNO1	33058-372-014	B10XB10/F/350
EYE-P	33104-107-210	BST 2.8X2.0
EYE-P	33104-107-220	BSP 3.2X2.7(2.2)
JA01	A3040-0134	P13.5 UL-PJ 1P MONO-12.1
JA02	A3040-0135	P13.5 UL-PJ 1P MONO-12.1
CN81	33124-111-100	1P AUTO
CN81A	33124-111-100	1P AUTO

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
LEAD/C	33058-003-012	S3 2 F/300			ASSY-H/S, VERT(HORI)
**SPK	34209-200-020	05 6 1 as RA, 8R, 3W			*3Y82-70059-010 31124-0014-000, 2SD171Y
		ASSY-TRANSMITTER			ASSY-H/S, POWER
	*3F14-00034-900	TM34 RM238 33 E S/S BR			*3Y83-70029-010 31122-0017-070, STR5010
		CT-3362V/1MACX(OPTION)			ASSY-SPEAKER
		BUYER : MABUHAY (94.11.07)			*3Y73-00011-010 5902BR3W(2), L300, WIRE
		ASSY-PWB MAIN			LEAD/C 33058-003-012 S3 2)/ 700
	*3X30-02481Y060	CT-3362V/1MACX, CKC50HM	**SPK	34209-169-140	59 6 2 BR 8 R 2W
		RESISTORS			ASSY-ACCESSORY
**R400	31048-527-511	RS 2P 510-J	I/B	34709-0011-000	W/P120(G) CT-3362V ENG
R409	31018-177-153	RD 1/8T 15K-J			
**R410	31049-175-682	RM 1/8T 6.8K-F			
**R411	31049-311-059	RM 1/2P 120K-F			
R412	31018-377-104	RD 1/2T 100K-J			
R413	31018-377-474	RD 1/2T 470K-J			
**R425	31046-567-750	RS 2T 75-J AUTO			
**R425A	31046-567-750	RS 2T 75-J AUTO			
**R669	31049-101-130	RS 1P 22-J			
		CAPACITORS			
BOT		(T) B2KV 561-K			
BOT	31417-767-102	CK45 (T) B2KV 102-K			
C153	31607-402-200	CE04W TAPG 50V 0.47M			
**C403	A1102-0294	CF 922 N 63V T 473-J -4C			
C411	31417-109-140	CK45 TAPG 50V 103-Z			
C454	31607-401-450	CE04W TAPG 16V 33M			
C455	31607-403-580	CE04W TAPG 315V 2.2M-M			
C850	31607-803-280	CE04W TAPG 50V 10-M(NP)			
		TRANSISTOR			
9403	32137-401-530	KSA539-Y(TAPG)/YTAM			
		DIODES			
**D400	B4102-0046	RGPI0J-5701 600V 45A			
D402	32167-201-170	TVR10G TAPG			
D801	32167-201-650	ERC13-68V1 TAPG			
D802	32167-201-650	ERC13-08V1 TAPG			
D803	32167-201-650	ERC13-08V1 TAPG			
D804	32167-201-650	ERC13-08V1 T(TPG)			
**ZD403	32167-408-080	EQA02-06D/MTZ6.2B(TAPG)			
		MISCELLANEOUS			
GT-PIN	33124-205-001	OM			
CN89	33124-205-003	2P 10MM			
PA08	33124-205-007	4P 6-12.5-14MM			
NT0049	34503-0100-000	TETRON PAPER 90(G) ALL			
H/WIRE	37158-230-061	2S-3X6 FE FZY			
		ASSY-H/S, VERT			
	*3Y82-70058-010	31124-0014-000, KA2131			

2-3. Electrical Parts List

ABBREVIATIONS : CC C-CERAMIC
CE C-ELECTROLYTIC
 CFS C-M, POLYESTER
 CR C-CERAMIC, **HK**
CQ C-POLYPROPYLENE, POLYESTER
 CS C-TANTALIUM, SOLID

RC	R-COMPOSITION
RD	R-CARBON
RF	R-FUSIBLE
RM	R-METAL, FILM
RP	R-CEMENT WIRE
RS	R-METAL, OXIDE

NOTE : The items with "*" are usually out of stock since they are seldom required for the routine service. There may be some anticipated delay when you order these items.

S.N.A. = Service Not Available , L/C = **Local** Purchase

The components identified by mark ******* are critical for safety. Replace only with Supplier part number specified.

When **indicating** parts by location number, Please include the PWB names
(PWB = Printed Writing Board)

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
ASSY-PWB MAIN BUYER: ANTARES ('94.08.25)					
*3X30-02480Y020 CT-5062V/1ANCX (S.N.A)					
PWB	36029-0146-000 T1.6 W330	L245 (S.N.A)			
RESISTORS					
JO48	31018-177-102	RD 1/8T 1K-J	R203	31018-177-221	RD 1/8T 220-J
JO49	31018-177-102	RD 1/8T 1K-J	R206	31018-177-821	RD 1/8T 820-J
JO55	31018-177-563	RD 1/8T 56K-J	R208	31018-177-562	RD 1/8T 5.6K-J
5131	31018-177-221	RD 1/8T 220-J	R209	31018-177-683	RD 1/8T 68K-J
J132	31018-177-221	RD 1/8T 220-J	R210	31018-177-334	RD 1/8T 330K-J
5133	31018-177-221	RD 1/8T 220-J	R214	31018-177-391	RD 1/8T 390-J
R101	31018-177-101	RD 1/8T 100-J	R215	310 18-377-47 1	RD 1/2T 470-J
R102	31018-177-562	RD 1/8T 5.6K-J	**R224	31049-315-10 1	RS 2P 100-J
R103	31018-177-122	RD 1/8T 1.2K-J	**R225	31048-527-220	Rs 2P 22-J
R104	31018-177-330	RD 1/8T 33-J	R301	31018-177-331	RD 1/8T 330-J
R105	31018-177-681	RD 1/8T 680-J	R302	31018-377-224	RD 1/2T 220K-J
R106	31018-177-101	RD 1/8T 100-J	R303	31018-177-472	RD 1/8T 4.7K-J
R107	31018-177-472	RD 1/8T 4.7K-J	R304	31018-177-393	RD 1/8T 39K-J
R108	31018-177-470	RD 1/8T 47-J	R305	31018-377-684	RD 1/2T 680K-J
R109	31018-177-104	RD 1/8T 100K-J	R307	31018-177-331	RD 1/8T 330-J
R110	31018-177-104	RD 1/8T 100K-J	**R308	31057-002-010	RF 1/2T 1-J
R111	31018-177-221	RD 1/8T 220-J	R309	31018-177-393	RD 1/8T 39K-J
R112	31018-177-563	RD 1/8T 56K-J	**R310	31048-363-903	RM 1/2T 390K-G
R113	31018-177-154	RD 1/8T 150K-J	R311	31018-376-124	RD 1/2T 120K-G
R114	31018-177-223	RD 1/8T 22K-J	**R314	31047-176-152	RM 1/8T 1.5K-G
R115	31018-177-333	RD 1/8T 33K-J	R315	31018-177-680	RD 1/8T 68-J
R116	31018-177-102	RD 1/8T 1K-J	R316	31018-177-682	RD 1/8T 6.8K-J
R117	31018-177-391	RD 1/8T 390-J	**R317	A1000-0398	RD 1/2 (S) 3R3-J 3.3R
R118	31018-177-221	RD 1/8T 220-J	R320	31018-177-333	RD 1/8T 330-J
R120	31018-177-102	RD 1/8T 1K-J	**R401	31049-527-562	RS 2P 5.6K-J
R121	31018-177-271	RD 1/8T 270-J	**R401A	31049-527-272	RS 2P 2.7K-J
R122	31018-177-223	RD 1/8T 22K-J	R402	31018-177-272	RD 1/8T 2.7K-J
R123	31018-177-822	RD 1/8T 8.2K-J	R403	31018-177-332	RD 1/8T 3.3K-J
R124	31018-177-562	RD 1/8T 5.6K-J	R404	31018-177-331	RD 1/8T 330-J
R201	31018-177-162	RD 1/8T 1.6K-J	R405	31018-177-681	RD 1/8T 680-J
R202	31018-177-202	RD 1/8T 2K-J	R406	31018-377-752	RD 1/2T 7.5K-J
			R406A	31018-377-822	RD 1/2T 8.2K-J
			**R407	31049-315-302	RS 2P 3.3K-J
			R408	31018-377-122	RD 1/2T 1.2K-J
			R408A	310 18-377-272	RD 1/2T 2.7K-J
			**R414	31059-003-100	RF 1P 1K
			**R415	31049-101-350	RS 1P 1K-J
			**R416	31049-375-154	
			**R417	31057-201-025	RM 1/2T 150K-F
					RF 1T 0 47-K

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**R418			R902	31018-377-120	RD 1/2T 12-J
**R419	31049-276-102 31049-315-302 RM RS	13.3K-JK-G	**R904	31049-103-820	RS 2P 12K-J
R421	31018-377-183	RD 1/2T 18K-J	**R905	31049-103-820	RS 2P 12K-J
**R425	31046-567-750	RS 2T 75-J AUTO	R906	31018-177-752	RD 1/8T 7.5K-J
**R425A	31046-567-750	RS 2T 75-J AUTO	R907	31018-177-103	RD 1/8T 10K-J
R444	31018-377-330	RD 1/2T 33-J	R908	31018-377-152	RD 1/2T 1.5K-J
**R445	A1000-0660	RD 1/2T(S) R39-K 0.39R	R909	31018-377-752	RD 1/2T 7.5K-J
R502	31018-177-101	RD 1/8T 100-J	R910	31018-377-752	RD 1/2T 7.5K-J
R508	31018-377-514	RD 1/2T 510K-J	R911	31018-177-103	RD 1/8T 10K-J
R510	31018-177-561	RD 1/8T 560-J	R912	31018-177-682	RD 1/8T 6.8K-J
R511	31018-177-561	RD 1/8T 560-J	R913	31018-177-223	RD 1/8T 22K-J
R512	31018-177-561	RD 1/8T 560-J	R914	31018-177-560	RD 1/8T 56-J
R513	31018-377-395	RD 1/2T 3.9M-J	R915	31018-177-823	RD 1/8T 82K-J
R516	31018-377-471	RD 1/2T 470-J	R916	31018-177-823	RD 1/8T 82K-J
R517	31018-177-222	RD 1/8T 2.2K-J	R917	31018-177-823	RD 1/8T 82K-J
R518	31018-177-272	RD 1/8T 2.7K-J	R918	31018-177-823	RD 1/8T 82K-J
R530	31018-177-101	RD 1/8T 100-J	R919	31018-177-823	RD 1/8T 82K-J
R531	31018-177-151	RD 1/8T 150-J	R920	31018-177-823	RD 1/8T 82K-J
R532	31018-177-151	RD 1/8T 150-J	R921	31018-177-103	RD 1/8T 10K-J
R533	31018-177-151	RD 1/8T 150-J	R924	31018-177-823	RD 1/8T 82K-J
R534	31018-177-102	RD 1/8T 1K-J	R925	31018-177-153	RD 1/8T 15K-J
R535	31018-177-102	RD 1/8T 1K-J	R926	31018-177-102	RD 1/8T 1K-J
R536	31018-177-102	RD 1/8T 1K-J	R931	31018-177-243	RD 1/8T 24K-J
**R537	31049-101-409	RS 1P 15K-J	R933	31018-177-222	RD 1/8T 2.2K-J
**R538	31049-101-409	RS 1P 15K-J	R934	31018-177-333	RD 1/8T 33K-J
**R539	31049-101-409	RS 1P 15K-J	R935	31018-177-153	RD 1/8T 15K-J
**R540	31028-328-472	RC 1/2T 4.7K-K	R937	31018-177-113	RD 1/8T 11K-J
**R541	31028-328-472	RC 1/2T 4.7K-K	**R939	31049-527-820	RS 2P 82-J
**R542	31028-328-472	RC 1/2T 4.7K-K	R940	31018-177-513	RD 1/8T 51K-J
R543	31018-177-472	RD 1/8T 4.7K-J	R941	31018-177-102	RD 1/8T 1K-J
R544	31018-377-331	RD 1/2T 330-J	R942	31018-177-123	RD 1/8T 12K-J
**R545	31059-004-019	RF 2P 1.9-J	R944	31018-177-273	RD 1/8T 27K-J
R546	31018-177-472	RD 1/8T 4.7K-J	R946	31018-177-203	RD 1/8T 20K-J
R547	31018-377-331	RD 1/2T 330-J	R947	31018-177-393	RD 1/8T 39K-J
R548	31018-377-331	RD 1/2T 330-J	R949	31018-177-363	RD 1/8T 36K-J
R549	31018-177-472	RD 1/8T 4.7K-J	R952	31018-177-102	RD 1/8T 1K-J
**R599	31049-103-510	RS 2P 47-J	R953	31018-177-103	RD 1/8T 10K-J
**R600	31057-577-561	RF 2T 560-J/RF 2S 560-J	R956	31018-177-202	RD 1/8T 2K-J
R601	31018-177-681	RD 1/8T 680-J	R957	31018-177-102	RD 1/8T 1K-J
R602	31018-177-102	RD 1/8T 1K-J	R958	31018-177-331	RD 1/8T 330-J
R603	31018-177-102	RD 1/8T 1K-J	R960	31018-177-472	RD 1/8T 4.7K-J
R604	31018-177-512	RD 1/8T 5.1K-J	R961	31018-377-681	RD 1/2T 680-J
R605	31018-177-202	RD 1/8T 2K-J	R962	31018-177-681	RD 1/8T 680-J
R606	31018-177-622	RD 1/8T 6.2K-J	R964	31018-177-682	RD 1/8T 6.8K-J
R607	31018-377-274	RD 1/2T 270K-J	R965	31018-177-122	RD 1/8T 1.2K-J
**R608	31049-101-360	RS 1P 12K-J	R966	31018-177-183	RD 1/8T 18K-J
**R699	31049-101-130	RS 1P 22-J	R967	31018-177-272	RD 1/8T 2.7K-J
**R802	31039-787-339	RW 10H 3.3-J	R968	31018-177-822	RD 1/8T 8.2K-J
R803A	31018-377-224	RD 1/2T 220K-J	R970	31018-177-821	RD 1/8T 820-J
R803B	31018-377-224	RD 1/2T 220K-J	R971	31018-177-821	RD 1/8T 820-J
R804	31018-377-221	RD 1/2T 220-J	R972	31018-177-821	RD 1/8T 820-J
R805	31018-377-229	RD 1/2T 2.2-J	R973	31018-177-332	RD 1/8T 3.3K-J
**R806	31039-567-331	RW 5H 330-J	R974	31018-177-332	RD 1/8T 3.3K-J
**R808	31057-002-010	RF 1/2T 1-J	R975	31018-177-332	RD 1/8T 3.3K-J
R888A	31018-377-514	RD 1/2T 510K-J	R976	31018-177-472	RD 1/8T 4.7K-J
R901	31018-177-102	RD 1/8T 1K-J	R981	31018-177-333	RD 1/8T 33K-J
			R982	31018-177-152	RD 1/8T 1.5K-J

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
*R990	31049-103-820 RS	2P 12K-J	C101	31417-109-100	CK45 TAPG F 50V 102-Z
R991	31018-177-102 RD	1/8T 1K-J	C102	31417-109-100	CK45 TAPG F 50V 102-Z
R992	31018-177-102 RD	1/8T 1K-J	C103	31417-109-140	CK45 TAPG F 50V 103-Z
R993	31018-177-102 RD	1/8T 1K-J	C105	31417-109-140	CK45 TAPG F 50V 103-Z
R994	31018-177-102 RD	1/8T 1K-J	C106	31417-104-290	CK45 TAPG B 50V 472-K
R995	31018-177-102 RD	1/8T 1K-J	C107	31407-105-660	CC45 (T) CH 50V 101-J
R999	31018-177-103 RD	1/8T 10K-J	C108	31407-105-660	CC45 (T) CH 50V 101-J
RC15	31018-177-100 RD	1/8T 10-J	C110	31417-109-140	CK45 TAPG F 50V 103-Z
RC16	31018-177-100 RD	1/8T 10-J	C111	31507-127-007	ECQ B1 H 1535 F3
RC17	31018-177-100 RD	1/8T 10-J	C112	31407-105-110	CC45 TAPG CH 50V 120-J
RJ106	31018-177-223 RD	1/8T 22K-J	C114	31417-109-140	CK45 TAPG F 50V 103-Z
RJ134	31018-177-104 RD	1/8T 100K-J	C151	31607-402-240	CEO4W TAPG 50V 4.7M
RV001	31018-377-680 RD	1/2T 68-J	C152	31607-402-240	CEO4W TAPG 50V 4.7M
*RV002	31057-002-040 RF	1/2T 68-J	C153	31507-127-012	ECQ B1 (V1) H 1045 F3 Z3
RV003	31018-177-154 RD	1/8T 150K-J	C154	31607-401-510	CEO4W TAPG 16V 1000 6M
RV004	31018-177-563 RD	1/8T 56K-J	C155	31607-402-070	CEO4W TAPG 35V 22M
RV005	31018-177-153 RD	1/8T 15K-J	C156	31607-401-500	CEO4W TAPG 16V 470M-M
RV006	31018-177-331 RD	1/8T 330-J	C201	31407-105-660	CC45 (T) CH 50V 101-J
*RV007	31028-328-475 RC	1/2T 4.7M-K	C202	31407-105-090	CC45 (T) CH 50V 100-C
RV010	31018-177-750 RD	1/8T 75-J	C251	31607-401-430	CEO4W TAPG 25V 10M
RV011	31018-177-752 RD	1/8T 7.5K-J	C252	31607-401-430	CEO4W TAPG 25V 10M
RV012	31018-177-222 RD	1/8T 2.2K-J	C253	31507-127-006	ECQ B1 H 1035 F3
RV013	31018-177-470 RD	1/8T 47-J	C254	31607-803-730	CEO4W TAPG 50V 4.7M-NP
RV021	31018-177-681 RD	1/8T 680-J	C255	31507-127-006	ECQ B1 H 1035 F3
RV022	31018-177-471 RD	1/8T 470-J	C301	31507-127-001	ECQ B1 H 1525 F3
RV023	31018-177-102 RD	1/8T 1K-J	C302	31507-127-023	ECQ B1 H 1225 F3
RV024	31018-177-622 RD	1/8T 6.2K-J	C303	31507-127-016	ECQ B1 H 4725 F3
RV025	31018-177-103 RD	1/8T 10K-J	C304	31507-127-010	ECQ B1 H 4735 F3
RV026	31018-177-121 RD	1/8T 120-J	C305	31507-127-011	ECQ B1 H 6835 F3
RV027	31018-177-132 RD	1/8T 1.3K-J	C307	31507-127-010	ECQ B1 H 4735 F3
RV028	31018-177-183 RD	1/8T 18K-J	C309	31507-127-006	ECQ B1 H 1035 F3
RV029	31018-177-333 RD	1/8T 33K-J	C311	31417-468-681	CK45 TAPG B500V 681-K
RV030	31018-177-302 RD	1/8T 3K-J	C320	31507-127-011	ECQ B1 H 6835 F3
RV031	31018-177-822 RD	1/8T 8.2K-J	C321	31507-127-011	ECQ B1 H 6835 F3
RV032	31018-177-393 RD	1/8T 39K-J	C351	31607-902-250	CEO4W TAPG 50V 0.22M
RV034	31018-177-102 RD	1/8T 1K-J	C352	31607-402-100	CEO4W TAPG 35V 100M-M
RV035	31018-177-221 RD	1/8T 220-J	C353	31607-403-970	CEO4W TAPG 25V 1000M-M
RV036	31018-177-123 RD	1/8T 12K-J	C354	31607-402-250	CEO4W TAPG 50V 10M
RV037	31018-177-183 RD	1/8T 18K-J	C355	31607-402-130	CEO4W TAPG 35V 470M-M
RV038	31018-177-302 RD	1/8T 3K-J	C356	31607-402-570	CEO4W TAPG 50V 1M
RV039	31018-377-561 RD	1/2T 560-J	C357	31607-402-570	CEO4W TAPG 50V 1M
RV040	31018-177-152 RD	1/8T 1.5K-J	C401	31507-127-009	ECQ B1 H 3335 F3
RV041	31018-177-472 RD	1/8T 4.7K-J	C402	31507-127-010	ECQ B1 H 4735 F3
VARIABLE RESISTORS			C403	31507-127-005	ECQ B1 H 822J F3
VR101	31249-128-023	RH0638C100-472 4.7KB	C404	31417-109-100	CK45 TAPG F 50V 102-Z
VR203	31249-128-029	RH0638C100-473 47KB	C405	31417-106-170	CK45 TAPG B 500V 222-K
VR301	31249-128-015	RH0638C100-221 220B	C406	31417-106-090	CK45 TAPG B 500V 471-K
VR401	31249-128-015	RH0638C100-221 220B	**C407	31519-400-008	CFS 922M 1600V 0.0074-H
VR531	31249-128-015	RH0638C100-221 220B	C409	31607-401-670	CEO4W TAPG 25V 47M
VR532	31249-128-015	RH0638C100-221 220B	C410	31607-401-670	CEO4W TAPG 25V 47M
VR533	31249-128-023	RH0638C100-472 4.7KB	**C412	31517-390-502	CFS922M TAPG 250V 104-J
VR534	31249-128-023	RH0638C100-472 4.7KB	**C413	31518-333-334	CFS 922M 200V 0.33U-J
VR535	31249-128-023	RH0638C100-472 4.7KB	C414	31417-106-090	CK45 TAPG B 500V 471-K
VRV01	31249-128-019	RH0638C100-102 1KB	C451	31607-401-460	CEO4W TAPG 16V 47M
CAPACITORS			C452	31607-402-210	CEO4W TAPG 50V 1M
			C456	31607-401-710	CEO4W TAPG 25V 470M-M
			C458	31607-403-490	CEO4W TAPG 250V 10M-M

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
C497	31417-318-152	CK45 TAPG B 50V 152-K	C955	31607-401-460	CE04W TAPG 16V 47M
C499	31417-468-561	CK45 TAPG B500V 561-K	C956	31607-402-200	CE04W TAPG 50V 0.47M
C501	31407-105-260	CC45(T) CH 50V 470-J	C957	31607-401-430	CE04W TAPG 25V 10M
C502	31407-106-760	CC45(T) RH 50V 151-J	C958	31607-401-430	CE04W TAPG 25V 10M
C504	31417-109-140	CK45 TAPG F 50V 103-Z	C959	31607-401-430	CE04W TAPG 25V 10M
C506	31407-105-180	CC45(T) CH 50V 220-J	C960	31607-402-250	CE04W TAPG 50V 10M
C507	31507-127-007	ECQ B1 H 1535 F3	C961	31607-402-240	CE04W TAPG 50V 4.7M
C508	31417-104-070	CK45 TAPG B 50V 271-K	C962	31607-401-430	CE04W TAPG 25V 10M
C509	31417-104-070	CK45 TAPG B 50V 271-K	C963	31607-401-430	CE04W TAPG 25V 10M
C510	31417-104-070	CK45 TAPG B 50V 271-K	C964	31607-401-430	CE04W TAPG 25V 10M
C531	31417-318-152	CK45 TAPG B 50V 152-K	C965	31607-402-210	CE04W TAPG 50V 1M
C532	31417-318-152	CK45 TAPG B 50V 152-K	C966	31417-104-070	CK45 TAPG B 50V 271-K
C533	31417-318-152	CK45 TAPG B 50V 152-K	C970	31607-401-430	CE04W TAPG 25V 10M
**C534	A1100-0783	CK 45F 3KV 103-Z CK45FZ1	C971	31507-127-016	ECQ B1 H 4725 F3
C535	31417-109-100	CK45 TAPG F 50V 102-Z	C973	31507-127-012	ECQ B1(V1)H 1045 F3(Z3)
C536	31417-109-100	CK45 TAPG F 50V 102-Z	**CA101	31467-001-001	CK45PTAPGE400V 22 6-M
C537	31417-109-100	CK45 TAPG F 50V 102-Z	**CA102	31467-001-001	CK45P TAPG E400V 222-M
C551	31607-402-170	CE04W TAPG 50V 0.1U-L,L	**CN901	31499-009-440	NCYBIH331M06/CN50V 6
C553	31607-402-230	CE04W TAPG 50V 3.3M	**CN902	31499-009-350	EXF-P7 331MW/NCYBIH331M
C554	31607-402-220	CE04W TAPG 50V 2.2M	**CN903	31499-009-430	NCYBIH331M04
C555	31607-401-670	CE04W TAPG 25V 47M	**CN904	31499-009-360	EXF-P8 331MW/NCYBIH331M
C556	31607-402-210	CE04W TAPG 50V 1M	CV002	31417-109-140	CK45 TAPG F 50V 103-Z
C557	31607-402-210	CE04W TAPG 50V 1M	CV003	31417-106-090	CK45 TAPG B 500V 471-K
C558	31417-109-140	CK45 TAPG F 50V 103-Z	**CV005	31467-001-001	CK45P TAPG E400V 222-M
C560	31607-401-690	CE04W TAPG 25V 220M-M	CV051	31607-401-430	CE04W TAPG 25V 10M
C561	31607-401-430	CE04W TAPG 25V 10M	CV052	31607-401-700	CE04W TAPG 25V 330M-M
C601	31407-106-150	CC45(T) RH 50V 150-J	CV053	31607-401-670	CE04W TAPG 25V 47M
C602	31507-127-006	ECQ B1 H 1035 F3	CV055	31607-401-460	CE04W TAPG 16V 47M
C603	31417-109-140	CK45 TAPG F 50V 103-Z	**CV059	A1104-0521	CE 04 -40/85 50V T 330-M
C606	31417-106-010	CK45 TAPG B 500V 101-K	CV060	31607-401-430	CE04W TAPG 25V 10M
C607	31417-104-330	CK45 TAPG B 50V 331-K	CV061	31607-803-730	CE04W TAPG 50V 4.7M-NP1
C651	31607-401-430	CE04W TAPG 25V 10M	I C		
C655	31607-403-210	CE04W TAPG 160V 10M-M	IC101	32119-102-131	CXA1110BSI
C656	31607-402-250	CE04W TAPG 50V 10M	IC501	32119-102-020	LA7625
C657	31607-403-210	CE04W TAPG 160V 10M-M	**IC901	B4002-0302	Z8622704PSC-R1006/R1127
C701	31607-402-470	CE04W TAPG 50V 47M-M(FR)	ICV01	32109-410-270	TC4066BP
**C777	31467-001-001	CK45P TAPG E400V 222-M	TRANSISTORS		
**C801	31516-002-140	ECQ-E2A 224M N86(TAPG)	Q101	32137-301-050	KSC 1674(TAPG)
C803	31407-052-709	CC45(T) CH 50V 070-C	Q201	32137-401-530	KSA 539-Y(TAPG)/YTAM
C812	31417-767-102	CK45(T) B2KV 102-K	Q203	32137-103-430	KSA 642-0(TAPG)
C850	31507-127-026	ECO-V1H 4745 Z3	**Q401	32137-301-530	KSC 2330-0(TAPG)
C851	31607-403-250	CE04W TAPG 160V 100M-M	Q501	32137-301-560	KSC 2331-Y(TAPG)
**C852	31609-403-840	CE04W 400V 220M(30X40)	Q531	32137-301-530	KSC 2330-0(TAPG)
C900	31607-401-690	CE04W TAPG 25V 220M-M	Q532	32137-301-530	KSC 2330-0(TAPG)
C901	31417-468-681	CK45 TAPG B500V 681-K	Q533	32137-301-530	KSC 2330-0(TAPG)
C902	31417-109-100	CK45 TAPG F 50V 102-Z	Q534	32137-301-530	KSC 2330-0(TAPG)
C905	31407-105-180	CC45(T) CH 50V 220-J	Q535	32137-301-530	KSC 2330-0(TAPG)
C906	31407-105-180	CC45(T) CH 50V 220-J	Q536	32137-301-530	KSC 2330-0(TAPG)
C907	31407-105-270	CC45(T) CH 50V 300-J	Q601	32137-301-540	KSC 2330-Y(TAPG)
C908	31417-109-100	CK45 TAPG F 50V 102-Z	**Q602	A4052-0053	KTA1657 20W 1.5A 4MHZ
C909	31407-105-150	CC45(T) CH 50V 160-J	**Q603	A4052-0059	KSC2073 25W 1.5A 4MHZ
C912	31407-105-660	CC45(T) CH 50V 101-J	Q901	32137-301-560	KSC 2331-Y(TAPG)
C919	31417-109-140	CK45 TAPG F 50V 103-Z	Q905	32137-301-720	KSC 815-Y(TAPG)/YTAM
C951	31507-127-012	ECQ B(V1)H 1045 F3(Z3)	Q907	32137-301-720	KSC 815-Y(TAPG)/YTAM
C952	31607-401-430	CE04W TAPG 25V 10M	Q909	32137-301-720	KSC 815-Y(TAPG)/YTAM
C953	31607-401-290	CE04W TAPG 10V 220U			
C954	31607-401-140	CE04W TAPG 6.3V 1000M-M			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
Q910	32137-301-720 KSC 815-Y	(TAPG)/YTAM	D916	32167-406-480	1N4148 TAPG
Q911	32137-301-720 KSC 815-Y	(TAPG)/YTAM	D971	32167-406-480	1N4148 TAPG
Q912	32137-301-720 KSC 815-Y	(TAPG)/YTAM	DA00	32167-406-080	MTZ 5.1B
Q923	32137-301-720 KSC 815-Y	(TAPG)/YTAM	DV002	32167-201-170	TVR10G(TAPG)
QV001	32137-301-720 KSC 815-Y	(TAPG)/YTAM	DV004	32167-406-480	1N4148 TAPG
QV002	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD501	32167-406-150	MTZ 13A
QV003	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD901	32167-406-080	MTZ 5.1B
QV004	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD902	A4106-0128	MTZ 6.29
QV005	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD903	32167-406-080	MTZ 5.1B
QV006	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD904	32167-403-850	EOB 01-33(TAPG)
QV007	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD905	32167-406-130	MTZ 9.1B
QV008	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD906	32167-406-080	MTZ 5.1B
QV009	32137-301-720 KSC 815-Y	(TAPG)/YTAM	ZD908	32167-406-150	MTZ 13A
DIODES			POSISTOR		
D1	32167-406-080	EQAO2-06D/MTZ6.2B(TAPG)	*R801	32189-609-390	2C18R
D2	32167-406-480	1N4148 TAPG	MODULE REMOCON		
D201	32167-406-480	1N4148 TAPG	PRE-AM	32196-411-002	SR-5CPST
D202	32167-406-480	1N4148 TAPG	LED-GUIDE, ASSY		
D203	32167-406-480	1N4148 TAPG	LED01	32306-101-020	DL-G2RA
D204	32167-201-32167-408-080	EQAO2-06D/MTZ6.2B(TAPG)	PHOTO-COUPLR		
D3	32167-201-170	TVR10G(TAPG)	*PC001	32309-024-040	LTV817B
D301	32167-201-170	TVR10G(TAPG)	*PC002	32309-025-000	HP6N136-020 8DIP 5KV
D302	32167-201-170	TVR10G(TAPG)	COILS		
D303	32167-406-480	1N4148 TAPG	*D-COIL	32479-029-480	20"/250HM/T125/L2220MM
D304	32167-406-480	1N4148 TAPG	L101	32427-904-918	AL02-100K
D305	32167-406-480	1N4148 TAPG	L102	32427-904-944	AL02 R56-M
*D401	32167-201-170	TVR10G(TAPG)	L103	32427-904-945	AL02 R80M(0.8UH)
*D406	32167-406-480	1N4148 TAPG	L111	32427-805-840	AL03 100-K
*D408	32167-406-480	1N4148 TAPG	L201	32427-904-926	AL02-150K(15UH)
**D409	32167-406-480	1N4148 TAPG	L202	32429-903-810	100UH-K(C-50)
D502	32167-406-480	11114148 TAPG	L301	32427-803-130	10UH-K TAPK
D503	32167-406-480	1N4148 TAPG	*L401	32427-904-924	AL02-100K(10UH)
D601	32167-406-480	1N4148 TAPG	*L402	32449-712-010	AL02-100K(10UH)
D699	32167-406-480	1N4148 TAPG	*L403	32427-904-924	AL02-100K(10UH)
D701	32167-207-12C	1R5GU41(TAPG)	*L407	32426-226-190	AL03 331-K
**D800	32167-401-04	ENC431D-10A(TAPG)	L501	32427-904-924	AL03 331-K
**D801	32167-201-65	ERC13-08V1(TAPG)	L532	32427-805-858	AL03 331-K
**D802	32167-201-65	ERC13-08V1(TAPG)	L602	32427-805-878	AL02 220-J
**D803	32167-201-65	ERC13-08V1(TAPG)	*L801	32429-633D160	6MH-SQ1913
*D804	32167-201-650	ERC13-08V1(TAPG)	L901	32427-805-550	47UH-K TAPG
*D805	32167-207-120	1R5GU41(TAPG)	L902	32427-904-924	AL02-100K(10UH)
*D806	32167-201-170	TVR10G(TAPG)	L903	32427-904-924	AL02-100K(10UH)
*D807	32167-201-170	TVR10G(TAPG)	LA00	32427-805-840	AL03 100-K
*D808	32167-401-850	R-2KY(TAPG)	LA01	32427-805-840	AL03 100-K
D900	32167-201-170	TVR10G(TAPG)	LW01	32427-904-924	AL02-100K(10UH)
D901	32167-406-480	1N4148 TAPG	DELAY-LINE		
D902	32167-406-480	1N4148 TAPG	X201	32466-200-013	SDL401TN
D904	32167-406-480	1N4148 TAPG	TRANS-FLY BACK		
D905	32167-406-480	1N4148 TAPG			
D906	32167-406-480	134148 TAPG			
D907	32167-406-480	114148 TAPG			
D908	32167-406-480	1N4148 TAPG			
D909	32167-201-070	1N 4003/LTIN 4003			
D913	32167-406-480	184148 TAPG			
D914	32167-406-480	1N4148 TAPG			
D915	32167-406-480	1N4148 TAPG			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**T444	32859-200-040	FCM-20A025	HOLD/C	33323-0001-000	PP VO BLK
	TRANS		PA1 1	33347-108-310	67094-003 3(UTO)
L105	32707-200-014	45.75MHZ/2(7M/M)	SW201	33549-007-010	JRS1301/KLR1301
L106	32707-200-013	45.75MHZ(7M/M)	SW02	33598-001-001	JTR-1104
**T401	32846-070-006	130MH/105UH ST	SW902	33606-101-025	KPT-2104-21 ST
T601	32786-550-080	200:40FM 24MM ST	SW901	33609-101-011	KPT-1112/JTM-1109F
**T801	32899-001-090	P:90-260, S:95V ER3541	NT0 139	34503-0100-000	TETTRONE PAPER 90 (G) ALI
**T802	32999-001-000	486UH: 28.8UH	S-CASE	34543-130-810	STPE TO. 25
TV001	A1207-0004	EE1916 2MH 50HM ST	GUID/L	36602-105-510	ABS HB NTR V2 MODEL
	CORE-FERRITES		IC301	36604-134-511	NYLON 66 VO NTR
L404	34047-019-060	3.5X6X1.0	FBT1	36633-101-910	ABS VO GRAY ALL MODEL
L803	34047-019-060	3.5X6X1.0	FBT3	36635-112-010	NYLON 6.6 DATL-600
L804	34047-019-060	3.5X6X1.0	H/WIRE	37148-530-083	2S-3X8 FE FZB
	FILTERS		IC301	37158-230-061	2S-3X6 FE FZY
Z101	34529-700-019	F52LM	L-WRNG	38113-135-610	PASCAL SE SHEET TO.2
Z102	34527-700-024	SAF41MC80Z-TF01	L-WAR	38114-604-910	ART PAPER 90
Z201	34527-460-001	TPS4.5MCTF21	H/S-V	38114-691-210	ART PAPER 120(S) P58SC
**Z601	B1243-0071	BP 4.5M SFSH4.5MCB-TF21	DOOR	38114-698-710	TETTRONE PAPER REMOCON
Z602	34527-460-064	CDA4.5ME30 TF21	L-GUID	38114-699-710	ART PAPER 90(S)
	CRYSTALS			ASSY-H/SINK VERT	
X501	34539-013-010	HC-18/U(3.579545MHZ)	**3H82-00360Y000	35684-121-410, KA2131	
X901	34537-001-003	4.0MHZ	**IC301	32119-102-300	KA 2131
	RESONATOR		H/SINK	35684-121-410	SPC-1 T1.0 FTZ (S.N.A)
x40 1	34539-300-006	CSB503F5	S CREW	37158-230-061	2S-3X6 FE FZY (S.N.A)
	FUSE			ASSY-H/SINK VERT(HORI)	
**FUSE	34709-087-020	T/L 250V 4A 20M/M	**3H82-00360Y003	35684-121-410, KSD5072YI	
	TUNER		**Q402	32139-410-020	KSD5072YDI
**H901	A1292-0040	TECC1880PA09C(S) 181CH	H/SINK	35684-121-410	SPC-1 T1.0 FTZ (S.N.A)
	SOCKET-CRT		S CREW	37158-230-081	2S-3X8FE FZY (S.N.A)
**V999	A3047-0010	ISHS09SI P125.5 HI-FOCUS	WASHER	37334-105-910	SPC-1 T1.0 FZY-1 (S.N.A)
	MISCELLANEOUS			ASSY-H/SINK POWER	
S-BOX	32079-0033-000	100PFX470PF1/0MM 4KV	**3H83-00780Y000	33112-0017-070	STR50 10:
PC801	33053-817-080	DW-006/MSP-107, SPC-2	**Q801	32119-910-003	STR50103A LF501
CN81A	33054-834-018	P1XP1 D/F/ 161 #22 400	H/SINK	31122-0017-070	A6063 EXTR. WHT (S.N.A)
CN01	33058-372-016	B10XB108X2F400	S CREW	37158-230-101	2S-3X10 FE FZY (S.N.A)
EYE-P	33104-107-210	BST 2. X .0		ASSY-ACCESSORY	
JA01	A3040-0 134	P13.5 UL-PJ 1P MONO-12.5	MACH/T	32759-115-050	R300-R75 CSA
JA02	A3040-0135	P13.5 UL-PJ 1P MONO-12.5	SVC/N	38134-379-010	ART PAPER 100
CN81	33124-111-100	1P AUTO	I/B	38134-454-310	W/P 120(S) EXP STANDARD
CN81A	33124-111-100	1P AUTO	PE-BAG	38653-108-161	HDPE TO.015 400X230 NO
CN89	33124-111-100	1P AUTO	ROD/A	A1262-0003	4S DO DIPOLE 620MM BRN
GT7	33124-111-100	1P AUTO		ASSY-CRT	
GT8	33124-111-100	1P AUTO	**CRT	32019-255-113	A48KRD82X/51GGB95X
PA08	33124-111-100	1P AUTO	**D/Y	32439-310-029	DSE-1992LLJ 1)
TBC	33124-111-100	1P AUTO	SP-DY	33309-0020-000	NEOPLENE 60 BLK W 12MM
F801	33167-001-001	PFC 5000-0202	**C/Y	A1155-0003	NY-291, PI29.1
				ASSY-SPEAKER	
			**3Y73-20051-010	SAMEX ONLY 50628 DUAL	
			LEAD/C	33058-003-016	S3(2)/F/400

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
LEAD/C	33058-003-016	S3(2)/F/400			PGSISTOR
**SPK	A1300-0033	3W 160HM 90X50MM 05F14	**R801	A1332-0016	2C18R DEGAUSS180HM 220
ASSY-TRANSMITTER			MODULE REMOCON		
	*3F14-00034-900	TM34 RM238 33E S/S	PRE-AM32199-411-002SR-5CP		
CT-5062V/1MACX(OPTION)			MISCELLANEOUS		
BUYER : MABUHAY ('94.11.07)			EYE-P 33104-107-210 BST 2.8X2.0		
ASSY-PWB MAIN			GT-PIN 33124-205-001 OM		
	*3X30-02480Y120	CT-5062V/1MACX (S.N.A)	CN89 33124-205-003 2P 10MM		
RESISTORS			PA08 33124-205-007 4P 6-12.5-14MM		
J106	31018-177-223	RD 1/8T 22K-J	FBI/C 36633-101-910 ABS VO GRAY ALL MODEL		
**R400	31049-315-290	RS 2P 330-J	ASSY-H/S, VERT		
R409	31018-177-153	RD 1/8T 15K-J	*3Y82-70058-010 31124-0014-000,KA2131		
**R410	31049-175-682	RM 1/8T 6.8K-F	ASSY-H/S,VERT(HORI)		
**R411	31047-351-273	RM 1/2T 127K-F	*3Y82-70060-010 31124-0014-000,RSD5072		
R412	31018-377-104	RD 1/2T 100K-J	ASSY-H/&POWER		
R413	31018-377-474	RD 1/2T 470K-J	*3Y83-70029-010 31122-0017-070,STR5010		
**R417	31059-428-047	RF 1P 0.47-K	ASSY-SPEAKER		
**R425	31046-567-750	RS 2T 75-J AUTO	*3Y73-00012-010 5902BR3W(2),L400,WIRE		
**R425A	31046-567-750	RS 2T 75-J AUTO	LEAD/C 33058-003-016 S3(2)/F/00		
R961	31018-177-681	RD 1/8T 680-J	**SPK 34209-169-140 5902B 2R 8R 2W		
**RV002	31059-002-040	RF 1/2P 68-J	ASSY-ACCESSORY		
RV039	31018-177-561	RD 1/8T 560-J	I/B 34709-0011-000W/P120(G)CT-3362VENG		
CAPACITORS					
BOT	31417-901-400	CK45(T) B2KV 561-K			
BOT	31417-767-104	CK45(T) B2KV 102-K			
C153	31607-402-200	CE04W TAPG 50V 0.47M			
C403	31507-127-017	ECO B1 H 6825 F3'			
C411	31417-109-140	CK45 TAPG F 50V 103-Z			
C454	31607-401-450	CE04W TAPG 16V 33M			
C455	31607-403-580	CE04W TAPG 315V 2.2M-M			
**CN901	31497-009-440	EXF-FP5 331MDV(6P 331)			
**CN902	31497-009-350	EXF-FP7 331MDV(8P 331)			
**CN903	31497-009-430	EXF-FP3 331MDV(4P 331)			
**CN904	31497-009-360	EXF-FP8 331MDV(9P 331)			
TRANSISTOR					
**Q403	32137-401-530	KSA 539-Y(TAPG)/YTAM			
DIODES					
D400	B4102-0046	RGP10J-5701 600V 45A 250			
D402	32167-201-170	TVR10G(TAPG)			
D801	32167-201-650	ERC13-08V1(TAPG)			
D802	32167-201-650	ERC13-08V1(TAPG)			
D803	32167-201-650	ERC13-08V1(TAPG)			
D804	32167-201-650	ERC13-08V1V1(TAPG)			
DV003	32167-406-480	1N4148 TAPG			
ZD403	32167-408-080	EQA02-06D/MTZ6.2B(TAPG)			
DEGAUSING-COIL					
**D-COIL	A1149-0011	20" 150HM T70 L2300MM			

2-4. Electrical Parts List

ABBREVIATIONS : CC C-CERAMIC
 CE C-ELECTROLYTIC
 CFS C-M, POLYESTER
 CR C-CERAMIC, HK
 CQ C-POLYPROPYLENE, POLYESTER
 CS C-TANTALUM, SOLID

RC R-COMPOSITION
 RD R-CARBON
 RF R-FUSIBLE
 RM R-METAL, FILM
 RP R-CEMENT WIRE
 RS R-METAL, OXIDE

NOTE : The items with "*" are usually out of stock since they are seldom required for the routine service. There may be some anticipated delay when you order these items.

S.N.A. = Service Not Available , L/C = Local Purchase

The components identified by mark "*" are critical for safety. Replace only with Supplier part number specified.

When indicating parts location number, Please include the PWB names
 (PWB = Printed Writing Board)

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
ASSY-PWB MAIN BUYER:CORRIPIO('94.07.20)					
*3T30-02480-120 CT-5062V/1CORX, CKC50HM					
PWB	36029-0146-000	T1.6 W330 L245 (S.N.A)			
RESISTORS					
JO48	31018-177-102	RD 1/8T 1K-J	R203	31018-177-221	RD 1/8T 220-J
JO49	31018-177-102	RD 1/8T 1K-J	R206	31018-177-821	RD 1/8T 820-J
JO55	31018-177-563	RD 1/8T 56K-J	R208	31018-177-562	RD 1/8T 5.6K-J
5131	31018-177-221	RD 1/8T 220-J	R209	31018-177-683	RD 1/8T 68K-J
J132	31018-177-221	RD 1/8T 220-J	R210	31018-177-334	RD 1/8T 330K-J
5133	31018-177-221	RD 1/8T 220-J	R214	31018-177-391	RD 1/8T 390-J
R101	31018-177-101	RD 1/8T 100-J	R215	31018-377-471	RD 1/2T 470-J
R102	31018-177-562	RD 1/8T 5.6K-J	**R224	31046-567-101	RS 2T 100-J(AUTO)
R103	31018-177-122	RD 1/8T 1.2K-J	**R225	31046-567-220	RS 2T 22-J(AUTO)
R104	31018-177-330	RD 1/8T 33-J	R301	31018-177-331	RD 1/8T 330-J
R105	31018-177-681	RD 1/8T 680-J	R302	31018-377-224	RD 1/2T 220K-J
R106	31018-177-101	RD 1/8T 100-J	R303	31018-177-472	RD 1/8T 4.7K-J
R107	31018-177-472	RD 1/8T 4.7K-J	R304	31018-177-393	RD 1/8T 39K-J
R108	31018-177-470	RD 1/8T 47-J	R305	31018-377-684	RD 1/2T 680K-J
R109	31018-177-104	RD 1/8T 100K-J	R307	31018-177-331	RD 1/8T 330-J
R110	31018-177-104	RD 1/8T 100K-J	**R308	31057-002-010	RF 1/2T 1-J
R111	31018-177-221	RD 1/8T 220-J	R309	31018-177-393	RD 1/8T 39K-J
R112	31018-177-563	RD 1/8T 56K-J	**R310	31048-363-903	RM 1/2T 390K-G
R113	31018-177-154	RD 1/8T 150K-J	R311	31018-376-124	R D 1/2T 120K-G
R114	31018-177-223	RD 1/8T 22K-J	**R314	31047-176-152	RM 1/8T 1.5K-G
R115	31018-177-333	RD 1/8T 33K-J	R315	31018-177-680	RD 1/8T 68-J
R116	31018-177-102	RD 1/8T 1K-J	R316	31018-177-682	RD 1/8T 6.8K-J
R117	31018-177-391	RD 1/8T 390-J	R317	31018-277-339	RD 1/4T 3.3-J
R118	31018-177-221	RD 1/8T 220-J	**R317	A1000-0398	RD 1/2 T 3R3-J
R120	31018-177-102	RD 1/8T 1K-J	R320	31018-177-333	RD 1/8T 33K-J
R121	31018-177-271	RD 1/8T 270-J	**R401	31046-567-562	RS 2T 5.6K-J(AUTO)
R122	31018-177-223	RD 1/8T 22K-J	**R401A	31046-567-272	RS 2T 2.7K-J(AUTO)
R123	31018-177-822	RD 1/8T 8.2K-J	R402	31018-177-272	RD 1/8T 2.7K-J
R124	31018-177-562	RD 1/8T 5.6K-J	R403	31018-177-332	RD 1/8T 3.3K-J
R201	31018-177-162	RD 1/8T 1.6K-J	R404	31018-177-331	RD 1/8T 330-J
R202	31018-177-202	RD 1/8T 2K-J	R405	31018-177-681	RD 1/8T 680-J
			R406	31018-377-752	RD 1/2T 7.5K-J
			R406A	31018-377-822	RD 1/2T 8.2K-J
			**R407	31046-567-332	RS 2T 3.3K-J(AUTO)
			R408	31018-377-122	RD 1/2T 1.2K-J
			R408A	31018-377-272	RD 1/2T 2.7K-J
			**R414	31057-477-109	RF 1T 10-J/RF 1S 1.0-J
			**R415	31046-467-102	RS 1T 1K-J(AUTO)
			**R416	31049-375-154	RM 1/2T 150K-F

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
**R417	31057-201-025	RF 1T 0.47-K/RF 1S 0.47	R902	31018-377-120	RD 1/2T 12-J
**R418	31049-276-102	RM 1/4T 1K-J	**R904	31046-567-123	RS 2T 12K-J (AUTO)
**R419	31046-567-332	RS 2T 3.3K-J (AUTO)	**R905	31046-567-123	RS 2T 12K-J (AUTO)
R421	31018-377-183	RD 1/4T 18K-J	R906	31018-177-752	RD 1/8T 7.5K-J
**R425	31046-567-750	RS 2T 75-J AUTO	R907	31018-177-103	RD 1/8T 10K-J
**R425A	31046-567-750	RS 2T 75-J AUTO	R908	31018-377-152	RD 1/2T 1.5K-J
R444	31018-377-330	RD 1/2T 33-J	R909	31018-377-752	RD 1/2T 7.5K-J
**R445	A1000-0660	RD 1/2T (S) R39-K 0.39R	R910	31018-377-752	RD 1/2T 7.5K-J
R502	31018-177-101	RD 1/8T 100-J	R911	31018-177-103	RD 1/8T 10K-J
R508	31018-377-514	RD 1/2T 510K-J	R912	31018-177-682	RD 1/8T 6.8K-J
R510	31018-177-561	RD 1/8T 560-J	R913	31018-177-223	RD 1/8T 22K-J
R511	31018-177-561	RD 1/8T 560-J	R914	31018-177-560	RD 1/8T 56-J
R512	31018-177-561	RD 1/8T 560-J	R915	31018-177-823	RD 1/8T 82K-J
R513	31018-377-395	RD 1/2T 3.9M-J	R916	31018-177-823	RD 1/8T 82K-J
R516	31018-377-471	RD 1/2T 470-J	R917	31018-177-823	RD 1/8T 82K-J
R517	31018-177-222	RD 1/8T 2.2K-J	R918	31018-177-823	RD 1/8T 82K-J
R518	31018-177-272	RD 1/8T 2.7K-J	R919	31018-177-823	RD 1/8T 82K-J
R530	31018-177-101	RD 1/8T 100-J	R920	31018-177-823	RD 1/8T 82K-J
R531	31018-177-151	RD 1/8T 150-J	R921	31018-177-103	RD 1/8T 10K-J
R532	31018-177-151	RD 1/8T 150-J	R924	31018-177-823	RD 1/8T 82K-J
R533	31018-177-151	RD 1/8T 150-J	R925	31018-177-153	RD 1/8T 15K-J
R534	31018-177-102	RD 1/8T 1K-J	R926	31018-177-102	RD 1/8T 1K-J
R535	31018-177-102	RD 1/8T 1K-J	R931	31018-177-243	RD 1/8T 24K-J
R536	31018-177-102	RD 1/8T 1K-J	R933	31018-177-222	RD 1/8T 2.2K-J
**R537	31046-567-153	RS 2T 15K-J (AUTO)	R934	31018-177-333	RD 1/8T 33K-J
**R538	31046-567-153	RS 2T 15K-J (AUTO)	R935	31018-177-153	RD 1/8T 15K-J
**R539	31046-567-153	RS 2T 15K-J (AUTO)	R937	31018-177-113	RD 1/8T 11K-J
**R540	31028-328-472	RC 1/2T 4.7K-K	**R939	31046-567-820	RS 2T 82-J (AUTO)
**R541	31028-328-472	RC 1/2T 4.7K-K	R940	31018-177-513	RD 1/8T 51K-J
**R542	31028-328-472	RC 1/2T 4.7K-K	R941	31018-177-102	RD 1/8T 1K-J
R543	31018-177-472	RD 1/8T 4.7K-J	R942	31018-177-123	RD 1/8T 12K-J
R544	31018-377-331	RD 1/2T 330-J	R944	31018-177-273	RD 1/8T 27K-J
**R545	31057-201-018	RF 2T 1.8-J/RF 2S 1.8-J	R946	31018-177-243	RD 1/8T 24K-J
R546	31018-177-472	RD 1/8T 4.7K-J	R947	31018-177-393	RD 1/8T 39K-J
R547	31018-377-331	RD 1/2T 330-J	R949	31018-177-363	RD 1/8T 36K-J
R548	31018-377-331	RD 1/2T 330-J	R952	31018-177-102	RD 1/8T 1K-J
R549	31018-177-472	RD 1/8T 4.7K-J	R953	31018-177-103	RD 1/8T 10K-J
**R599	31046-567-470	RS RF 2T 470-J (AUTO)	R956	31018-177-202	RD 1/8T 2K-J
**R600	31057-577-561	RS RF 2T 560-J (AUTO)	R957	31018-177-102	RD 1/8T 1K-J
R601	31018-177-681	RD 1/8T 680-J	R958	31018-177-331	RD 1/8T 330-J
R602	31018-177-102	RD 1/8T 1K-J	R960	31018-177-472	RD 1/8T 4.7K-J
R603	31018-177-102	RD 1/8T 1K-J	R961	31018-377-681	RD 1/2T 680-J
R604	31018-177-512	RD 1/8T 5.1K-J	R962	31018-177-681	RD 1/8T 680-J
R605	31018-177-202	RD 1/8T 2K-J	R964	31018-177-682	RD 1/8T 6.8K-J
R606	31018-177-622	RD 1/8T 6.2K-J	R965	31018-177-122	RD 1/8T 1.2K-J
R607	31018-377-274	RD 1/2T 270K-J	R966	31018-177-183	RD 1/8T 18K-J
**R608	31046-467-123	RS 1T 12K-J (AUTO)	R967	31018-177-272	RD 1/8T 2.7K-J
**R699	31046-467-220	RS 1T 22-J (AUTO)	R968	31018-177-822	RD 1/8T 8.2K-J
**R802	31036-787-339	RW 10H 3.3-J ST	R970	31018-177-821	RD 1/8T 820-J
R803A	31018-377-224	RD 1/2T 220K-J	R971	31018-177-821	RD 1/8T 820-J
R803B	31018-377-224	RD 1/2T 220K-J	R972	31018-177-821	RD 1/8T 820-J
R804	31018-377-221	RD 1/2T 220-J	R973	31018-177-332	RD 1/8T 3.3K-J
R805	31018-377-229	RD 1/2T 2.2-J	R974	31018-177-332	RD 1/8T 3.3K-J
**R808	31057-002-010	RF 1/2T 1-J	R975	31018-177-332	RD 1/8T 3.3K-J
R888A	31018-377-514	RD 1/2T 510K-J	R976	31018-177-472	RD 1/8T 4.7K-J
R901	31018-177-102	RD 1/8T 1K-J	R981	31018-177-333	RD 1/8T 33K-J
			R982	31018-177-152	RD 1/8T 1.5K-J

Loc No	Supplier Parts No	Specification
**R990	31046-567-123 RS	2T 12K-J(AUTO)
R991	31018-177-102 RD	1/8T 1K-J
R992	31018-177-102 RD	1/8T 1K-J
R993	31018-177-102 RD	1/8T 1K-J
R994	31018-177-102 RD	1/8T 1K-J
R995	31018-177-102 RD	1/8T 1K-J
R999	31018-177-103 RD	1/8T 10K-J
RC15	31018-177-100 RD	1/8T 10-J
RC16	31018-177-100 RD	1/8T 10-J
RC17	31018-177-100 RD	1/8T 10-J
RJ106	31018-177-223 RD	1/8T 22K-J
RJ134	31018-177-104 RD	1/8T 100K-J
RV001	31018-377-680 RD	1/2T 68-J
**RV002	31057-002-040 RF	1/2T 68-J
RV003	31018-177-154 RD	1/8T 150K-J
RV004	31018-177-563 RD	1/8T 56K-J
RV005	31018-177-153 RD	1/8T 15K-J
RV006	31018-177-331 RD	1/8T 330-J
**RV007	31028-328-475 RC	1/2T 4.7M-K
RVO 10	31018-177-750 RD	1/8T 75-J
RV011	31018-177-752 RD	1/8T 7.5K-J
RVO 12	31018-177-222 RD	1/8T 2.2K-J
RV013	31018-177-470 RD	1/8T 47-J
RV021	31018-177-681 RD	1/8T 680-J
RV022	31018-177-471 RD	1/8T 470-J
RV023	31018-177-102 RD	1/8T 1K-J
RV024	31018-177-622 RD	1/8T 6.2K-J
RV025	31018-177-103 RD	1/8T 10K-J
RV026	31018-177-121 RD	1/8T 120-J
RV027	31018-177-132 RD	1/8T 1.3K-J
RV028	31018-177-183 RD	1/8T 18K-J
RV029	31018-177-333 RD	1/8T 33K-J
RV030	31018-177-302 RD	1/8T 3K-J
RV031	31018-177-822 RD	1/8T 8.2K-J
RV032	31018-177-393 RD	1/8T 39K-J
RV034	31018-177-102 RD	1/8T 1K-J
RV035	31018-177-221 RD	1/8T 220-J
RV036	31018-177-123 RD	1/8T 12K-J
RV037	31018-177-183 RD	1/8T 18K-J
RV038	31018-177-302 RD	1/8T 3K-J
RV039	31018-377-561 RD	1/2T 560-J
RV040	31018-177-152 RD	1/8T 1.5K-J
RV041	31018-177-472 RD	1/8T 4.7K-J
VARIABLE RESISTORS		
VR101	31249-128-005 EVN DJA	A03 B53
VR203	31249-128-008 EVN DJA	A03 B54
VR301	31249-128-006 EVN DJA	A03 B22
VR401	31249-128-006 EVN DJA	A03 B22
VR531	31249-128-006 EVN DJA	A03 B22
VR532	31249-128-006 EVN DJA	A03 B22
VR533	31249-128-005 EVN DJA	A03 B53
VR534	31249-128-005 EVN DJA	A03 B53
VR535	31249-128-005 EVN DJA	A03 B53
VRV01	31249-128-004 EVN DJA	A03 B13
CAPACITORS		

Loc No	Supplier Parts No	Specification
C101	31417-109-100 CK45 TAPG F 50V	102-Z
C102	31417-109-100 CK45 TAPG F 50V	102-Z
C103	31417-109-140 CK45 TAPG F 50V	103-Z
C105	31417-109-140 CK45 TAPG F 50V	103-Z
C106	31417-104-290 CK45 TAPG B 50V	472-K
C107	31407-105-660 CC45 (T) CH 50V	101-J
C108	31407-105-660 CC45 (T) CH 50V	101-J
C110	31417-109-140 CK45 TAPG F 50V	103-Z
C111	31507-127-007 ECQ B1 H 1535 F3	
C112	31407-105-110 CC45 TAPG CH 50V	120-J
C114	31417-109-140 CK45 TAPG F 50V	103-Z
C151	31607-402-240 CE04W TAPG 50V	4.7M
C152	31607-402-240 CE04W TAPG 50V	4.7M
C153	31607-402-200 CE04W TAPG 50V	0.47M
C154	31607-401-510 CE04W TAPG 16V	10000-M
C155	31607-402-260 CE04W TAPG 50V	22M-M
C156	31607-401-500 CE04W TAPG 16V	470M-M
C201	31407-105-660 CC45 (T) CH 50V	101-J
C202	31407-105-090 CC45 (T) CH 50V	100-C
C251	31607-401-430 CE04W TAPG 25V	10M
C252	31607-401-430 CE04W TAPG 25V	10M
C253	31507-127-006 ECQ B1 H 1035 F3	
C254	31607-803-730 CE04W TAPG 50V	4.7M-NP
C255	31507-127-006 ECQ B1 H 1035 F3	
C301	31507-127-001 ECQ B1 H 1525 F3	
C302	31507-127-023 ECQ B1 H 1225 F3	
C303	31507-127-016 ECQ B1 H 4725 F3	
C304	31507-127-010 ECQ B1H 4735 F3	
C305	31507-127-011 ECQ B1H 6835 F3	
C307	31507-127-010 ECQ B1H 4735 F3	
C309	31507-127-006 ECQ B1 H 1035 F3	
C311	31417-468-681 CK45 TAPG B500V	681-K
C320	31507-127-011 ECQ B1H 683J F3	
C321	31507-127-011 ECQ B1H 6835 F3	
C351	31607-902-250 CE04W TAPG 50V	0.22M
c352	31607-402-100 CE04W TAPG 35V	100M-M
c353	31607-403-970 CE04W TAPG 25V	1000M-M
C354	31607-402-250 CE04W TAPG 50V	10M
C355	31607-402-130 CE04W TAPG 35V	470M-M
C356	31607-402-570 CE04W TAPG 50V	1M
C357	31607-402-570 CE04W TAPG 50V	1M
C401	31507-127-009 ECQ B1 H 3335 F3	
C402	31507-127-010 ECQ B1H 473J F3	
C403	31507-127-017 ECQ B1 H 6825 F3	
C404	31417-109-100 CK45 TAPG F 50V	102-Z
C405	31417-106-170 CK45 TAPG B 500V	222-K
C406	31417-106-090 CK45 TAPG B 500V	471-K
*C407	A1102-0214 CF 922P 1.6KV T 742-H BU	
C409	31607-401-670 CE04W TAPG 25V	47M
C410	31607-401-670 CE04W TAPG 25V	47M
*C412	31517-390-502 CFS922M TAPG 250V	104-J
*C413	31517-333-334 CFS 922M TAPG 200V	334-J
C414	31417-106-090 CK45 TAPG B 500V	471-K
c451	31607-401-460 CE04W TAPG 16V	47M
C452	31607-402-210 CE04W TAPG 50V	1M
C456	31607-401-710 CE04W TAPG 25V	470M-M
C458	31607-403-490 CE04W TAPG 250V	10M-M

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
C497	31417-318-152	CK45 TAPG B 50V 152-K	C954	31607-401-140	CE04W TAPG 6.3V 1000M-M
C499	31417-468-561	CK45 TAPG B 500V 561-K	C955	31607-401-460	CE04W TAPG 16V 47M
C501	31407-105-260	CC45(T) CH 50V 470-J	C956	31607-402-200	CE04W TAPG 50V 0.47M
C502	31407-106-760	CC45(T) RH 50V 151-J	C957	31607-401-430	CE04W TAPG 25V 10M
C504	31417-109-140	CK45 TAPG F 50V 103-Z	C958	31607-401-430	CE04W TAPG 25V 10M
C506	31407-105-180	CC45(T) CH 50V 220-J	C959	31607-401-430	CE04W TAPG 25V 10M
C507	31507-127-007	ECQ B1 H 1535 F3	C960	31607-402-250	CE04W TAPG 50V 10M
C508	31417-104-070	CK45 TAPG B 50V 271-K	C961	31607-402-240	CE04W TAPG 50V 4.7M
C509	31417-104-070	CK45 TAPG B 50V 271-K	C962	31607-401-430	CE04W TAPG 25V 10M
C510	31417-104-070	CK45 TAPG B 50V 271-K	C963	31607-401-430	CE04W TAPG 25V 10M
C531	31417-318-152	CK45 TAPG B 50V 152-K	C964	31607-401-430	CE04W TAPG 25V 10M
C532	31417-318-152	CK45 TAPG B 50V 152-K	C965	31607-402-210	CE04W TAPG 50V 1M
C533	31417-318-152	CK45 TAPG B 50V 152-K	C966	31417-104-070	CK45 TAPG B 50V 271-K
*C534	A1100-0783	CK 45F 3KV 103-Z CK45FZ:	C970	31607-401-430	CE04W TAPG 25V 10M
*C534	A1100-0783	CK 45F 3KV 103-Z CK45FZ:	C971	31507-127-016	ECQ B1 H 4725 F3
C535	31417-109-100	CK45 TAPG F 50V 102-Z	C973	31507-127-012	ECQ B1(V1)H 1045 F3(Z3)
C536	31417-109-100	CK45 TAPG F 50V 102-Z	**CA101	31467-001-001	CK45P TAPG E400V 222-M
C537	31417-109-100	CK45 TAPG F 50V 102-Z	**CA102	31467-001-001	CK45P TAPG E400V 222-M
C551	31607-402-170	CE04W TAPG 50V 0.1U-L,L	**CN901	31497-009-440	EXF-FP5 331MDV(6P 331)
C553	31607-402-230	CE04W TAPG 50V 3.3M	**CN902	31497-009-350	EXF-FP7 331MDV(8P 331)
C554	31607-402-220	CE04W TAPG 50V 2.2M	**CN903	31497-009-430	EXF-FP3 331MDV(4P 331)
C555	31607-401-670	CE04W TAPG 25V 47M	**CN904	31497-009-360	EXF-FP8 331MDV(9P 331)
C556	31607-402-210	CE04W TAPG 50V 1M	CV002	31417-109-140	CK45 TAPG F 50V 103-Z
C557	31607-402-210	CE04W TAPG 50V 1M	CV003	31417-106-090	CK45 TAPG B 500V 471-K
C558	31417-109-140	CK45 TAPG F 50V 103-Z	**CV005	31467-001-001	CK45P TAPG E400V 222-M
C560	31607-401-690	CE04W TAPG 25V 220M-M	CV051	31607-401-430	CE04W TAPG 25V 10M
C561	31607-401-430	CE04W TAPG 25V 10M	CV052	31607-401-700	CE04W TAPG 25V 330M-M
C601	31407-106-150	CC45(T) RH 50V 150-J	CV053	31607-401-670	CE04W TAPG 25V 47M
C602	31507-127-006	ECQ B1 H 1035 F3	CV055	31607-401-460	CE04W TAPG 16V 47M
C603	31417-109-140	CK45 TAPG F 50V 103-Z	**CV059	A1104-0521	CE 04 -40/85 50V T 330-I
C606	31417-106-010	CK45 TAPG B 500V 101-K	CV060	31607-401-430	CE04W TAPG 25V 10M
C607	31417-104-330	CK45 TAPG B 50V 331-K	CV061	31607-803-730	CE04W TAPG 50V 4.7M-NP
C651	31607-401-430	CE04W TAPG 25V 10M	I C		
C655	31607-403-210	CE04W TAPG 160V 10M-M	IC101	32119-102-131	CXA1110BSI
C656	31607-402-250	CE04W TAPG 50V 10M	IC501	32119-102-020	LA7625
C657	31607-403-210	CE04W TAPG 160V 10M-M	**IC901	B4002-0302	Z8622704PSC-R1006/R1127
C701	31607-402-470	CE04W TAPG 50V 47M-M(FR)	ICV01	32109-410-270	TC4066BP
*C777	31467-001-001	CK45P TAPG E400V 222-M	TRANSISTORS		
*C801	31516-002-140	ECQ-E2A 224MN86 (TAPG)	Q101	32137-301-050	KSC 1674(TAPG)
C803	31407-052-709	CC4(T) CH 50V 070-C	Q201	32137-401-530	KSA 539-Y(TAPG)/YTAM
C812	31417-767-102	CK45(T) B2KV 102-K	Q203	32137-103-430	XSA 642-0(TAPG)
C850	31507-127-026	ECO-V1H 4745 Z3	**Q401	32137-301-530	KSC 2330-0(TAPG)
C851	31607-403-250	CE04W TAPG 160V 100M-M	Q501	32137-301-560	KSC 2331-Y(TAPG)
*C852	31606-403-840	CE04W 400V 220M-M 30X40	Q531	32137-301-530	KSC 2330-0(TAPG)
C900	31607-401-690	CE04W TAPG 25V 220M-M	Q532	32137-301-530	KSC 2330-0(TAPG)
C901	31417-468-681	CK45 TAPG B 500V 681-K	Q533	32137-301-530	KSC 2330-0(TAPG)
C902	31417-109-100	CK45 TAPG F 50V 102-Z	Q534	32137-301-530	KSC 2330-0(TAPG)
C905	31407-105-180	CC45(T) CH 50V 220-J	Q535	32137-301-530	KSC 2330-0(TAPG)
C906	31407-105-180	CC4(T) CH 50V 220-J	Q536	32137-301-530	KSC 2330-0(TAPG)
C907	31407-105-270	CC4(T) CH 50V 300-J	Q601	32137-301-540	KSC 2330-Y(TAPG)
C908	31417-109-100	CK45 TAPG F 50V 102-Z	**Q602	A4052-0055	KSA940 25W -1.5A 4MHZ
C909	31407-105-150	CC45 T)CH 50V 160-J	**Q603	A4052-0059	KSC2073 25W 1.5A 4MHZ
C912	31407-105-660	CC45(T)CH 50V 101-J	Q901	32137-301-560	KSC 2331-Y(TAPG)
C919	31417-109-140	CK45 TAPG F 50V 103-Z	Q905	32137-301-720	KSC 815-Y TAPG /YTAM
C951	31507-127-012	ECO I(V1)H 1045 F3(Z3)	Q907	32137-301-720	KSC 815-Y TAPG /YTAM
C952	31607-401-430	CE04W TAPG 25V 10M			
C953	31607-401-290	CE04W TAPG 10V 220U			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
Q909	32137-301-720	KSC 815-Y TAPG)/YTAM	D915	32167-406-480	1N4148 TAPG
Q910	32137-301-720	KSC 815-Y TAPG)/YTAM	D916	32167-406-480	1N4148 TAPG
Q911	32137-301-720	KSC 815-Y TAPG)/YTAM	D971	32167-406-480	1N4148 TAPG
Q912	32137-301-720	KSC 815-Y (TAPG))/YTAM	DA00	32167-406-080	MTZ 5.1B
Q923	32137-301-720	KSC 815-Y (TAPG))/YTAM	DV002	32167-201-170	TVR10G(TAPG)
QV001	32137-301-720	KSC 815-Y (TAPG))/YTAM	DV003	32167-406-480	184148 TAPG
QV002	32137-301-720	KSC 815-Y (TAPG))/YTAM	DV004	32167-406-480	1N4148 TAPG
QV003	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD501	32167-406-150	MTZ 13A
QV004	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD901	32167-406-080	MTZ 5.1B
QV005	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD902	A4106-0128	MTZ6.8A-T72 6.29
QV006	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD903	32167-406-080	MTZ 5.1B
QV007	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD904	32167-403-850	EQB 01-33(TAPG)
QV008	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD905	32167-406-130	MTZ 9.1B
QV009	32137-301-720	KSC 815-Y (TAPG))/YTAM	ZD906	32167-406-080	MTZ 5.1B
			ZD908	32167-406-150	MTZ 13A
DIODES			POSISTORS		
D2	32167-408-080	EQA02-06D/MTZ6.2BTAPG)	**R801	A1332-0016	2C18R DEGAUSS 180HM 220V
D201	32167-408-080 32167-406-480	EQA02-06D/MTZ6.21N4148TAPG	MODULE REMOCON		
D202	32167-406-480	1N4148 TAPG	PRE-AM	32196-411-002	SR-5CP ST
D203	32167-406-480	1N4148 TAPG	LED-GUIDE, ASSY		
D204	32167-201-070	1N 4003/LTIN 4003	LED01	32306-101-020	DL-G2RA
D3	32167-408-080	EQA02-06D/MTZ6.2B(TAPG)	PHOTO-COUPERS		
D301	32167-201-170	TVR10G TAPG	**PC001	32309-024-040	LTV817B
D302	32167-201-170	TVR10G TAPG	**PC002	32309-025-000	HP6N136-020 8DIP 5KV
D303	32167-406-480	1N4148 TAPG	COILS		
D304	32167-406-480	1N4148 TAPG	**D-COIL	A1149-0011	20" /150HM T70 L2300MM
D305	32167-406-480	1N4148 TAPG	L101	32427-904-918	AL02-150K(150H)
**D401	32167-201-170	TVR10G TAPG	L102	32427-904-944	AL02 R56-M
**D406	32167-201-170	TVR10G TAPG	L103	32427-904-945	AL02 R80M(0.8UH)
**D408	32167-406-480	1N4148 TAPG	L111	32427-805-840	AL03 100-K
**D409	32167-406-480	184148 TAPG	L201		
D502	32167-406-480	1N4148 TAPG	L202	32427-904-906	AL02-150K(150H)
D503	32167-406-480	1N4148 TAPG	L301	32427-803-130	10UH-K TAPG
D601	32167-406-480	1N4148 TAPG	**L401	32427-904-924	AL02-100K(10UH)
D699	32167-406-480	1N4148 TAPG	**L402	32446-705-050	195UH ST
D701	32167-207-120	1R5GU41(TAPG)	**L403	32427-904-924	AL02-100K(10UH)
**D800	32167-401-041 32167-201-650	ENC431D-10A(TAPG)	**L407	32426-226-190	82MH-K(ROBOT)
**D802	32167-201-650	ERC13-08V1(TAPG)	L501	32427-904-924	AL02-100K(10UH)
**D803	32167-201-650	ERC13-08V1(TAPG)	L532	32427-805-858	AL03 331-K
**D804	32167-201-650 32167-207-120	ERC13-08V1(TAPG)	L602	32427-805-878	AL02 220-J
**D806	32167-201-170	1R5GU41(TAPG)	**L801	32426-633-160	6MH-SQ1913 ST
**D807	32167-201-170	TVR10G(TAPG)	L901	32427-805-550	47UH-K TAPG
**D808	32167-401-850	R-2KY(TAPG)	L902	32427-904-924	AL02-100K(10UH)
D900	32167-201-170	TVR10G(TAPG)	L903	32427-904-924	AL02-100K(10UH)
D901	32167-406-480	1N4148 TAPG	LA00	32427-805-840	AL03 100-K
D902	32167-406-480	1N4148 TAPG	LA01	32427-805-840	AL03 100-K
D904	32167-406-480	1N4148 TAPG	LV01	32427-904-924	AL02+100K(10UH)
D905	32167-406-480	1N4148 TAPG	DELAY-LINES		
D906	32167-406-480	1N4148 TAPG	X201	32466-200-013	SDL401TN
D907	32167-406-480	1N4148 TAPG			
D908	32167-406-480	1N4148 TAPG			
D909	32167-201-070	1N 4003/LTIN 4003			
D913	32167-406-480	1N4148 TAPG			
D914	32167-406-480	1N4148 TAPG			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
		TRANS-FLY BACK			SILD/C 34543-130-810STPETO.25
**T444	32859-200-04	(FCM-20A025)			FBI/C 36633-101-910 ABS VO GRAY ALL MODEL
		TRANS			CLMP/W 36635-112-010 NYLON 6.6 DATL-600
L105	32707-200-014	45.75MHZ/2(7M/M)			CLMP,D 36635-112-110 NYLON 6.6 DADH-460
L106	32707-200-013	45.75MHZ(7M/M)			L-WRNG 38114-691-210 ART PAPER 120(S)P58S
T401	32846-070-006	130MH/105UH ST			ASSY-H/SINK VERT
T601	32786-550-080	200:40EM 24MM ST			*3H82-00530-000 31124-0014-000KA213
**T801	32896-001-090	P:90-260 S:95V ER354			**IC301 32119-102-300 KA 2131
**T802	32996-001-000	486UH:28.8UH ST			H/SINK 31124-0014-000 SPC-1 T1.0 FT-2 {S.N.A}
TV001	A1207-0004	EE1916 2MH 50HM ST			S CREW 37158-230-061 2S-3X6 FE FZY {S.N.A}
		CORE-FERRITES			ASSY-H/SINKVERT(HORI)
L404	34047-019-060	3.5X6X1.0			*3H82-00530-002 31124-0014-000 KSD5072Y
L803	34047-019-060	3.5X6X1.0			**Q402 32139-410-02(KSD5072YD)
L804	34047-019-060	3.5X6X1.0			H/SINK 31124-0014-000 SPC-1 T1.0 FT-2 {S.N.A}
		FILTERS			S CREW 37158-230-081 2S-3X8FE FZY {S.N.A}
Z101	34529-700-019	F52LM			WASHER 37334-105-910 SPC-1 T1.0 FZY-1 {S.N.A}
2102	34527-700-024	SAF41MC80Z-TF01			ASSY-H/SINK POWER
2201	34527-460-001	TPS4.5MCTF21			*3H83-00780-000 31122-0017-070,STR50103
Z601	B1243-0071	BP 4.5M SP5H4.5MCB-TF21			**Q801 32119-910-003STR50103ALF501
2602	34527-460-064	CDA4.5ME30 TF21			H/SINK 31122-0017-070 A6063,EXTR,WHI {S.N.A}
		CRYSTALS			S CREW 37158-230-101 2S-3X10 FE FZY {S.N.A}
X501	34537-001-002	3.579545MHZ			ASSY-POWER CORD
X901	34537-001-003	4.0MHZ			*3H64-00051-200 H/C200MM BLK-HGU EP2/NO
		RESOSATOR			**PC801 33053-817-080 DW-006/SP-10/,SPC-2
X401	34539-300-006	CSB503F5			HOLD/C 33323-0015-000 PP VO BLACK
		FUSE			ASSY-ACCESSORY
**FUSE	34709-087-020	T/L 250V 4A 20M/M			MACH/T 32759-115-050R300-R75CSA
		TUNER			ROD/A 34509-334-004 4S N/UL DIPOLE 700M/M
**H901	A1292-0040	TECC1880PA09C(S) 181CH			I/B 38134-379-010 ART PAPER 100
		SOCKET-CRT			SVC/N 38134-454-31(W/V P 120(X) EXP STANDARD
**V999	A3047-0010	ISHS09SP125.5HI-FOCUS			PE-BAC 38653-108-161 HDPE TO.015 400X230 NO
		MISCELLANEOUS			ASSY-CRT
ANT/B	32079-0033-000	100PFX470PF 100MM 4KV			**CRT 32019-255-113A48KRD82X151GGB95X
JA01	A3040-0134	P13.5UL-PJ1P MONO-12.5			**D/Y 32439-310-029 DSE-1992L1(1)
JA02	A3040-0135	P13.5UL-PJ1P MONO-12.5			SP-DY 33309-0020-000NEOPLENE VO BLK W 12MM
CN81A	33054-834-014	P1XP1/DIW/500			**C/Y A1155-0003 NY-291 P129.1
CN01	33058-372-016	B10XB10/F/400			ASSY-TRANSMITTER
EYE-P	33104-107-210	BST 2.8X2.0			*3F14-00034-900 TM34 RM238 33 E S/S BRI
GT-PIN	33124-111-100	1P AUTO			ASSY-SPEAKER
F801	33167-001-001	PFC 5000-0202			*3H73-20400-012 05F14BRA*2, L400, W800
PA11	33347-108-310	67094-003 (AUTO)			LEAD/C 33058-003-016 S(2)/F/400
SW201	33546-007-010	JRS-1301-1/KLR-1301A			**SPK 34209-200-020 05 F14BRA, 8R, 3W
SW02	33596-001-001	JTR-1104 ST			
SW901	33606-101-011	KPT-1112 ST			
SW902	33606-101-025	KPT-2104-21 ST			
NT0061	34503-0100-000	TETRONE PAPER 90(G) ALL			

Loc No	Supplier Parts No	Specification	Loc No	Supplier Parts No	Specification
CT-5062V/5RASX(OPTION) BUYER:RAYTON('94.07.25) ASSY-PWB MAIN *3T30-02480-350 CT-5062V/1RASX,CKC50HM RESISTORS R946 31018-177-203 RD 1/8T 20K-J R413 31018-377-474 RD 1/2T 470K-J MISCELLANEOUS LED/G 36602-105-510 ADS HB NTR V2 MODEL ASSY-ACCESSORY I/B 34709-0011-000 W/P120(G) CT-3362V ENG					